

3-Outlet Power Stake

BNC-60/U207

OPERATING INSTRUCTIONS

1. Align the arrows on the two ground stake parts and insert the lower stake part into the other one to make one long stake. You'll hear a "click" when the two parts are correctly connected.
2. Firmly attach the long stake to the bottom of power outlet.
3. Push the stake into the ground leaving 8 inches exposed.
4. Plug the power outlet into an outdoor rated, GFCI protected, grounded outlet.
5. Attach up to 3 devices to the power stake.

SAFETY INFORMATION & SPECIFICATIONS

This is a "GROUNDED" device. The male plug contains a ground pin and is only intended for use with a three-pronged grounded outlet.

This power stake is for use with a 125 VAC power source.

125VAC / 60Hz

DO NOT ATTACH A DEVICE THAT EXCEEDS THE UNIT RATINGS:

- 13A / 1625W Resistive (General Purpose) and Tungsten (Incandescent)
- 1/2 HP (Horsepower Motor)

WARNING: RISK OF ELECTRIC SHOCK

- Keep children away
- Unplug before cleaning
- Fully insert plug
- Do not use near standing water.

RISK OF FIRE

- Do not use to control appliances that contain heating elements (cooking appliances, heaters, irons, etc.)
- Do not exceed electrical ratings.

CENTURY PRODUCTS INC.
Customer Service Assistance: 1.909.592.1881
Email: support@bn-link.com
Web: www.bn-link.com
Hours: 9AM - 5PM PST, Mon - Fri
Designed in California, Made in China