





















<div></div> <div>Smart Color String Lights</div> <div>-1-</div>	<div>Trouble reading this guide? Use this link for PDF version <a href="http://www.bn-link.com">www.bn-link.com</a></div> <div>Need Help? Email: <a href="mailto:support@bn-link.com">support@bn-link.com</a> Web: <a href="http://www.bn-link.com/ticket">www.bn-link.com/ticket</a></div> <div>-2-</div>	<div>NOTE: Hold ON/OFF button for 5 seconds while it is plugged in to restore the factory setting if you want to erase the light's current settings.</div> <div>►Light Status Light blinks every 0.5 second-Easy Mode connection Light blinks every 2 seconds- AP Mode connection</div> <div>►Parameter 125V 60Hz</div> <div>-3-</div>	<div>Linkable up to 1728 ft. and easy to install. Heavy duty 18/5 SJTW cord Working Temp: -10 ~60°C Wi-Fi Frequency: 2.4 GHz</div> <div>►Install the “Smart Life” App 1. Search for Smart Life App on App store/Google Play Store, or just scan the QR code below to download. (For iPhone, you can use build-in camera to scan the QR code. For Android, you may need barcode scanner to do that. Please confirm the App icon before</div> <div>-4-</div>	<div>downloading.) PS: You can also add this smart light to smart life app directly if you already have it on your phone, it is compatible and works the same way.</div> <div>2. Register an account and memorize the password, enter your email address or your phone number, then obtain verification code to complete the registry.</div> <div>-5-</div>	<div></div> <div>►Connect with Your Cellphone Requirements: 2.4GHz Wi-Fi network</div> <div>Please note: 1.If you only have 5GHz Wi-Fi router,you will not be able to complete the connection.</div> <div>-6-</div>	<div>2. If you are using a dual Wi-Fi router and it broadcast 2 Wi-Fi signals, make sure that your phone is connected with the 2.4GHz Wi-Fi signal, it should be the Wi-Fi signal that next to “_5G”</div> <div></div> <div>-7-</div>	<div>3. If you are using a dual-band Wi-Fi router but it broadcast only 1 Wi-Fi signal, you will have to manage your Wi-Fi router and change the settings to have 2.4GHz Wi-Fi.</div> <div></div> <div>-8-</div>	<div>---&gt; Confirm the smart light is plugged into a live outlet ---&gt; Open Smart Life app ---&gt; Choose the “+” symbol, ---&gt; Lighting (Wi-Fi) ---&gt; Input password of your 2.4 GHz Wi-Fi network and tap “Next”.</div> <div></div> <div>-9-</div>
<div></div> <div>A: For Easy Mode Connection-Light Blinks Rapidly ( Twice a second ).</div> <div>-10-</div>	<div>---&gt; Confirm the light status and tap the option “is fast blinking (0.5 s/time)” in the pop-up menu, ( If you don't see light quickly blinking, press On/Off button to reset.) ---&gt; Rename the device or tap “Done”.</div> <div></div> <div>-11-</div>	<div>B: AP Mode(Light blinks once every 2 seconds ) If the Easy mode connection failed, please remove and install the smart light into your power outlet again. When the light is blinking quickly, it is in Easy mode. Hold the power button for about 7 seconds to enter into AP mode. Once you see the light slowly blinking(every 2 seconds), you can start to try the AP mode connection,</div> <div>---&gt; Tap the option “is slowly blinking (2 s/time)” in the pop-up menu.</div> <div>-12-</div>	<div></div> <div>Connect your mobile phone to the device's hotspot</div> <div></div> <div>-13-</div>	<div>--&gt;Tap “Go to Connect” and choose Wi-Fi hotspot named “SmartLife-xxx”, then go back to Smart Life application; --&gt;Wait till successful configuration and rename the device or tap “Done”.</div> <div></div> <div>-14-</div>	<div>►Getting to Know Smart Life App</div> <div></div> <div>-15-</div>	<div>Note: edit the default names in this interface, for better management.</div> <div>►Create Automations/Groups You can create certain scenes and groups on Smart Life App, it allows you to control different smart devices in different rooms at the same time.</div> <div>-16-</div>	<div></div> <div>-17-</div>	<div>►Device Sharing If you want to give others the permission to control your smart light, you can authorize that by activating the device sharing function Go to the Smart Life app --&gt;Choose the device you want to share --&gt;Choose Edit Button --&gt;Choose “Share Device” --&gt;Add sharing--&gt;Enter his/her Smart Life account --&gt;Search and complete.</div> <div>-18-</div>

<div>►How To Connect with Amazon Alexa Requirements: 1.Amazon Alexa Device and Alexa App 2.The Smart device connected with Smart Life App 3.Smart LifeApp user ID and password.</div> <div>Add Smart Life as a “Skill” for Alexa Open Alexa app and choose Skills &amp; Games --&gt; Search for Smart Life --&gt; ENABLE TO USE --&gt; Enter the Smart Life account</div> <div>-19-</div>	<div>--&gt;Authorize to use --&gt;Choose Smart Life. And then, the devices you added on will sync to Alexa App. You can also ask Alexa to discover new devices for you in this moment.</div> <div></div> <div>-20-</div>	<div></div> <div>How to ask Alexa to turn on/off Smart Plug First, you will need to make sure the names for the device are the same on the Alexa app and on the Smart Life app. If they are not the same, Alexa will not</div> <div>-21-</div>	<div>be able to identify the device .</div> <div></div> <div>Things you can do with Alexa * Voice Control the smart device * Remote Control the smart device via Alexa App. * Add the smart device to certain groups</div> <div>-22-</div>	<div>on Alexa App.You should make sure all the smart devices' names at your home are nonrepetitive and recognizable for Alexa. For other questions about Alexa, please find out with Amazon Alexa support page, or contact us for help directly by email.</div> <div>Tips for using Alexa Voice Control Please make sure the device name you set for the smart device is unique and recognizable for Alexa voice assistant. You should make sure all the smart devices names at your home are non-repetitive and recognizable for Alexa.</div> <div>-23-</div>	<div>Voice assistant system needs the exact command to do the work.</div> <div>►How To Connect with Google Home After you've connected the smart device with the Smart Life app successfully, you can start to link them to Google Home app: Open Google Home app and find “Set up device” --&gt;Click “Works with Google” --&gt;Search Smart Life --&gt;Enter your Smart Life account --&gt;Authorize to use.</div> <div>-24-</div>	<div>After that, you will see the smart device at the home page of Google Home as “Linked to you”, but you still haven't set the device name and assign a home or a room for it.</div> <div></div> <div>-25-</div>	<div></div> <div>-26-</div>	<div></div> <div>Now click the device that “Linked to you” or open “Works with Google” again to manage your linked devices, follow the steps below and set up the device</div> <div>-27-</div>
<div>names, rooms and home for the smart device , you won't be able to voice control it before you complete that.</div> <div></div> <div>-28-</div>	<div></div> <div>►Trouble Shooting Q: Why did my phone connection fail? A: * You should try both Easy Mode and AP Mode, read page 5-page 14, make sure to follow the guide and try again.</div> <div>-29-</div>	<div>* Confirm your home Wi-Fi is 2.4GHz and that you've entered the correct password during the connection. * Remove&amp;Install the smart device to start again. Contact the customer support team for assistance if you still have problems with the connection after following the steps above. Q: Why can't I voice control the device with my Alexa/Google A: * Make sure the smart device is connected successfully on the Smart Life app. Ensure that they are working</div> <div>-30-</div>	<div>well by testing to see if you can turn the plug on and off through the app. * Make sure the same account is linked on the Smart Life as a skill on Alexa/ Google App. * Make sure your Alexa/Google device is working fine. * Check the device names that you set for this smart device, it should be non-repetitive and recognizable for voice assistant. Also, please make sure your native language is available for Alexa. If you still having trouble controlling our smart device through voice control after</div> <div>-31-</div>	<div>following all instructions, do not hesitate to contact us for help. Q: Do I need to set up the device again if I changed my router? A: Yes, you must set up the smart device again if there are any changes to the current wifi status. (i.e changing the name of the wifi, changing the router/modem). There is no need to set the device up again if you are just changing the placement of the router in the same house. Q: Why does it turns on/off or comes offline surprisingly ?</div> <div>-32-</div>	<div>A: Make sure your connection to the wifi is not interrupted. Check to see if there were any timers/schedules set for the device. If everything looks fine, reset the device and install it again on the app. Email us at <a href="mailto:support@bn-link.com">support@bn-link.com</a> if the problem still persists</div> <div>►Safety Information This device is for outdoor and indoor use Please keep the device dry and away from hot, humid, and/or other extreme environments. Please ensure that the appliance used with our device is in compliance with our</div> <div>-33-</div>	<div>product's rating. Do not attempt to disassemble the device. Be aware of the safety risks and product damage done to the device. This device meets UL94 V-0 flammability standard.</div> <div>►Warranty 30 days money-back guarantee: If you're not satisfied with this purchase, you can choose to refund this order within 30 days. 15 months warranty: * The device was used in proper technical working condition.</div> <div>-34-</div>	<div>* Failures and defects not from human errors Not covered if the device was found to be disassembled from use.</div> <div>►Contact Us Friendly reminder: Using a different app from Smart Life may lead to differences in the interface, but the functionality of the device should still be the same,</div> <div>-35-</div>	<div>For any questions or concerns about our products, please contact us at <a href="mailto:support@bn-link.com">support@bn-link.com</a></div> <div>CENTURY PRODUCTS INC. Customer Service Assistance: 1.909.592.1881 Email: <a href="mailto:support@bn-link.com">support@bn-link.com</a> Web: <a href="http://www.bn-link.com">www.bn-link.com</a> Hours: 9AM - 5PM PST, Mon - Fri Designed in California, Made in China</div> <div>-36-</div>