INSTRUCTIONS

ATHENA BOLLARD



4640.52

Please read the instructions before commencing installation

And retain for future reference.

SPECIFICATIONS:

- Fitting: Aluminum body with PC.
- Lamp types: E27 23W.
- Protection against electric shock: CLASS I requires earth connection.
- Ingress Protection: IP44. Protection against dust and water
- Ballast: Without LED Driver
- Quality/Corrosive Rating: Suitable for garden use, commercial use and indoor/outdoor applications
- Ambient temperature range: -20° to +40°

INSTALLATION INSTRUCTIONS:

▲ Electrical products can cause death, injury or damage to property. Installation of this product must be carried out by a qualified electrician, in accordance with SANS 10142. On completion of installation, ensure that the Certificate of Compliance is updated.



CAUTION: Risk of electric shock

PLEASE NOTE: The light source contained on this luminaire shall only be replaced by the manufacturer or the service agent or a similar qualified person.

Ensure mains supply is switched off.

- Fig 1. Screw out the three screws on the base Make 3 point according lamp base.
 Use a gun drill 3 holes.
 Putting plastic expansion to hole.
- Fig 2. Tighten the screws
 Open lamp plastic head
 Install bulb
 Connecting the Terminal Block
- Fig 3. Put plastic head in the lamp and tighten the screws
 Three screws fill into ground

Switch on mains supply and test the fitting.

WARNING:

- Ensure all items and screws are secure and fitted correctly.

