

# INSTRUCTIONS

## LED STRIP

**4W:** 7038.04.30.31 / 7038.04.40.31  
**8W:** 7038.08.30.31 / 7038.08.40.31  
**12W:** 7038.12.30.31 / 7038.12.40.31  
**16W:** 7038.12.30.31 / 7038.12.40.31

Please read the instructions before commencing installation and retain for future reference.

### SPECIFICATIONS:

- **Fitting:** Polycarbonate body
- **Lamp types:**
  - 4W/230V** Natural White 4000K / Warm White 3000K
  - 8W/230V** Natural White 4000K / Warm White 3000K
  - 12W/230V** Natural White 4000K / Warm White 3000K
  - 16W/230V** Natural White 4000K / Warm White 3000K
- **Protection against electric shock:** CLASS II. Does not require earth connection.
- **Ingress Protection:** IP20.
- **Ballast:** Includes LED driver.
- **Quality/Corrosive rating:**
  - Suitable for commercial use and indoor applications.
- **Ambient temperature range:** -20°C to +40°C.

### INSTALLATION INSTRUCTIONS:

**⚠** Electrical products can cause death, injury, damage to property. Installation of this product must be carried out by a qualified electrician, in accordance with SANS 10142. On completion of installation, ensure that the Certificate of Compliance is updated.

Ensure mains supply is switched off.

- Mount the clips to the surface accordingly. (Fig. 1)
- Connect the fitting to its electrical source: (Fig 3)
  - Brown (Live) - to Brown or Red
  - Blue (Neutral) - to Blue or Black
- Attach the fitting to the clips (Fig. 4)
- (remove) Ensure the end cap has properly put and Max connection power not bigger than 150W totally
  - On single installations: ensure the end cap is secured in place. (Fig. 5)
  - On linear installations: ensure the end cap is secured in place and do not exceed an installation length of 150W. (Fig. 5)
- Switch on the power supply and test the fitting (Fig. 6)

### WARNING:

- Ensure all items and screws are secure and fitted correctly.

