

Keystone Control Panel

Quick Start Guide



Initial Start-up

When your spa is first turned on, it will go into Priming mode (after displaying some configuration information). The Priming mode will last for up to 4 minutes and then the spa will begin to heat and maintain the water temperature in standard mode. You can exit Priming mode early by pressing "Temp".

Temp Set (80°F - 104°F / 26.0°C - 40.0°C)

The start-up temperature is set at 100°F/37.5°C by default. The last measured temperature is constantly displayed on the LCD.

Note that the last measured spa temperature displayed is current only when the pump has been running for at least 2 minutes.

Temp

Press the "Temp" button once to display the set temperature (it will be flashing). To change the set temperature, press "Temp" a second time before the LCD stops flashing. Each press of the "Temp" button will continue to either raise or lower the set temperature.

If the opposite direction is desired, release the "Temp" button and let the display revert to the current water temperature. Press "Temp" to display the set temperature (it will flash), and again to make the temperature change in the desired direction.

After three seconds, the LCD will automatically display the last measured spa temperature.

Jets

Press the "Jets" button once to turn the pump on or off and shift between low and high speeds. If left running, the low speed turns off after 2 hours and

the high speed turns off after 15 minutes.

The jets may activate for at least 2 minutes every half hour to detect the spa temperature, circulate the water for even heating, and circulate water to the filter. When the low speed turns on automatically, it cannot be deactivated from the panel; however, the high speed may be started.

Air

1-speed operation: on/off.

The low speed water pump automatically runs when the Air pump is turned on. If left on, the air pump will automatically turn off after 15 minutes.

Light

Press the "Light" button once to turn on the light. Press it again to turn the light off. Continue pressing the button on and off to cycle through different lighting modes: Slow cycle through all colors; Fast cycle; Flashing; and constant color. In constant color mode press the button repeatedly to find your favorite color.

If any light is left on, it will automatically turn off after 4 hours.

