

# 300W/41.6Ah All-in-1 High Capacity Portable Power Station

Wireless Speaker • 3 USB Ports • Dual AC Sockets • 60W Power Delivery • LED Light



## Power & Entertainment On The Go

124800mAh



Type-C™ PD Output

Power Button

AUX Port

USB QC 3.0 Output

**Qualcomm Quick Charge 3.0**

**STEREO SOUND**  
High Definition Sound Quality

DC 12V Outlets x3

AC Power Sockets

Auxiliary Port

LED Light Indicators

2 AC Sockets

3 DC Sockets

Dual USB Ports

Automatic Voltage Regulation

Ultra-Fast Charging

10W Powerful Speakers

Power-on-the-go: SafariMate is a powerful 300W/41.6Ah powerbank which is a one stop solution for all your on-the-go charging needs, especially in today's fast-paced lifestyle. Now you can take all your essential small appliances and electronic devices on the road with you wherever you go and literally set them up anywhere. The 300w inverter provides 220V AC mains power to run appliances such as TVs and laptops. SafariMate also includes a 4.8A high power USB charging ports and quick charge 3.0 charging port suitable for charging most smartphones.

### Specifications

- Battery Capacity: 462Wh (3.7V, 124800mAh)
- Output: - QC 3.0 USB-1: 5V/3A,9V/2A
- Wireless Speaker: 10W
- Battery Type: Lithium-Ion
- USB Ports: 2x 5V, 2.4A
- Bluetooth Version: v4.0
- Rate Power: 300W (Peak 600W)
- USB-C: 5V/3A,9V/3A,12V/3A,15V/3A,20V/3A (60W)
- LED Light: 5W
- Input: DC 19V/4.5A
- DC Ports: 3x 10A Share
- Charging Time: 6-8hours
- Cigarette Lighter Socket: 10A Share
- AC Sockets: 2x 220V/50Hz

### Available Socket Options



COMPATIBILITY	PACKAGING CONTENT	AVAILABLE COLOR	CERTIFICATION
All AC/DC/USB Powered Devices	» SafariMate » UserGuide	<b>Black</b>	