



# 48V MAMMOTH Plus

SKU: FMMTH-48096-G1

Powered by  BigBattery



## PARAMETERS

*Bulk, Absorption, Float, and Equalize are not applicable to lithium batteries but are included here with the correct numbers to input into your charge controller.*

**Charge Voltage:** 58.0V

**Bulk Voltage:** 58.0V *(Not Applicable to Lithium Batteries)*

**Absorption Voltage:** 58.0V *(Not Applicable to Lithium Batteries)*

**Absorption Time:** 0 Minutes *(Not Applicable to Lithium Batteries)*

**Float Voltage:** 58.0V *(Not Applicable to Lithium Batteries)*

**Equalize:** Off *(Not Applicable to Lithium Batteries)*

**Low Voltage Cutoff:** 43V

**High Voltage Cutoff:** 58.8V

**Suggested Inverter Low Voltage Setting:** 44V - 45V



## FREQUENTLY ASKED QUESTIONS

### How do I connect this battery into my existing system?

Our product uses a standard 175 electrical connector. A single battery order will include a 175 Connector to Ring Terminal cable for ease of installation.

### Where can I install this battery?

This battery is designed for indoor use only, and should not be exposed to direct sun light for an extended period of time.

### How many times can I put this battery in parallel / series?

This battery is not series capable but can be connected in parallel up to 8 times. Make sure that the total amount of these batteries in your configuration never exceeds 8 total batteries. When connecting batteries in parallel, make sure all batteries are within 1 volt of one another.

### How many years will my battery last?

Lithium Iron Phosphate (LiFePO4) batteries can be cycled from 3000 to 5000 times. If you cycle the battery daily then you can get more than 10 years of use from your battery.

### Can I connect into this battery's BMS to get extra info?

Our BMS is just there to keep your battery safe and healthy, it does not have the ability to network with any charge controllers or inverters for extra read-outs.

### What is the warranty on this battery?

We offer a comprehensive 10 year warranty on all of our batteries. You can read more about our warranty at [BigBattery.Com/Policies](https://BigBattery.Com/Policies).

### What should I do when my battery is at the end of its life?

Contact us and we'll recycle it for you, free of charge!



## CONTACT US

**Phone:** (818) 280-3091 **Email:** [Sales@BigBattery.com](mailto:Sales@BigBattery.com)

**Hours:** Monday through Friday 9:00 AM to 5:00 PM PST

**Address:** 21314 Lassen St. Chatsworth, CA 91311

Last Revision Date - 11/8/2022



## BATTERY SPECS

**Chemistry:** Voltage:

LiFePO4 48V

**kWh:** **Amp Hours:**

9.6 kWh 190 Ah

**Operating Voltage Range:**

43V - 58.8V

**Charging Voltage Range:**

55.6V - 58.0V

**Max Charging Voltage:**

58.8V

**⚠ WARNING:** Do NOT exceed max charging voltage.

**Cell Configuration:**

16S

**Charge Temperature Range:**

0°C - 55°C

**Discharge Temperature Range:**

-30°C - 55°C

**Optimal Discharge Temp. Range:**

15°C - 35°C

**Storage Temperature Range:**

-5°C - 35°C (Max 6 months)

## BMS SPECS

**Max Continuous Discharge:**

175A

**Max Continuous Power:**

7000W

**Max Peak Discharge:**

350A (Over 6 Seconds)

**Max Charge Current:**

120A

## BATTERY SIZE

**Weight:** **Width:**

220 lbs 10 in

**Length:** **Height:**

26.75 in 36.25 in