

ATOMIC DIGITAL WALL CLOCK

WITH CALENDAR & INDOOR TEMPERATURE

QUICK START GUIDE




MODEL: C86279V4

DC: 060419


For more product information visit: bit.ly/laxtech_support

POWER UP

1. Insert the 5 volt power cord into an outlet, then into your Wall Clock. Optional: Insert 2-AA batteries for backup.
2. Configure your basic settings.



ATOMIC TIME SIGNAL - WWVB

- Your clock will automatically search for the Atomic Time Signal at UTC 7:00, 8:00, 9:00, 10:00, and 11:00.
- Press the MINUS (-) button to manually start or stop a search for the WWVB Atomic Time Signal.
- While searching, the Tower Icon  will flash. The Tower Icon will be solid when the WWVB Signal is received by your clock.
- For information about WWVB Atomic Time visit: bit.ly/AtomicTime

SETTINGS

1. Hold the MODE button to enter the Settings Menu.
2. Press the + or - button to adjust values.
3. Press the MODE button to confirm and move to next item.
4. Press the SNOOZE button at any time to exit.

Settings Menu Order:

- Language (English or Spanish)
- Beep ON/OFF
- Atomic ON/OFF
- Time Zone
- Daylight Saving Time (DST) ON/OFF
- 12/24 Hour
- Hour
- Minutes
- Year
- Month
- Date
- Fahrenheit/Celsius

TIME ZONE

AST = Atlantic
EST = Eastern
CST = Central
MST = Mountain
PST = Pacific
AKT = Alaska
HAT = Hawaii

Language: Whichever language is selected, the following instructions and weekday will be presented in that language.

Atomic OFF: When Atomic OFF is selected, you will move directly to 12/24 Hour setting.

Weekday: Weekday will set automatically when Year, Month and Date are set.

BUTTON FUNCTIONS




The buttons are located at the top of your clock.

ALARM	Hold to enter Alarm Settings. Press to activate/deactivate alarm.
SNOOZE/LIGHT (HI-LO-OFF)	Press to adjust Backlight HI-LO-OFF. Power Cord required. When alarm sounds Press to Snooze Alarm for 10 minutes.
+ (PLUS)	Settings Menu: Press to increase value. Hold to increase quickly.
- (MINUS)	Press to start or stop Atomic Time Signal search. Settings Menu: Press to decrease value. Hold to decrease quickly.
MODE	Hold to enter the Settings Menu. Press to toggle Custom Display Options.

CUSTOM DISPLAY

Press the MODE button to change the clock display:

- Calendar
- Full Weekday
- Seconds
- Indoor Temperature



LOW BATTERY INDICATOR

When the Low Battery Indicator  appears between the hour and minutes, replace batteries in your Wall Clock.

WE'RE HERE TO HELP!

If you require additional support, get in touch with our friendly customer support team based out of La Crosse, WI.

Phone: 1-608-782-1610

Online: bit.ly/contact_techsupport

Our knowledgeable customer support team is available:
Monday-Friday, 8am-6pm CST.

JOIN THE CONVERSATION

Ask questions, watch detailed setup videos, and provide feedback on our social media outlets!



SPECIFICATIONS

Temperature Range: 32°F to 99°F (0°C to 37°C)

Update Interval: About every 60 seconds

Power: 5.0V Power Cord GPU280500150WA00

Optional: 2 "AA" (LR6, IEC) batteries (sold separately)

Battery Life: Over 24 months

Dimensions: 9.84" L x 1.14" W x 7.48" H

(25 cm L x 2.9 cm W x 19 cm H)

WARRANTY INFO

La Crosse Technology, Ltd. provides a **1-year limited time warranty** (from date of purchase) on this product relating to manufacturing defects in materials & workmanship.

La Crosse Technology, Ltd
2830 S. 26th St.
La Crosse, WI 54601

For Full Warranty Details, Visit: www.lacrossetechnology.com/support

CARE + MAINTENANCE

- Do not mix old and new batteries.
- Do not mix Alkaline, Lithium, standard, or rechargeable batteries.
- Always purchase the correct size and grade of battery most suitable for intended use.
- Clean the battery contacts and also those of the device prior to battery installation.
- Ensure the batteries have with correct polarity (+ / -).
- Remove batteries from equipment that will not be used for an extended period.
- Promptly remove expired batteries.

FCC STATEMENT

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Increase separation between equipment & receiver.
- Consult the dealer or an experienced radio/TV technician for help.

This device must not be co-located or operating in conjunction with any other antenna or transmitter.

Operation is subject to the following two conditions:


- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

CAUTION!

The manufacturer is not responsible for any radio or TV interference caused by unauthorized changes or modifications to this equipment. Such changes or modifications could void the user authority to operate the equipment.

All rights reserved. This manual may not be reproduced in any form, even in part, or duplicated or processed using electronic, mechanical or chemical process without the written permission of the publisher.

This booklet may contain errors or misprints. The information it contains is regularly checked and corrections are included in subsequent editions. We disclaim any responsibility for any technical error or printing error, or their consequences. All trademarks and patents are recognized.

 **WARNING:** This product can expose you to chemicals including styrene, which is known to the State of California to cause cancer. For more information go to: www.P65Warnings.ca.gov