



Honda

Honda EU1000i Generator

Pine Item # 51511

DESCRIPTION:

The Honda Super Quiet EU1000 is a very light weight, portable generator weighing 29 lbs. The Super Quiet series uses Honda's patented technology, Eco-Throttle which adjusts the engine speed to maximum efficiency depending on the load, thus reducing fuel consumption, engine noise, and emissions. The Honda EU1000 produces a clean sine wave of energy that does not spike and is safe for sensitive electronic equipment. This generator consists of a 1.8 HP single cylinder Honda overhead valve engine. The Honda EU1000 is ideal for smaller recreational or home usage. This model has .6 gallon fuel capacity and can run up to 8.3 hours at 1/4 load with Eco-Throttle.

FEATURES:

- 1000 watts, 120V
- Ideal for TV, lights, fans, small power tools and more
- Super quiet
- Less than 29 lbs!!
- Fuel efficient - up to 8.3 hrs on 0.6 gal of gas
- Inverter - stable power for computers and more

APPLICATION:

This generator can power the following common applications. Please note: not all applications can be powered simultaneously.

- Microwave Oven (up to 650 watts)
- Incandescent Lights
- Portable fan
- TV / DVD
- Coffee Maker
- Computer
- Blender
- Slow Cooker
- Two-Way Radio

Contact a Pine branch near you to request a quote or place an order

VISIT OUR U.S. AND CANADA WEBSITES TO FIND A BRANCH NEAR YOU

United States

www.pine-environmental.com

Canada

www.pine-environmental.ca

Product Specifications

Engine	Honda GXH50
Displacement	50cc
AC Output	120V 1000W max. (8.3A) 900W rated (7.5A)
Receptacles	15A 125V Duplex
DC Output	12V 96W (8A)
Starting System	Recoil
Fuel Tank Capacity	0.6 gal.
Run Time per Tankful	3.8 hrs. @ rated load 8.3 hrs. @ 1/4 load
Dimensions (L x W x H)	17.7" x 9.4" x 15.0"
Noise Level	59 dB(A) @ rated load 53dB(A) @ 1/4 load
Dry Weight	29 lbs.
Residential Warranty	2 Years
Commercial Warranty	1 Year



Video:
<https://youtu.be/cAw-4f5rACE>

Local Delivery Pick-up

In-Stock Equipment

Repair & Calibration

Rental Protection Plan