

## Features:

- Color OLED display
- Multi-direction display
- Multi-mode display
- PR waveform and bargraph display
- Accurate measurement of SpO<sub>2</sub> value and PR value
- Power off automatically when no signal
- Audible and visible alarm function
- Low battery voltage indication
- Low power consumption
- Widely used in hospital, home, community medical treatment, sports healthcare etc.

## Specifications

Model		BP-10M
Display		Color OLED
Display Direction		4
Waveform		YES
Audio Alarm		YES
SpO <sub>2</sub>	Measurement Range	35%-100%
	Accuracy	70%-100%, ±2%; 35%-69% no definition
	Resolution	1%
PR	Measurement Range	25-250 bpm
	Accuracy	± 2 bpm
	Resolution	1 bpm
Low Perfusion		≤0.3%
Alarm Indication	SpO <sub>2</sub>	< 90%
	PR	Upper Limit Lower Limit
Power Supply Management		Power off automatically (no signal for more than 16 sec)
Power Requirements		AAA size battery (1.5V)×2
Battery Life		24 hrs
Power Consumption		30 mA
Dimension		64×38×37mm (L×W×H)
Net Weight Including Battery		57 g



[www.biocare.com.cn](http://www.biocare.com.cn)



# BP-10M

Fingertip  
Pulse Oximeter



Distributed by:



PO Box 530, Camden NSW 2570  
Ph: 1300 651 958  
Email: [enquiries@nesgroup.com.au](mailto:enquiries@nesgroup.com.au)

[www.nesgroup.com.au](http://www.nesgroup.com.au)

