

AUTOMATIC BATTERY CHARGER

Zip 24 Volt Lithium-ion Battery

Model: 24v-LC2323

User Manual and Important Safety Information

VERSION 2.0

IMPORTANT

- The battery is designed for indoor charging only. Please ensure it is used on an uncarpeted, non-flammable hard floor in a well ventilated area.
- Do not attempt to use the charger if it has been dropped or damaged.
- Never attempt to charge a damaged battery, frozen battery or non-rechargeable battery.
- Do not smoke, use an open flame or create sparks near your battery and charger during charging.
- Do not operate the charger if the cord or plug is damaged.
- Do not attempt to open or repair the battery or charger casing as it will void the warranty.
- Ensure the battery is fully charged after each use no matter how many holes are played. A lithium battery is designed to last 18 holes in a day, not combined over the period of multiple consecutive days.
- Never attempt to fully discharge your battery. If your Zip cuts out repeatedly, please take your model, battery and charger to your nearest MGI Service Agent.
- It is not recommended that you leave your battery off charge for longer than 3 months. If you are not playing golf for some time, fully charge your battery, disconnect it and store it in a warm and dry environment. The battery will need charging at least every 3 months and must be charged prior to use.
- Only use this MGI Zip charger with the correct MGI Zip battery. The wrong charger on a battery may cause damage to the battery or model. This will also void the warranty of both the battery and the charaer.
- Your lithium battery leads, casing and connections should be regularly inspected for damage and wear.
- If your leads or connections need repair or replacement, please contact your local MGI repair centre for assistance immediately.
- Under no circumstances should a Lithium Battery that has been dropped, damaged or immersed in water be connected to a Zip or charger. By doing so you may create a fire hazard or risk the battery catchina fire. Please safely dispose of your battery immediately.

Operating Instructions

- Prior to first use and after every use, charge the battery.
- In between use, always leave the charger connected to the battery with power on. The battery is fitted with a smart charger that will charge until full then turn off until needed again.

MGI battery chargers have different connectors:

Battery	Connectors
24v Lithium	Red (1) and Black (2) on top of each other

• The charger should be matched with its respective battery by ensuring the same coloured connector is on the battery. For example the MGI Zip 24v Lithium charger with the Red and Black connector is to be connected to a MGI Zip 24v Lithium battery also with a Red and Black connect ors. Connect Red to Red and Black to Black.

Do **NOT** connect unmatched batteries or chargers otherwise the warranty on each item will be void.

- Plug the charger into a power point and attach the battery lead to the charger, matching the connections properly.
- Always recharge the battery as soon as possible after use, no matter how short the period of use. Your battery will charge best, Iving flat, in a warm and air ventilated location.
- Do not charge your battery on cold concrete or in a room below 10°C (50°F).
- To minimise drain on the battery during play, avoid taking your Zip into thick rough where possible.
- Do not use the Zip to pull yourself up hills.
- The battery is a sealed battery. If you are intending to take your model and battery on air travel, we advise that you make contact with your airline prior to travel.
- Be very careful not to drop your battery. The battery casing is fragile and the battery's subsequent life will be severely compromised. Any damage may compromise its functionality and operation.

Charging Process

LED Indicator

 The charging indicator will show the different states of the battery during the charging process.



- The Green LED illuminates solid to indicate the charger is powered on.
- The Red LED illuminates solid to indicate when charging.
- The LED will turn solid Green when the battery is fully charged.
- If the Green or Red LED indicator flashes constantly, this
 indicates that the charging process has failed, there may be
 a problem with your charger or battery. In this situation you
 should contact the MGI service centre.
- If the LED indicator light does not turn Green when the power is connected, there may be a problem with your charger. In this situation you should also contact the MGI service centre.

Warranty Information

Your MGI Zip model has a 24 month manufacturer warranty from the date of purchase against faulty material or workmanship which includes the battery and charger.

This warranty is void if the charger is damaged due to misuse or overheating from inadequate conditions during charging.

IMPORTANT: Register your model online to validate your warranty. Visit www.mgigolf.com to register.

Customer Support

For customer support, please contact MGI directly for immediate and professional advice.

www.mgigolf.com

MGI AUSTRALIA

Service Email: customerservice@mgigolf.com

Live Chat: visit www.maiaolf.com

Toll Free within Australia: 1300 644 523 (excludes mobiles)

Western Australia/ Internal phone +61 3 8872 6700 **Local Service Centres:** visit www.mgigolf.com

MGI USA

Service Email: serviceusa@mgigolf.com

Live Chat: visit www.mgigolf.com **Telephone:** 1800 617 2990

Servicing Enquiries Telephone: 1888 391 0200

MGI GLOBAL

Sales Email: globalsales@mgigolf.com

Service Email: customerservice@mgigolf.com

Live Chat: visit www.mgigolf.com



www.mgigolf.com

MGI AUSTRALIA MGI HEAD OFFICE

11 Maurice Court Nunawading 3131 Victoria Australia

T+61388726700 **E** sales@mgigolf.com **SERVICE** customerservice@mgigolf.com

MGI USA

T 1800 617 2990 E salesusa@mgjgolf.com SERVICE 1888 391 0200 SERVICE serviceusa@mgjgolf.com

MGI GLOBAL

E globalsales@mgigolf.com

Follow us on



Absolute attention has been taken to ensure this manual is correct at time of printing. Specifications, images and statistics may change at any time. Visit www.mgigolf.com for the most current model information. Version 2.0. 05/20