

# User Manual

MODEL: USL110  
Decorative Round Solar Wall Light  
1LED - 2 Pack

# HOSELINK®

A highly decorative light for your garden, this round solar design has a built-in intelligent light sensor that illuminates automatically at night and turns off at dawn.

## INSTALLATION

### OPTION 1

Adhere using outdoor double sided tape.



### OPTION 2

Follow these steps to mount to the wall or fence using the supplied plugs and screws:

1

Find a suitable location Solar - lights need access to direct sunlight for optimum results, preferably 6-8 hours per day.

2

Mounting the solar light - Use a 15/64" drill piece for masonry installation. Gently hammer the plugs into place and then secure the screws tightly. For timber use a 1/8" drill piece without the plugs.

3

Turn on the light - To activate the light, turn on the switch on the back of the unit. Test by covering the solar panel completely to check that the light comes on. The light is now ready for use.

## SPECIFICATIONS

Solar panel	2V / 0.25W
LED lumens	6
Waterproof rating	IP65
Battery Capacity	600mAh / 1.2V
Light temperature	3200 - 4000K
Charge time	8 hours
Operating Time	20 hours

### Note:

If the light does not turn on this could be due to the battery not being charged. Leave out in direct sunlight for 6 - 8 hours and try again.

MODEL: USL110  
Decorative Round Solar  
Wall Light 1LED - 2 Pack

For more information visit

[hoselink.com](https://www.hoselink.com)

or call

1 833 216 4673

Cultivating **Connections**

# HOSELINK®

