

INVERTER REMOTE CONTROL

MODEL: RS-RM02 / RS-RM03



Remote & Custom

Power ON/OFF and mode switching at your fingertips.
Configurable settings for tailored performance in any scenario.

Robust & Reliable

Comes with a 20 ft high-quality shielded cable.
Flame-retardant ABS enclosure with vibration and shock resistance.
Built to perform reliably in demanding environments.

Smart Alerts

Dual-color LED indicators (Green/Red) for clear status updates.
Instant fault codes with audible alarms for quick response.

Easy Interface & Installation

High-definition backlit LCD with wide viewing angles.
Real-time voltage, load, and battery status display.
Precision flush-mount design with RJ12 plug-and-play connectivity for effortless setup.

SPECIFICATIONS

Model	RS-RM02	RS-RM03
Bluetooth	No	Yes
Compatibility	NOVA SWITCH & NOVA SUPERCHARGER Series	
Display	HD Backlit LCD	
Indicators	Dual-color LED + Fault Code + Buzzer	
Monitoring	Voltage, Load, Battery Status	
Dimensions	5.4 × 3.4 × 1.3 in	
Cut-out Dimensions	4.3 × 2.3 in	
Connection	Wired RJ45 (6 m/20 ft cable)	