MULTI-FUNCTIONAL DOCK

USER MANUAL



SIDETRAK

Thank you for your purchase! This multi-functional USB-C dock is a convenient way to expand the capabilities of your laptop ports.


We hope you enjoy it!

- sidetrak.com
- facebook.com/sidetrakmonitor
- @sidetrakmonitor
- @sidetrak.monitor

If you have any questions, please feel free to contact us. We are happy to help!


> (240) 580-8725 customerservice@sidetrak.com

COMPONENT LIST



1	USB-C Cord	Corded USB-C to connect to your computer
2	Audio/Mic	3.5mm headphone input. External audio connector
3	USB-C 3.0	USB-C type power only
4	SD/TF Card Reader	Memory card reader input
(5)	USB-A 3.0	USB input for external keyboard, mouse, etc
6	Ethernet	Ethernet type input
7	HDMI	HDMI type data connector
8	Disp l ayPort	Disp l ayPort type input
9	USB-C 3.0	USB-C type power only

CONNECTION



Check the USB-C ports on your laptop for the symbols shown below to ensure you have a USB-C port that can transmit both power and data.







All USB-C ports on an Apple laptop are compatible, even if they don't show any svmbols.


This dock can transmit data for 2 HD monitors + accessories OR 1 4K monitor + accessories. Apple laptops don't support MST and can only do 1 monitor at a time, whether it's HD or 4K.

FEATURES

This docking station can be used as a wedge between your laptop and the desk to help airflow to your laptop.

Simply prop your laptop on the rubber feet on top of the docking station. The rubber feet will prevent the laptop from sliding.





FAQ

Why is there no video output?

- Make sure the USB-C port on your laptop can support video output. A USB-C port with the thunderbolt symbol.
- Check that the cable is well connected.
- Dock only supports two external monitors a

Why is there no audio output from HDMI?

- Make sure the USB-C port on your laptop can support video output. A USB-C port with the thunderbolt symbol.
- Make sure your monitor supports audio output.
- Set the external monitor as default audio output device.

Why does the output not reach 4K 60Hz?

- Make sure your monitor supports 4K 60Hz.
- Make sure to use the 2.0 or higher version of the HDMI cable.
- Make sure your computer specifications support DisplayPort1.4 signal output.

For more information please visit: support.sidetrak.com/knowledge

TECH SPECS

Weight	0.35 l b
Length	10.98 in
Width	2.14 in
Height	0.54 in
Transfer speed	5 Gb/s
Support 4K	Yes
Power delivery	Yes
Data delivery	Yes
USB-C type	USB-C 3.0
USB-A type	USB-A 3.0
HDMI type	HDMI 4K 60Hz and 4K 30Hz
Materia l	Aluminum







