



XP4850EH

DUAL FUEL PORTABLE GENERATOR
4,850 STARTING WATTS • 3,850 RUNNING WATTS





XP4850EH

DUAL FUEL PORTABLE GENERATOR

FEATURES

- Large Fuel Tank
- All Metal Construction
- Powerful OHV Engine
- No-Flat Tires
- All-Copper Windings
- Fully-Loaded Power Panel
- Low Oil Shutoff
- DC Circuit Protector



DOUBLE THE 120V POWER

OUTLETS



X2

120V 20A
GFCI Outlet



X1

120/240V
30A Twist
Lock

SPECS

Watts (Gasoline)	4,850 (peak) • 3,850 (running)
Watts (Propane)	4,608 (peak) • 3,608 (running)
Engine	OHV 210cc
Amperage	32.08A / 16.04A
Voltage	120V / 240VAC & 12VDC
Fuel Type	Gasoline / Propane
Runtime (Gasoline) at 50% Load	10 hrs
Runtime (Propane) at 50% Load	9 hrs