


# Circuit Breaker Enclosures Dimensions and Outline Drawings

## Section 7

### NEMA Type 1 Enclosures


Product Number	Dimension <sup>1</sup> A (in.)	Dimension <sup>1</sup> B (in.)	Dimension <sup>1</sup> C (in.)	Dimension D (in.)	Dimension E (in.)	Outline Drawing No.
TE100F, S, SB <sup>4</sup>	17	-	7 7/8	5 1/2	4 3/4	208C2891 Sh 3
TE150F, S, SB <sup>4</sup>	26 7/16	8 7/8	8 7/8	6 3/16	5 1/2	139C5497 Sh 1
SF250F, S, SB <sup>4</sup>	29 7/8	8 7/8	8 7/8	6 3/16	5 1/2	139C5497 Sh 2
FE250F, S, SB <sup>4</sup>	26 7/16	8 7/8	8 7/8	6 3/16	5 1/2	139C5497 Sh 9
PE250F, S, SB	26 7/16	8 7/8	8 7/8	6 3/16	5 1/2	139C5497 Sh 11
SG400F	31 3/8	-	15 5/32	7 5/16	6 5/8	208C2891 Sh 1
SG400S, SB <sup>4</sup>	30 5/16	-	14 1/8	7 5/16	6 5/8	208C2891 Sh 1
TJ400F, S <sup>2</sup>	27 7/16	15 7/16	15 7/16	7 1/8	6 7/16	139C5497 Sh 3
SG600F	44	-	18 3/16	9	8 3/8	208C2891 Sh 2
SG600S, SB <sup>4</sup>	42 3/4	-	17 1/8	9	8 3/8	208C2891 Sh 2
FG600F, S, SB <sup>4</sup>	42 3/4	-	17 1/8	9	8 3/8	208C2891 Sh 7
PG600F, S, SB	42 3/4	-	17 1/8	9	8 3/8	208C2891 Sh 9
TJ600F, S	46 5/8	17 3/16	17 3/16	9 1/16	8 3/8	139C5497 Sh 4
TK4V1200F, S, SB <sup>4</sup>	48 1/8	21 15/16	21 15/16	9 9/16	8 11/16	139C5497 Sh 5
TQC100F, S	15 1/4	-	6 7/8	4 3/4	4	139C5651 Sh 1
TQD225F, S	26 7/16	8 7/8	8 7/8	6 3/16	5 1/2	139C5497 Sh 1
TQL70F, S	12 7/8	-	5 3/4	4 3/4	4 1/16	208C2817 Sh 1
TQL100F, S	15 1/4	-	6 7/8	4 3/4	4	139C5651 Sh 2
TQL125F, S	16 7/8	-	6 3/4	5 3/16	4 1/2	139C5651 Sh 2



NEMA Type 1  
Suffix F (Flush) Suffix S (Surface)

### NEMA Type 3R Enclosures


Product Number	Dimension A (in.)	Dimension B (in.)	Dimension C (in.)	Dimension D (in.)	Dimension E (in.)	Outline Drawing No.
TE100R	18 1/8	7 7/8	7 1/2	5 11/16	5 3/8	139C5652 Sh 1
TE150R	27 7/16	10 1/4	10	6 1/4	5 1/2	139C5498 Sh 1
TF225R	30 13/16	10 1/4	10	7	6 1/4	139C5498 Sh 2
FE250R	27 7/16	10 1/4	10	6 1/4	5 1/2	139C5498 Sh 5
SG400R	30 13/16	14 15/16	14 5/8	9 1/8	8	208C2837 Sh 1
SG600R	43	18 7/8	18 1/6	8 13/16	7 11/16	208C2838 Sh 1
FG600R	43	18 7/8	18 1/6	8 13/16	7 11/16	208C2838 Sh 2
TJ400R <sup>2</sup>	27 5/16	15 7/8	15 11/16	8 11/16	8	139C5498 Sh 4
TJ600R	46 3/16	18 1/16	18 1/16	8 5/8	7 5/8	139C5519 Sh 1
TK4V1200R	47 3/4	23 3/8	22 9/16	9 7/16	8 5/16	139C5520 Sh 1
TQC100R	15 3/4	7 7/8	7 1/2	5 11/16	5 3/8	139C5652 Sh 1
TQD150NRE	26 13/16	7 13/16	7 5/8	5 1/8	4 7/16	139C5498 Sh 3
TQD200NRE	26 13/16	7 13/16	7 5/8	5 1/8	4 7/16	139C5498 Sh 3
TQD225NR	26 13/16	7 13/16	7 5/8	5 1/8	4 7/16	139C5498 Sh 3
TQD225R	26 3/8	10 1/4	10	6 1/4	5 1/2	139C5498 Sh 1
TQL70R	17	-	6 7/8	5 15/16	5	208C3061 Sh 1
TQL100R, RE	17	7 1/4	6 7/8	6	5	139C5652 Sh 1
TQL125R	18 5/16	7 11/16	7 1/2	6 5/16	5 3/16	139C5652 Sh 1
THQMV150NRE	18 13/16	9 1/2	9 5/16	5 1/2	4 7/8	208C3061 Sh 2
THQMV200NRE	18 13/16	9 1/2	9 5/16	5 1/2	4 7/8	208C3061 Sh 2



NEMA Type 3R Outdoor Enclosure

### NEMA Type 4/4X Enclosures


Product Number	Dimension A (in.)	Dimension B (in.)	Dimension C (in.)	Dimension D (in.)	Dimension E (in.)	Outline Drawing No.
SE100CS	19 1/4	18 1/2	8 1/2	7	5	139C5654 Sh 1
TE100CS	19 1/4	17 1/4	8 1/2	7	5	139C5654 Sh 1
SF250CS	36 5/8	34 13/16	9 1/4	7 27/32	5 29/32	168D1626 Sh 1
TJ400CS <sup>2</sup>	29 1/4	27 1/2	16 1/4	9 1/16	7 1/8	139C5496 Sh 2
SG400CS <sup>3</sup>	32	31 1/4	14 1/8	9 5/16	7 7/16	208C2887 Sh 1
TJ600CS	46 1/4	45 1/2	19 1/8	9 1/16	7 1/8	139C5496 Sh 3



NEMA Type 4/4X Stainless Steel

### NEMA Type 12 and 12K Enclosures

Product Number	Dimension A (in.)	Dimension B (in.)	Dimension C (in.)	Dimension D (in.)	Dimension E (in.)	Dimension F (in.)	Outline Drawing No.
SE100J, D	19 1/4	17 7/8	9	5	5 3/4	4 7/8	139C5653 Sh 1
TE100J, D	19 1/4	17 7/8	9	5	5 3/4	4 7/8	139C5653 Sh 1
SF250D	36 1/4	35 3/8	9 13/16	9 3/16	7 9/16	6 1/2	208C2884 Sh 1
SF250J	36 1/4	35 3/8	9 13/16	9 3/16	7 9/16	6 1/2	208C2884 Sh 2
SG400D	31 3/8	30 1/2	16 5/16	15 11/16	7 7/8	6 9/16	208C2885 Sh 1
SG400J	31 3/8	30 1/2	16 5/16	15 11/16	7 7/8	6 9/16	208C2885 Sh 2
TJ400J <sup>2</sup>	29 5/16	27 13/16	14 1/4	13 3/16	7 7/8	6 7/16	139C5682 Sh 4
SG600J	44 7/8	44	18	17 3/8	9 9/16	8 3/8	208C2886 Sh 1
TJ600J	48 7/16	46 15/16	17 3/4	17 3/16	9 3/4	8 3/8	139C5682 Sh 5
SK1200J	56 5/16	55 7/16	22 11/16	22	10 7/16	8 11/16	139C5682 Sh 6



NEMA Type 12 and 12K  
Suffix D (with KOs) Suffix J (without KOs)

<sup>1</sup>Flush front extends approximately 5/8-inch beyond each side.  
<sup>2</sup>Suitable for parallel 250 kcmil maximum. If larger cable is applied, use 600 amp enclosure.  
<sup>3</sup>Not suitable for use with ground fault.  
<sup>4</sup>NEMA Type 1 Enclosure Product Numbers ending in "SB" contain blank end walls (No Knockouts).



# Circuit Breaker Enclosures Dimensions and Knockout Drawings

## Section 7

Symbol	A	⊕	B	C	D	E	F	G	H	I	J	K	L	M	N	P	Q	R	S	T	U	V	W	X	Y	Z	
Conduit Size (Inches)	9/32	—	3/8	—	—	—	—	—	—	3/8	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	
	—	1/2	1/2	1/2	—	1/2	—	1/2	—	1/2	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	
	—	—	3/4	3/4	3/4	3/4	3/4	3/4	3/4	3/4	3/4	—	—	—	—	3/4	—	—	—	—	—	3/4	—	—	—	—	
	—	—	—	—	—	1	1	1	1	1	1	1	—	1	—	1	1	—	—	—	—	1	—	—	—	—	
	—	—	—	—	—	—	—	—	1 1/4	1 1/4	1 1/4	1 1/4	1 1/4	1 1/4	1 1/4	1 1/4	—	—	1 1/4	—	—	1 1/4	—	—	—	—	
	—	—	—	—	—	—	—	—	—	—	1 1/2	1 1/2	1 1/2	1 1/2	1 1/2	1 1/2	1 1/2	1 1/2	1 1/2	1 1/2	1 1/2	—	—	—	—	—	
	—	—	—	—	—	—	—	—	—	—	—	—	—	—	2	2	2	2	2	2	2	2	—	2	2	—	2
	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	2 1/2	2 1/2	2 1/2	2 1/2	2 1/2	2 1/2	2 1/2	—	2 1/2	—	—	2 1/2
	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	3	3	3	—	3	3	3	3
	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—	—

### Circuit Breaker Enclosures

Product Number	Knockout Figure No.
TE100F, S	1
TE100R	10
TE150F, S	4
TE150R	7
SF250F, S, FE250F, S, PE250F, S	4
TF225R, FE250R	7
TJ400F, S, SG400F, S	5
TJ400R, SG400R	6
TJ600R, SG600R, FG600R	9
TJ600F, S, SG600F, S, FG600F, S, PG600F, S	3
TK4V1200F, S	No KO
TK4V1200R	No KO
TQC100F, S	2
TQC100R	10
TQD225F, S	4
TQD225NR	8
TQD225R	7
TQL100F, S	2
TQL100R	10




Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6




Fig. 7




Fig. 8




Fig. 9




Fig. 10

