



TERRA

LUNA

Warranty	3-Year Limited Warranty	3-Year Limited Warranty
Max. Curable Imprint Area	4.9' L x 8.2' W (59" L x 98" W)	3.2' L x 5.9' W (39.3" L x 70.8" W)
Max. Substrate Height	3.93" H	5.9" H
Max. Substrate Weight	220 lbs (5.48 psf)	132 lbs (6.83 psf)
Machine Size	209" W x 110" L x 71" H	168" W x 69" L x 58" H
Print Heads	Konica Minolta KM1024aSHE	Konica Minolta KM1024aSHE
Built-in Vacuum Bed	8 zone, 141 CFM	4 zone, 141 CFM
Power Source	220V, 60 Hz - Single Phase, 40A	220V, 60 Hz - Single Phase, 40A
Compressed Air Requirements	100 psi	100 psi
Power Consumption	8KW	8KW
UV Lamp Specs	2 x 395nm air cooled 16 Watt/cm ² UV LED lamps	2 x 395nm air cooled 16 Watt/cm ² UV LED lamps
Built in PC	Dual-Core i7 Processor, 64 bit, 1TB SDD 8GB RAM, Windows 10	Dual-Core i7 Processor, 64 bit, 1TB SDD 8GB RAM, Windows 10
Control Panel	Touch Screen, built in PC	Touch Screen, built in PC
Interface	Ethernet	Ethernet
Optimized Resolution	720x360, 720x720, 720x1080, 720x1440 dpi (uni + bi available)	720x360, 720x720, 720x1080, 720x1440 dpi (uni + bi available)
Consumable Parts	Print heads, filters for UV lamp, home tray filters	Print heads, filters for UV lamp, home tray filters
Ink Process	CMYK + 2 custom channels + optional primer	CMYK + 2 custom channels
Ink Type	UV LED, ST1000 Strata Series	UV LED, ST1000 Strata Series
Ink Supply	Pressurized + White Ink Circulating System	Pressurized + White Ink Circulating System
Ink Configuration Options	C, M, Y, K C, M, Y, K, W, W C, M, Y, K, W, W, Primer C, M, Y, K, W, Varnish C, M, Y, K, LC, LM	C, M, Y, K, W, W C, M, Y, K, W, Primer C, M, Y, K, W, Varnish C, M, Y, K, LC, LM
Printer Weight	4,188 lbs	2,420 lbs
Shipping Weight	6,217 lbs	4,048 lbs
Shipping Dimensions	228" L x 90" W x 82" H	195" L x 78" W x 87" H
Environmental Condition	68~77° F; Humidity 40~60% (non-condensing)	68~77° F; Humidity 40~60% (non-condensing)
RIP Software - Included	LogoJET Edition Wasatch (1 year subscription) or Onyx Thrive (Level 3 Driver)	LogoJET Edition Wasatch (1 year subscription) or Onyx Thrive License (Level 3 Driver)
Installation & Training	3 Days onsite installation & training	3 Days onsite installation & training