

## SPECIFICATION SHEET



### CONNECTION

**DMX Channels:** 6, 8, or 12  
**DMX Connectors:** 3-pin XLR  
**Light Source:** 4 LEDs (hex-color RGBAW+UV) 10 W (2 A)  
**Strobe Rate:** 0 to 25 Hz  
**PWM Frequency:** 1,200 Hz  
**Beam Angle:** 23°  
**Field Angle:** 34°  
**Max Run Time (All On):** Up to 8 hours (with the limiter on),  
(single color): up to 20 hours  
**Recharge Time:** 6 hours  
**Operating Frequency:** 2.412 to 2.484 GHz  
**Brightness:** 1372 lux @ 2 m  
**Power Linking:** 26 units @ 120 V; 50 units @ 230 V  
**Input Voltage:** 100 to 240 VAC, 50/60 Hz (auto-ranging)  
**Power:** 35 Watts, 0.3 A @ 120 V,  
60 Hz, 34 Watts, 0.2 A @ 230 V, 50 Hz  
**Included:**  
- IRC-6Power Cord  
- Quick Reference Guide  
- Warranty Card  
**Dimensions (LxWxH):** 5.4 x 5.7 x 7.2 in (138 x 145 x 184 mm)  
**Weight:** 6.2 lb (2.9 kg)  
**Certifications:** FCC Approved, CE Approved



Built-in adjustable  
kickstand



Threaded hole for truss  
mounting option

**JOB NAME:**

**LOCATION:**

**QUOTE/REF#:**

### DESCRIPTION

The Freedom Par Hex-4 is the most colorful model in the next generation of the Freedom Par family. It has four 10-watt RGBAW+UV LEDs for that extra punch and the special effects that white and UV add to color mixing. The Freedom Par Hex-4 has a special limiter option for extending battery life so that when you use more than 4 colors you know you'll get a good long show! The Freedom Par Hex-4 comes in black or white housing so it fits into any décor.

### KEY FEATURES

- 100% TRUE wireless, battery-operated, hex-color (RGBAW+UV) LED Par with built-in DFi™ transceiver
- Multiple wireless triggering and control options via the FlareCON™ Air and the FlareCON™ app
- Works in Master/Slave with first-generation Freedom™ Pars
- Shine light where it is needed using the built-in adjustable kickstand
- Built-in glare shield prevents light spillage
- Extend the battery's lifespan with built-in discharge protection
- Convenient, wireless non-DMX control using the IRC-6 remote
- Create customized colors using the built-in LED display
- Achieve smooth LED fading with built-in dimming curves
- Safely store and transport your fixtures from gig to gig in the CHS-FR4 carry bag
- Compact and lightweight design easily fits inside sticks of TRUSST®
- Increase battery run time with built-in limiter circuitry that conserves energy when over 4 colors are in use simultaneously

### APPLICATIONS

- Trade Show and Exhibition Displays
- Retail Displays
- Architectural lighting for canopies, corridors, archways, windows
- Uplighting for wall wash applications
- Excellent for hospitality applications such as bars, restaurants, clubs, hotels
- Statue and sculpture lighting illumination