


EL-NDCC-350-3W 350mA LED Constant Current Drivers 3 Watts

SPECIFICATION SHEET



SPECIFICATIONS

Input Volt.: 100-240V AC **Output Volt.:** 3-9V DC **Current:** 350mA 1-3 Watts **Power:** Dimmable: No **Oper. Temp.:** -20°C ~ +50°C **Over Load Protection:** Yes **Over Temperature Protection: Yes** Short Circuit Protection: Yes Power Method: Hardwire **Dimensions:** 1.63 in. L x 1.5 in. W x 0.75 in. H 41 mm L x 38 mm W x 19 mm H White Polycarbonate Finish: **Environment:** Dry Location **IP Rating: IP20** Rating: UL Listed, CUL Listed, RoHS, CE Manufacturer: Elumalight 1 Year Limited Warranty:



630 Terminal Way, Costa Mesa, CA 92627 sales@step1dezigns.com | www.step1dezigns.com TF: 800.822.8527 |T: 949.270.0250 | FAX: 949.270.0253 JOB NAME: LOCATION:

QUOTE/REF#:

DESCRIPTION

350MA LED Constant current drivers are generally used when you need stable current to your LED lights. It has built-in overload, short circuit, and overheat protection.

Need help with your LED lighting applications? Our lighting experts are here to help! Contact us today for assistance with lighting plan or installation instructions.

KEY FEATURES

- Easy installation
- Maintenance-free
- Solid-state construction
- High vibration and shock resistance
- Overload, short circuit, and overheat protection
- No RF interference
- UL Listed, CUL Listed, RoHS, CE
- Long lifespan

APPLICATIONS

• For use with compatible Constant Current 350mA LED lights. Not for use with dimmers.



© 2020 Step 1 Dezigns, Inc. All Rights Reserved. Specifications are subject to change without notice.