


SPECIFICATION SHEET

JOB NAME: _____

LOCATION: _____

QUOTE/REF#: _____



DESCRIPTION

500MA 9 Watts LED Constant current drivers are generally used when you need stable current to your LED lights. It has built-in overload, short circuit, and overheat protection.

Need help with your LED lighting applications? Our lighting experts are here to help! Contact us today for assistance with lighting plan or installation instructions.

SPECIFICATIONS

- Input Volt.:** 100-240V AC
- Output Volt.:** 6.8-18V DC
- Current:** 500mA
- Power:** 3.25-9 Watts
- Dimmable:** No
- Oper. Temp.:** -20°C ~ +50°C
- Over Load Protection:** Yes
- Over Temperature Protection:** Yes
- Short Circuit Protection:** Yes
- Power Method:** Hardwire
- Dimensions:** 2.36 in. L x 1.57 in. W x 0.94 in. H
60 mm L x 40 mm W x 24 mm H
- Finish:** White Polycarbonate
- Environment:** Dry Location
- IP Rating:** IP20
- Rating:** UL Listed, CUL Listed, RoHS, CE
- Manufacturer:** Elumalight
- Warranty:** 1 Year Limited

KEY FEATURES

- Easy installation
- Maintenance-free
- Solid-state construction
- High vibration and shock resistance
- Overload, short circuit, and overheat protection
- No RF interference
- UL Listed, CUL Listed, RoHS, CE
- Long lifespan

APPLICATIONS

- For use with compatible Constant Current 500mA LED lights. Not for use with dimmers.

