

SPECIFICATION SHEET

JOB NAME:

LOCATION:

QUOTE/REF#:



DESCRIPTION

The 2.2 watt MR-11 LED Mini Swivel Downlight is a versatile and efficient recessed light fixture. It is a fully recessed LED light that adds brightness, focused illumination to any space.

This mini swivel downlight fits into shelving, cabinets, under countertops, display cases, and retail window displays. It features an adjustable gimbal design for directed lighting with 35° axial swivels. Its low profile and shallow installation create a modern design for recessed applications.

It is supplied with Cool White or Warm White MR-11 LED bulb and metal housing with a cutout template for recessed installation project. It is not intended for use in walls or ceilings. Available in 3000K Warm White or 5000K Cool White LED color temperature options.

SPECIFICATIONS

- Brightness:** 160 Lumens
- Power (Watts):** 2.2 Watt
- Input Voltage:** 12V AC/DC
- LED CCT:** 3000K or 5000K
- LED Bulb:** MR-11
- Dimmable:** Yes, with Dimmable Driver
- IP Rating:** IP20
- Environment:** Indoor Use - Dry Location
- Beam Angle:** 15 - 40°
- LED Density:** 1 LEDs
- Cut-out:** 2.38 in / 60.45 mm Diameter
- Gimbal Size:** 2.5 in / 63.5 mm
- Gimbal Depth:** 2.75 in / 69.85 mm
- Finish:** Black, White, Chrome, Brush Nickel, Bronze
- Manufacturer:** Elumalight
- Rating:** UL, ETL Listed
- Avg. Lifetime:** ± 30,000 - 50,000 hours
- Required:** The LED Swivel Downlight requires 12V AC/DC LED Power Supply, optional power cord. Sold separately.

KEY FEATURES

- Maintenance-free
- Solid-State Construction
- No IR or UV radiation
- Suitable for flat ceiling or under-cabinet installations
- Easy to mounting and install with tension spring clamps
- LEDs Chipsets are high intensity, ultra-bright, and energy-efficient
- No RF interference
- Long lifespan: Up to 50,000 hours

APPLICATIONS

- Decorative Lighting for Tradeshows, Exhibition, Retail Displays
- Architectural lighting for corridors, canopies, archways,
- Downlighting or Uplighting Recessed Applications
- Under-cabinet, Under-Counter, or accent lighting

