

# EL-S91000-301

## 12V AC 300 Watt Magnetic Plug N Play Transformer

JOB NAME:

LOCATION: QUOTE/REF#:

#### SPECIFICATION SHEET



### **SPECIFICATIONS**

120V AC 60 Hz Input:

Input Current: 2.5A

**Output:** 12V AC (Max 50VA) x 6

300 Watt Power:

**Power Method:** Plug N Play, 6 Ft Power Cord with Plug included

**Dimensions:** 8.5 in. L x 6.75 in. W x 2.25 in. H 216 mm L x 171 mm W x 57 mm H

**Environment: Dry Location** 

IP20 **IP Rating: Case Style:** Aluminum **Case Finish: Black** 

Manufacturer: Step 1 Dezigns Warranty: 1 Year Limited

#### **ACCESSORIES**



Male Female Banana Plug **Extension 10 Ft Long** SKU: EL-910EXT **Sold Separately** 



**MR16 Round Lamp Socket** with Male Banana Plug SKU: EL-LSOC-MR16-MBP **Sold Separately** 

#### DESCRIPTION

300 Watt magnetic transformer. Holds up to 6-50 Watt 12V AC light fixtures. Illuminated on/off switch. Accepts male banana plug extensions. Includes 6ft grounded cord and plug set.

Need help with your LED lighting applications? Our lighting experts are here to help! Contact us today for assistance with lighting plan or installation instructions.

#### **KEY FEATURES**

- Easy installation
- Maintenance-free
- High vibration and shock resistance
- Short circuit protection
- No RF interference
- Long lifespan

#### **APPLICATIONS**

For use with compatible 6-50 watt 12V AC light fixtures.





