



# 1. Adding Master Password (after Factory Reset Mode)

Step 1	Step 2
<p>Tap on * and then # to enter setting mode.</p>	<p>Enter the admin password that you want to register and press "#". Repeat again</p> <p><b>**NOTE:</b></p> <ul style="list-style-type: none"> <li>- At least 6 digits</li> <li>- Please do remember the admin password</li> </ul>

## 2. Add New Admin

Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode.	Verify Admin by passwords or finger vein	Press 1 (Add User)	Press "1" again (Add Admin)  Input information : type password and press "#" and repeat OR scan finger vein 6 times (same position) OR tap the RFID Card on "card icon" (below number 5)

## 3. Add New User

Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode.	Verify Admin by passwords or finger vein	Press 1 (Add User)	Press 2 (Add User)  Input information : type password and press "#" and repeat OR scan finger vein 6 times (same position) OR tap the RFID Card on "card icon" (below number 5)

## 4. System Setting (Time Setting)

Step 1	Step 2	Step 3
Press on "*" and then "#" to enter setting mode.	Verify Admin by passwords or finger vein. Press "3" for System Setting	Press 1 (Set Datetime) the details in the following format: YY : MM : DD HH : MM

## 5. System Setting (Language and Volume Setting)

Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode.	Verify Admin by passwords or finger vein	Press "3" for System Setting	For Language, press 3 1. Chinese 2. English  For Volume, press 4 (Volume)

## 6. System Setting (Restore Factory Setting/ Factory Reset)

Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode.	Verify Admin by passwords or finger vein	Press 3 (System Setting)	Press 4 and "#" to confirm

## 7. Delete Admin/User

Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode.	Verify Admin by passwords or finger vein	Press 2 (Delete User)	For verify delete, press 1 Input information : type password / scan finger vein / tap the RFID Card on "card icon" (below number 5)  For delete by ID, press 2 After that enter the user number that you want to delete and press #

## 8. Connect to Wi-Fi (Please download USmart Go App)

Step 1	Step 2	Step 3	Step 4
<p>Download <b>USmart Go</b> app into your phone and register for an account first.</p> 	<p>Go to the lock setting. Press on "*" and then "#" to enter setting mode.</p>	<p>Verify Admin by passwords or finger vein</p>	<p>Press 3 (System Setting)</p>
Step 5	Step 6	Step 7	Step 8
<p>Press 4 (Function Setting) The LCD screen appear "Configuring....."</p>	<p>Go into Usmart Go App (Phone) and click "Add Device"</p>	<p>Select Connect via Wi-Fi hotspot</p> <p>After that go into your phone's WiFi Setting and select CloudHome-XXXXXXXX to connect</p>	<p>After connected the CloudHome-XXXXXXXX WiFi, go back to the Usmart Go App, and it is loading a few seconds</p>
Step 9	Step 10	Step 11	
<p>Select your home Wi-Fi to connect and type the password of home Wi-Fi</p> <p><b>**NOTE:</b> Please connect with 2.4ghz WiFi</p>	<p>Press Search Device and show checking network and wait within 1 minute"</p>	<p>Once successful, your phone screen will show "Connected to server" and the system will say success.</p>	