

FR056 User Manual



1. Adding Master Password and Enter Digital Lock Setting

Step 1	Step 2	Step 3
Tap on “*” and then “#” to enter setting mode	Enter a 6 digit password and tap on “#” to confirm	Repeat the password and tap on “#” to confirm



2. User Manage (Adding Users)

Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode	Verify Admin and press "1" User Manage	Press "1" Create User and you will see the following options: 1. Administrator 2. Normal User 3. Guest User 4. Coerce User	Press any of the options from step 3 and you will see the following options: 1. Enroll FaceID 2. Enroll password 3. Enroll ID Card 4. Enroll Fingerprint
Step 5			
<p>A: Enroll Face ID</p> <p>(Voice Prompt: Please look at the camera) Stand in front of the digital lock, and look at the camera, the face detector will auto scan and register. Until hear (Voice Prompt: Enroll Success)</p> <p>B: Enroll Password</p> <p>Enter a 6-digit password and press on "#" to confirm. (Voice Prompt: Please enter again) Please enter the same 6-digit password again and press on "#" to confirm.</p> <p>C: Enroll ID Card</p> <p>Place your RFID card tag sticker between 5 and 8 to register. Until (Voice Prompt: Enroll Success)</p> <p>D: Enroll Fingerprint</p> <p>Place your selected finger on the fingerprint scanner and continuously the same position until (Voice Prompt: Enroll Success)</p>			



3. User Manage (Deleting User)

Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode	Verify Admin and press "1" User Manage	Press "3" Delete User and you will see the following options: 1. Delete by ID 2. Delete by Type 3. Delete All	If you Press "2" under step 3, you will see the following options: 1. Clean Face ID 2. Clean Password 3. Clean ID Card 4. Clean Fingerprint

*If all management users are deleted, users will not be able to enter the management menu, please exercise caution.

**After operating "Delete All", any unlocking method can be unlocked, please proceed with caution

4. System Setting (Time Setting)

Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode	Verify Admin and press "3" System Setting	Press "1" Time Setting and enter the details in the following format: YY : MM : DD HH : MM	Press "#" to confirm and Press "*" to exit setting mode



5. System Setting (Language and Voice Volume Setting)

Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode	Verify Admin and press "3"	Press "2" Language and Volume Setting and you will see the following options: <ol style="list-style-type: none">1. Chinese2. English3. Volume Low4. Volume High	Press "#" to confirm and Press "*" to exit setting mode



6. System Setting (Single Verify and Multiple Verify)

Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode	Verify Admin and press "3" System Setting	Press "3" Lock Setting and You will see the following options: 1. Single Verify 2. Multiple Verify 3. Disable Verify 4. Anti-Pry	Press "#" to confirm and Press "*" to exit setting mode

7. System Setting (Body Detect)

Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode	Verify Admin and press "3" System Setting	Press "4" Unlock Setting and Press "3" Body Detect [1] . Keep pressing "3" until Body Detect [0] to turn off	Press "#" to confirm and Press "*" to exit setting mode












8. System Setting (Restore Factory Setting/ Factory Reset)









Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode	Verify Admin and press "4" System Query	Press "4" Factory Reset and Press "#" to confirm	Press "*" to exit setting mode





9. Connect to Wi-Fi (Please download USmart Go)

Step 1	Step 2	Step 3	Step 4
Press on “*” and then “#” to enter setting mode	Verify Admin and press “2” Remote Manage . You will see the following options: 1. Create Phone 2. Delete Phone 3. Create Remote 4. Delete Remote	Press “1” from step 2 and you will see the following options: 1. WIFI 2. AP	Press “1” and the system will show Add WIFI please wait.....
Step 5	Step 6	Step 7	Step 8
Press Account Registration to register for an account 	Please Register by Email 	Press Add Device 	Press OK to add a family 

Step 9	Step 10	Step 11	Step 12
<p>Enter Family Name and press OK to proceed</p> 	<p>Press on Add Device</p> 	<p>Select Add Wi-Fi Device</p> 	<p>Once you have reached this page, go to Wi-Fi list on your phone (Refer to Step 13)</p> 
Step 13	Step 14	Step 15	Step 16
<p>Select the Wi-Fi name starting with CloudHome</p> 	<p>Press on Connect</p> 	<p>Ensure that the Wi-Fi has been Connected (No Internet Access)</p> 	<p>Return to the App and wait for a few second (As shown below)</p> 

Step 17	Step 18	Step 19	Step 20
<p>The app will start to search for Wi-Fi</p> 	<p>Please select your home Wi-Fi (Ensure it is 2.4 GHz)</p> 	<p>Ensure that the Wi-Fi name is correct and enter your Home Wi-Fi Password. Press Search Device to proceed</p> 	<p>The app will show Connecting Wi-Fi. Do wait for 20-30 seconds (Depending on Wi-Fi connection)</p> 
Step 21	Step 22	Step 23	Step 24
<p>Once it is successfully connected, you may see a photo as shown below. Press Finish to proceed</p> 	<p>Ensure that there is a Smart Lock Added under My Devices. Press on it to enter</p> 	<p>Under Smart Lock, you may see a photo as shown below. Do try using your password, card and fingerprint to unlock the door</p> 	<p>After using your password, card and fingerprint to unlock, You may see the records appeared as shown as the picture below</p> 



Step 25	Step 26
<p>Press on the Bell on the lock, You will receive a notification for Remote Unlock</p>  A photograph of a green, dome-shaped smart lock. A notification overlay is visible at the bottom of the frame. The notification has a blue header "Request for remote unlock" and shows device details: "Device Name: Smart Lock", "Device ID: 8C6ED9E1984B", and "Family: 1". At the bottom of the notification are two buttons: a red "Ignore" button and a blue "Unlock(31%)\" data-bbox="328 328 491 471"/>	<p>Enter your password to authorize Remote Unlock. The door will then be unlock</p>  A screenshot of the "Smart Lock" app's "Security verification" screen. It prompts the user to "Verify with security password" and shows a numeric keypad. Below the keypad, there is a notification card titled "Request for remote unlock" with a timestamp "Dec 9, 2021 9:00:34 PM" and a small image of the lock. At the bottom of the screen is a numeric keypad with symbols for back, forward, and checkmark."/>







10. Door Viewer Setting

Setup mode	Language	Date/Time
<p>Press the “OK” and then “▶” to enter setting mode. Press the right button twice and select Setup (⚙️)</p> <p>Select Setup Mode and you will see the following options:</p> <ol style="list-style-type: none"> 1. Photo Mode 2. Video Mode 	<p>Press the “OK” and then “▶” to enter setting mode. Press the right button twice and select Setup (⚙️)</p> <p>Select Language and you will see the following options:</p> <ol style="list-style-type: none"> 1. English 2. 简体中文 	<p>Press the “OK” and then “▶” to enter setting mode. Press the right button twice and select Setup (⚙️)</p> <p>Select Date/Time and enter the details in the following format:</p> <p>2021 / 01 / 02 18 : 52 : 48 YY/MM/DD</p>




11. Change Username in Apps (USmart Go)

Step 1	Step 2	Step 3	Step 4
<p>Press on Smart Lock to enter</p> 	<p>Select on any records (password, IC Card or Fingerprint) as shown from the picture below</p> 	<p>Press on OK to proceed</p> 	<p>Enter your name Under User Name and press OK to proceed</p> 





Step 5

Use any methods to unlock the door and you can see **Username** on the record





12. Add members in Apps (USmart Go)

Step 1	Step 2	Step 3	Step 4
<p>Press on Menu on the top left-hand corner</p> 	<p>Select My Families to proceed</p> 	<p>Ensure that Your Account Name (Email address) is correct. Press on Add Family Member to proceed</p> 	<p>Ensure that your family member has already registered an account. Input His/her Email address and Name to proceed</p> 

Unlock Protection:

FaceID Protection: Continuing to attempt the wrong password more than 4 times will activate the alert.

Password Protection: Continuing to attempt the wrong password more than 5 times will activate the alert.

Fingerprint Protection: Continuing to attempt the wrong fingerprint more than 10 times will activate the alert.

RFID Protection: Continuing to attempt the wrong RFID password more than 10 times will activate the alert.