





















Champion's 3000 watt dual fuel inverter generator is one of the lightest in the industry at only 21.5kg, making portable power easier

## PROPANE HAS 50 % LESS EMMISIONS & 50% COST SAVINGS

Rely on the 149cc engine with a quiet 58 dBA for up to 11.5 hours of run time on petrol or up to 34 hours with 19kg propane canister (based on 25% load). The Parallel Kit (sold separately) can increase your output.

CO Shield  $^{\circ}$  technology monitors the accumulation of carbon monoxide (CO), a poisonous gas produced by engine exhaust when the generator is running. If CO Shield detects unsafe elevated levels of CO gas, it automatically shuts off the engine.



i

## **FEATURES**

- 2800 Running Watts
- Super lightweight at only 21.5kg
- CO<sup>2</sup> Shield for safety
- Propane Gas or Petrol Powered
- Ultra quiet at only 58 dBA
- 12v DC Outlet
- True sine wave inverter technology
- Overload protection
- Parallel Connectable with optional ParaLINK kit
- Includes dual port USB adapter.
- Smart Economy Mode

# **3000 WATT** LPG DUAL FUEL INVERTER

93001i-DF



**Max AC output:** 

**Noise Level:** 58 dBA @ 7m

**Running Watts:** 2800/2520 (LPG)

3000

**Warranty:** 3 years

CE, UKCA, **Certification:** EU Stage V







Starting Watts	4500
Max Watts	3000
Rated Watts	2800 / 2520 LPG
AC Load	1 x 240v 16 Amp & 2 x 240v 13 Amp adapter (UK) 1 x 220v 16 Amp & 1 x 220v 16 Amp Schuko to Female Adapter (EU)
Frequency	50Hz
Engine	149cc Champion OHV
Fuel Capacity	4.5 Litres
Oil Capacity	0.58 Litres
Noise Level	58 dBA @ 7m
Start Type	Manual
Dimensions (L*W*H)	44 x 29.2 x 45 cm
Certification	CE, UKCA, EU Stage V
Weight (Kg)	21.5
Operation capacity (hr)	11.5 Hrs @ 25% load (Petrol)

## INCLUDED

- Oil Funnel
- **Dual USB Adapter**
- Propane Gas Pipe
- 16A-13A Adapter 12v DC battery Charging Cable





