



## 12 Hour In-Wall Preset Timer Switch

**Model No: HET06-12-W**

### Description

Wiring your lights or fan through a preset timer switch like the Enerlites HET06-12 can help save you money while adding a level of convenience and energy saving to your home. This Enerlites preset timer switch has the time adjustment from 30 minutes to 12 hours. This unit works with LED, incandescent, fluorescent lamp and fan motor; ideal for closet, pantry, garage, laundry room, basement, outdoor lighting, and home spas.

### Features

- 7 buttons preset timer switch.
- For use with LED, incandescent, fluorescent lights, and fan motor.
- Replace standard light or fan single pole switch.
- Neutral wire required
- Blue LED indicators constantly ON when the switch is not in use

- **Testing & Code Compliance**

### Specifications

Voltage	120VAC @ 60Hz
LED	150W
Incandescent	800W
Resistive	1800W
Fan motor	1/2HP
Time delay	30 minutes, 1-2-4-6-12 hour
Colors Available	White

