

HIGH ENERGY ALTERNATOR REGULATOR

Did you know? You Can Enable NMEA 2000 Messages









2. Select the "Live Details" in the upper-right corner.

÷				⇔ 🗉					
Battery	Battery	Engine	Alternator	Alternator					
Volts	Amps	RPM	Duty	Temp					
12.0V	22.0A	5050	30%	41°C					
Hold Standby									
↓ No Tach Detected									

3. Select "**Settings**" in the top-right corner.

← Live Details			=> 🗘					
Battery	Battery	Engine	Alternator	Alternator				
Volts	Amps	RPM	Duty	Temp				
11.0V	13.0A	5100	29%	39°C				
Hol	d Stand							
	⊾ No T	ach De	tected					

4. There will be a "**Warning**" screen. Select "**I Understand**".



ARCO ZEUS ENABLE NMEA 2000 MESSAGES



5. Select the "**Regulator**" tab near the bottom of the screen.



7. Upon selection, the dialog box message will vary depending on the previous state of the feature. Here, we are enabling the selection.



6. Scroll down until you locate the "Enable NMEA" Message Section.



8. Once you have "**Enabled**" the feature, select the save button in the top right-hand corner.



9. After the changes are made you will see a green check mark.

← 1	Regulator	Settings	C	⇒ 📀				
Battery	Battery	Engine	Alternator	Alternator				
Volts	Amps	RPM	Duty	Temp				
13.0V	13.0A	4900	15%	39°C				
Ho	d Stand							
No Took Datastad								



ARCO ZEUS INABLE RV-C MESSAGES