

# Patriot Single/Dual Bluetooth Headset Instructional Manual



## Contents:

1.Product Overview-----	1
2.Basic Operation-----	2
3.Bluetooth Pairing and Connection-----	3
4.Connecting Two devices-----	3
5.LED Indicator-----	4
6.Charging-----	4
7.TTS Tone-----	5
8.Product Specification-----	5
9.Q & A-----	6

## 1. Product Overview



Packing list:

- A. Patriot BT Headset x 1
- B. Type-C charge cable x 1
- C. User manual x 1



## 2.Basic Operation

Button	Function	Operation Instruction
MFB	Power On	Off status, long press 2 seconds to power on, until beep sound
	Power Off	On status, long press 3 seconds to power off, until beep sound
	Enter Pairing Mode	On headset press button until LED flashes blue light/red. Next Search phone blue tooth device named "M103" and select. Once connected( flashes 1 time every 10 seconds ), with prompt "Paired" on mobile device.
	Redial A Call	In connected standby mode, double press MFB to dial the last call.
	Voice Dialing	In connected standby mode, long press MFB for 1 second then release.
	Audio Switch	When during a call, long press for 2 seconds to switch
	Microphone mute	When during a call, short press to mute, press again to cancel
Volume +	Volume Up	Short press. (the maximum with the prompt "Di" )
	Next Song	Long press for 1 second.
Volume -	Volume Down	Short press.
	Previous Song	Long press for 1 second.
Phone Button	Answer a call	When a call incoming, short press to answer.
	Hang up a call	When during a call, short press to hang up.
	Reject a call	When a call incoming, long press for 1 second to reject the call.
	Three-way calling function	<ol style="list-style-type: none"> <li>1.Call coming during a call, short press to answer a new call and hang up the current call.</li> <li>2.Call coming during a call, double press to answer a new call and keep the current call.</li> <li>3.Call coming during a call, long press for 2 seconds to reject a new call.</li> <li>4.When you are on a three-party call, double press to switch audio between the current call and the keep call.</li> </ol>
	Play / Pause	Short press when play music.

### 3. Bluetooth Pairing and Connection

- A. Off status, long press 2 seconds to power on, with Red & Blue lights flicker alternately.
- B. Search and click to connect M103 on your phone Bluetooth lists, LED change to Blue slow flash once after connected, now you can play music from phone to headphone.
- C. You can press MFB / Volume+ / Volume- / Phone Button to control the answer/hang up a call and play/pause of the music, next and previous song, volume up and down, etc.

Pairing: Off status, long press 2 seconds to power on, with Red & Blue lights flicker alternately.

Search and click to connect "M103 on your phone Bluetooth list, LED change to Blue slow flash once after connected, now you can play music from phone to headphone.

2. Connect: search and click to connect" M103 " on your phone Bluetooth lists, LED turns into blue light and flashes slowly after connected( flashes 1 time every 10 seconds ), with prompt "Paired" .

### 4. Connection with Two devices

- Mobile phones connected to BT are divided into two sets: Machine A and Machine B.
- Connect machine A first, long press 2 seconds to enter pairing mode, turn on the Bluetooth of machine A and search for the device, search for "M103" and then click to connect. After the connection is successful, turn off the Bluetooth of machine A and M103 enters pairing mode again.
- Then use machine B to connect with M103, according to the method of machine A. After the pairing is successful, turn on the Bluetooth of machine A and click M103 to connect. (Some mobile phones may have the automatic connection function).



## 5. LED Indicator

Mode	LED Indicator
Power on	Blue LED flashes 2 times
Power off	Red LED flashes 2 times
Pairing mode	Red & Blue LED flash alternately
Connected standby mode	Blue LED flashes once every 10 seconds
Playing Music	Blue LED flashes once every 10 seconds
Talking	Blue LED flashes once every 10 seconds
Delete pairing record	Red & Blue LED are on for 1 second at the same time
Charging	Solid Red LED (It is normal that charging in the boot state will overlap with the Bluetooth function State light. )
Full charged	Solid Red Led to Solid Blue LED
Low battery	Red LED flashes

## 6.Charging

Please charge the Patriot BT Headset at once when Red LED flashes. Charging time is about 2 hours. Solid Red LED turns off and Blue Led turns on when full charged.

Charge Connections: Please connect BT through the Type-C end of Type-C charging cable.



Type-C charging cable / Charging with charger / Charging with PC

\*Note:

When not using consistently, charge the Patriot BT Headset at least one time every 2 months

## 7.TTS Tone

Power on	Power on
Enter paring mode	Pairing
Pair successfully	Paired
Connect successfully	Your headset is connected
Disconnect	Your headset is disconnected
Power off	Power off
Microphone mute on	mute on
Microphone mute off	mute off

## 8.Product Specification

Bluetooth Version	Bluetooth V5.0
Bluetooth Chipset	QCC3024
Operation Range	10 meters
Bluetooth Protocols	HSPv1.2 HFP v1.6 A2DP v1.3 AVRCP v1.5
Charging Time	About 2 hours
Calling Time	About 33hours (70% volume)
Working Time	About 35hours (70% volume)
Headset Net Weight	About 223g
Headset Dimension	197.54*18174.78*68.55mm

\*The above data are all from SKY WING laboratory, actual use time will vary based on usage and environment.



## 9. Attentions and Q & A

### A. How to reconnect and operation when failed to reconnect?

When Patriot BT Headset connect with your mobile phone successfully at the first time, it will search and reconnect the paired device automatically when power on, if failed, please pair and connect again. M103 can be reconnect in 10 minutes, will be power off if over 10 minutes. It will have a tone "Your headset is disconnected" after over operation range.

### B. How to delete paired records?

Long press MFB and Volume - Button for 5 seconds at the same time to clear the pairing record. After deleting, Patriot BT Headset will not connect devices automatically, needs to pair devices again.

### D. Pairing Password

Some connection devices require password for pairing, please try 0000 or 8888 or 1111 or 1234.

### D. What devices could charge for the headphone?

Any car charger, power bank, PC etc. which meet DC 5V, charging current more than 500mA could be charge for Patriot BT Headset.

### E. How to do if have connect issue or dead?

Please try charging reset, operation: plug in charging cable to charge, this will reset the headset to power off, it can be used normally after power on. If you still cannot use it normally, you can ask customer service or manufacturer for technical support.

### F. Power off automatically?

Patriot BT Headset will power off if does not connect any devices for over 10 minutes, or battery voltage is less than 3.1V.

### G. Three-way calling function operation?

1. Call coming during a call, short press Phone Button to answer the new call and hang up the current call.
2. Call coming during a call, double press Phone Button to answer the new call and keep the current call.

