


LMR BATTERY SPECIFICATIONS	PART NUMBER
	WV-7036-LI

COMPATIBLE RADIOS	Motorola XPR6100, XPR6300, XPR6350, XPR6380, XPR6500, XPR6550, XPR6580, Vertex Standard VXD720
REPLACES OEM BATTERY	PMNN4065, FNB-V116
COMPATIBLE CHARGERS	Endura EC1-MT16B, EC1M-MT16B, EC2M-MT16A-D, EC6M-MT16B, EC12M-MT16A-D / Logic LEVCA-MT16 / Motorola IMPRES 1 chargers
VOLTAGE	7.2V
CAPACITY	2500 mAh
CHEMISTRY / CELL TYPE	Li-Ion / Panasonic or equivalent
BATTERY TYPE	Smart
OPERATING TEMPERATURE	-20° C to +60° C (discharge) / 0° C to +40° C (charge)
CHARGE CYCLES	>300
CHARGE TYPE	Rapid
CONDITIONER COMPATIBLE	Smart battery conditions on Motorola IMPRES 1 chargers (conditioning not required for cycle life or battery run time)
PROTECTION TYPES	Over-charge / over-discharge / over-temperature
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
WARRANTY	12 months
PRODUCT PHOTO	 <div style="border: 1px dashed black; padding: 5px; margin-left: 20px;"> <p>Dimensions (HxWxD): 5.08" x 2.18" x 0.88" 129.0 x 55.4 x 22.4 mm</p> <p>Weight: 0.37 lbs.</p> </div>