


| | |
|-----------------------------------|-------------------|
| LMR BATTERY SPECIFICATIONS | PART NUMBER |
| | WVKAA010V2 |

| | |
|--------------------------|---|
| COMPATIBLE RADIOS | BK Technologies (RELM) / KNG Series: KNG-P150, KNG-P400, KNG-P500, KNG-P800 |
| REPLACES OEM BATTERY | KAA0100 |
| COMPATIBLE CHARGERS | Waveband WV-KNG150Pcharger, WV-R-KNG1506BANK BK2, EC12M-BK2A-D / BK Technologies KAA0300P |
| VOLTAGE | 10.8V |
| CAPACITY | 2200 mAh / 23.8 Wh |
| CHEMISTRY | Li-Ion |
| CELL TYPE | Panasonic or equivalent |
| OPERATING TEMPERATURE | -20° C to +60° C (discharge) / 0° C to +40° C (charge) |
| CHARGE CYCLES / TYPE | 300 / rapid |
| SMART BATTERY | Yes |
| CONDITIONER COMPATIBLE | Conditioning not required |
| PROTECTION TYPES | Over-charge / over-discharge / over-temperature |
| HOUSING MATERIAL / COLOR | ABS / black |
| HOUSING SEAL | Ultrasonic weld |
| METAL WELDING | Pure nickel tabs w/ spot welder |
| CLIP | Included |
| WARRANTY | 12 months |
| PRODUCT PHOTO |  |