REIGN

TX-100 / XRE-100 Transmitter & Receiver



WHEN A LONG RANGE TRANSMITTER / RECEIVER KIT WON'T REACH, TRY THE REIGN TX-100.

The Reign TX-100 / XRE-100 kit allow for triggering a dry contact relay using our proprietary wireless technology and our hand-held transmitter.

Forget about not being able to trigger your gate, door, alarm, or security panel. With the Reign TX-100 far is always reachable.

FEATURES

XRE-100 RECEIVER

- 2 Relays Latching or Momentary (Selectable w/ Jumper)
- Adjustable Delay Between Relays

TX-100 TRANSMITTER

- Micro-USB Rechargeable
- LED Notification for Transmit and Receive Verification
- Low Battery LED Indicator
- Adjustable Transmit Power





TX-100 / XRE-100 Transmitter & Receiver

SPECIFICATIONS

RECEIVER:

Security: AES128 Wireless Encryption

Operating Power: 12/24V AC/DC 12 V: 50mA (idle), 1A (transmit) 24 V: 25mA (idle), 500mA (transmit)

Dimensions: Box: 3-3/4"x 5-1/4" x 2" With Antenna: 3-3/4" x 10-1/2" x 2"

Temperature Range: -40°F to 185°F (-40°C to 85°C)

Relays: 2 Outputs: 3 Amp 250 v AC 3 Amp 220v DC 2 Inputs

Memory: 150 Transmitters

TRANSMITTER:

Power: Battery - Micro-USB Rechargeable

Dimensions: 2-3/8" x 3-1/2" x 3/4"

CONTACT US

TRANSMITTER SOLUTIONS PH 866.975.0101 FX 866.975.0404 www.transmittersolutions.com



TX-100



