IRB-325

Applications

- Complies with the UL 325 standard when used with steel hoods.
- The IRB-325 photocell is used as an external entrapment protection device type B1 non-contact sensor for use with automatic gate operators.
- Powder coated steel hoods help protect from damage.
- The IRB-325 transmitter and receiver are mounted in line of site at a distance of up to 65 feet.
- When the infrared beam is broken the IRB-325 produces a detection signal.

Sales Inquiries: salessupport@emxinc.com Technical Support: technical@emxinc.com



P. 800 426 9912 **F.** 216 518 9884

Accessories









IRB-325-PT

Technical Data

Range | 6 to 65 feet

Power 12 VDC to 24V AC/DC

Current Consumption 12 VDC Standby Detect, 24 V AC/DC Standby Detect

TX 47 mA

RX 33 mA 25 mA, 56 mA 38 mA

Relay Contact Rating 1A @ 30 VDC

t hatting

Housing UL and CSA Type 4, 4X, 3, 3R, 12, 13

Operating Temp. I-40°F to +170°F

Dimensions Housing Only
Dimensions Powder Coat Steel Hood

H=5.03" W=3.06" D=3.02"

H=6.7" W=3.3" D=4.4"

Ordering Information

- IRB-325 12 Infrared photocell, includes transmitter and receiver
- IRB-325-HD Set of two powder coated steel protective hoods (required)
- IRB-325-PT Mounting post 2in x 2in x 2 ft.
- IRB-325-SP Water tight strain relief for use with interconnecting cords

WARRANTY EMX INC. the product described herein for a period of 2 years under normal use and service from the date of sale to our customer. The product will be free from defects in material and workmanship. This warranty does not cover ordinary wear and tear, abuse, misuse, overloading, altered products, or damage caused by the purchaser from incorrect connections, or lightning damage. There is no warranty of merchantability. There are no warranties expressed, implied or any affirmation of fact or representation which extend beyond the description set forth herein. EMX Inc. sole responsibility and liability, and purchaser's exclusive remedy shall be limited to the repair or replacement at EMX's option of a part or parts not so conforming to the warranty. In no event shall EMX Inc. be liable for damages of any nature, including incidental or consequential damages, including but, not limited to any damages resulting from non-conformity defect in material or workmanship. Rev 2.1 07/09/08