

Z5 LED Video Controller

Specification V2.0





Overview

Z5, a new generation of professional LED video controller, is designed specially to meet the ultra-low latency display, HDR and wide color gamut needs of live event, broadcast, television, filming and other scenarios, where real time, low-latency processing and color fidelity is required for Ultra HD image and LED display control. Z5 includes features providing excellent vision effect for user.

Appearance



No.	Name	Description			
1	LCD screen	Displays the operation menu and system information.			
2	Knob	Select an item or adjust the parameter, press the knob to confirm your selection or adjustment.			
3	Function keys	 OK: confirm button. ESC: exit the current interface. Lock: lock buttons of front panel. Bright: tune brightness. Black: black screen. Freeze: freeze screen. SDI: switch to SDI signal. HDMI: switch to HDMI signal. DP: switch to DP signal. Part: crop or show the switch buttons in full screen. Test: test patterns. 			
4	Power switch	• Mode: select a preset. Power button.			



Rear panel



Cor	Control						
1	LAN	RJ45 port for accessing local area network.					
2	RS232	• RJ11(6P6C) port* for connecting to central control.					
	USB IN	• USB2.0 Type-B port, enabling connection to a PC for					
3		debugging or cascading input.					
	USB OUT	• USB2.0 Type-A port for cascading output.					
Ger	nlock						
		• 1× BNC port, male, for the input of an external					
		synchronization source.					
4	GENLOCK	Support Bi-level and Tri-level sync.					
4		• Support 23.98~60Hz frame rates.					
		• 1× BNC port, male.					
	GENLOCK LOOP	Loop out Genlock sync signal.					
3D							
5	3D*	4-pin S terminal connector, output 3D sync signal (optional,					
	30	for use with active 3D glasses).					
Inp	ut C						
		• 1× BNC port.					
	12G-SDI	Comply with SMPTE 2082/2081/424M/292M standards, and					
		support HD/3G/6G-SDI/12G-SDI (2SI format) / Level A/B.					
		• Maximum resolution: 4096×2160@60Hz.					
6		Support de-interlaced display.					
0		Not support EDID settings.					
	HDMI2.0	• 1 \times HDMI Type A port.					
		 Comply with HDMI 2.0 standard, support HDCP2.3 and 					
		compatible with HDCP1.4.					
		• Maximum resolution: 4096×2160@60Hz,minimum resolution:					

2



		800×600@60Hz,maximum pixel clock: 600MHz.
		Custom resolution:
		- Maximum width: 8192 (8192×1080@60Hz).
		- Maximum height:8192 (1080×8192@60Hz).
		• Support HDR.
		• Support independent EDID settings and comply with EDIDV1.3
		standard.
		Not support audio input.
		 Not support interlaced signal inputs.
		• 1× DisplayPort1.2.
		 Comply with DP1.2 standard, support HDCP2.3 and
		compatible with HDCP1.3.
		• Maximum resolution: 4096×2160@60Hz,minimum resolution:
		800×600@60Hz,maximum pixel clock: 600MHz.
		Custom resolution:
	DP1.2	- Maximum width: 8192 (8192×1080@60Hz).
		- Maximum height: 8192 (1080×8192@60Hz).
		• Support HDR.
		• Support independent EDID settings and comply with EDIDV1.3
		standard.
		Not support audio input.
		 Not support interlaced signal inputs.
Out	put	
		• 20-channel Gigabit Ethernet port, Neutrik (NE8FBH) port,
		compatible with standard RJ45 port.
	\mathcal{O}°	• Device load capacity:
		- Maximum width t is 16384 pixels, Maximum heigh is 8192
		pixels.
		- When output frame rate is 60Hz, 8bit color depth supports up
7	PORT 1-20	to 13.1 million pixels and 10bit supports up to 9.83 million
		pixels.
		- When output frame rate is 120Hz, 8bit color depth supports
		up to 6.55 million pixels and 10bit supports up to 4.91 million
		pixels.
		 Load capacity of one network port:
		- When output frame rate is 60Hz, 8bit color depth supports up
		- when output frame rate is 60Hz, 8bit color depth supports up



9	Power Socket	AC100-240V, 50 / 60Hz, built-in fuse.
Ροι	wer	
8	FIBER 1, FIBER 2	 module specifications). Automatically copy the output data of 20 network ports. FIBER 1 corresponds to network port PORT 1-10, fiber 2 corresponds to network port PORT 11-20. Select manually the signal output between network ports and fiber.
		• 2-channel 10G output fiber port (purchase separately10G SFP+ optical module, transmission distance depends on optical
		 to 650 thousand pixels and 10bit supports up to 490 thousand pixels. When output frame rate is 120Hz, 8bit color depth supports up to 320 million pixels and 10bit supports up to 240 million pixels.

*The equipment shown in the picture is for reference only. Due to the difference of boards assembled, the appea rance of the equipment may be different from the picture. Please refer to the actual product.

* The illustration is for reference only. Since the appearance of equipment may vary due to different production process, please refer to the actual product.

* The schematic of RJ11 (6P6C) to DB9 cable is shown as follows:





Features

Input

- Full 4K inputs: HDMI2.0, DP1.2, 12G-SDI.
- Single port supports up to 4096 ×2160@60Hz.
- Support 8bit / 10bit video signal input.
- Support HDCP1.4/HDCP1.3/HDCP2.3.
- Support input frame rate from 23.98Hz to 240Hz.

Output

- Maximum capacity of 13.1 million pixels, with maximum 16384 pixels in width or 8192 pixels in height.
- 20-channel Gigabit Ethernet port output; 2-channel 10 Gigabit fiber port output, choose any of two types.
- Support output frame rate of 23.98Hz to 240Hz.
- Support both Ethernet port redundancy and controller redundancy.

Video processing

- Video signal cropping, switching, and broadcasting level scaling.
- Multi-screen display (maximum three screens)
- Low latency, a minimal latency of one frame.
- Lag-free processing, 0 frame delay at minimum
- HDR10/HLG display.
- Genlock.
- Crossfade of a single layer
- Virtual pixel, support 3x virtual and 4x virtual
- Multi-function card automatic brightness

Color adjustment

- Picture adjustment for hue, saturation, contrast, and brightness compensation.
- Brightness adjustment, support network port grouping brightness adjustment.
- Color temperature adjustment with precision and RGB independent adjustment.

Control

- USB port for control and cascading.
- RS232 port.
- LAN port for TCP/IP control.



Signal format

	Max Resolution	Color space	Sam pling	Color depth	Frame rate(Hz)
Input					
		YCbCr	4:2:0	8,10bit	60
	4000-2100	YCbCr	4:2:2	8,10,12bit	23.98,24,25,29.97,30,50, 59.94,60
	4096x2160	YCbCr/RGB	4:4:4	8,10,12bit	23.98,24,25,29.97,30
4K		YCbCr/RGB	4:4:4	8bit	50,59.94,60
	3840x2160	YCbCr	4:2:2	8,10,12bit	23.98,24,25,29.97,30,50, 59.94,60
		YCbCr/RGB	4:4:4	8,10,12bit	23.98,24,25,29.97,30
		YCbCr/RGB	4:4:4	8bit	50,59.94,60
	2048x1080	YCbCr	4:2:2	8,10,12bit	23.98,24,25,29.97,30,50, 59.94,60
		YCbCr/RGB	4:4:4	8,10,12bit	
	1920x1080	YCbCr	4:2:2	8,10,12bit	
217		YCbCr/RGB	4:4:4	8,10,12bit	23.98,24,25,29.97,30,50, 59.94,6
2K	2048x1080	YCbCr	4:2:2	8bit	100.100
		YCbCr/RGB	4:4:4	8bit	100,120
	1920x1080	YCbCr	4:2:2	8bit	100 100 240
		YCbCr/RGB	4:4:4	8bit	100,120,240

Only some of the regular resolutions are shown above.

DP1.2

Input	Max Resolution	Color space	Sam pling	Color depth	Frame rate(Hz)
	4096x2160	YCbCr	4:2:2	8,10bit	
4K		YCbCr/RGB	4:4:4	8,10bit	
4N	3840x2160	YCbCr	4:2:2	8,10bit	23.98,24,25,29.97,30,50, 59.94,60
		YCbCr/RGB	4:4:4	8,10bit	
	2048x1080	YCbCr	4:2:2	8,10bit	23.98,24,25,29.97,30,50, 59.94,60
		YCbCr/RGB	4:4:4	8,10bit	
	1920x1080	YCbCr	4:2:2	8,10bit	
214		YCbCr/RGB	4:4:4	8,10bit	
2K	2048x1080	YCbCr	4:2:2	8bit	
		YCbCr/RGB	4:4:4	8bit	
	1920x1080	YCbCr	4:2:2	8bit	100,120,240
		YCbCr/RGB	4:4:4	8bit	
Only so	me of the regula	r resolutions are	shown al	pove.	



Input	Max Resolution	Color space	Sam pling	Color depth	Frame rate (Hz)
120	4096x2160p	YCbCr	4:2:2	10bit	F0 F0 04 C0
12G	3840x2160p	YCbCr	4:2:2	10bit	50,59.94,60
66	4096x2160p	YCbCr	4:2:2	10bit	23.98,24,25,29.97,30
6G	3840x2160p	YCbCr	4:2:2	10bit	23.98,24,25,29.97,30
3G	2048x1080p	YCbCr	4:2:2	10bit	
Level A/B	1920x1080p	YCbCr	4:2:2	10bit	50,59.94,60
	2048x1080p	YCbCr	4:2:2	10bit	23.98,24,25,29.97,30
HD	1920x1080p	YCbCr	4:2:2	10bit	23.98,24,25,29.97,30
	1920x1080i	YCbCr	4:2:2	10bit	50,59.94,60
	1280x720p	YCbCr	4:2:2	10bit	23.98,24,25,29.97,30,50, 59.94,60

Only some of the regular resolutions are shown above.



Parameters

Dimensions (W×H×D)			
Unboxed	482.6mm (19") \times 88.0mm (3.4") \times 407.1mm (16.0"), 2U chassis (w / o			
UNDOXED	foot pads)			
Boxed	655.0mm (25.7")×245.0mm (9.6")×615.0mm (24.2")			
Weight				
Net weight	5.85kg (12.90lbs)			
Total weight	7.65kg (16.87lbs)			
Electrical speci	fication			
Power input	AC100-240V, 50 / 60Hz			
Rated power	75W			
Operating envi	ronment			
Temperature	-20°C~55°C (-4°F~131°F)			
Humidity 0%RH-90%RH, no-condensing				
Storage enviro	nment			
Temperature	-30°C~80°C (-22°F~176°F)			
Humidity	0%RH-90%RH, no-condensing			
Certification				
CCC, CE, FCC, C	B, IC, cTUVus.			
* If there is no certification for the country or region where the product is sold, please contact Colorlight to				

confirm it right away. Otherwise, if the relevant legal risks are caused, the customer shall bear it or Colorlight has the right of recourse.

0



Application





Reference dimensions

Unit: mm





Statement

Copyright © 2024 Colorlight Cloud Tech Ltd. . All rights reserved.

Without the express written permission of Colorlight Cloud Tech Ltd., no unit or individual may copy, copy, transcribe or translate part or all of the contents of this book. Not to be used for any commercial or profit-making purposes in any form or by any means.

Colorlight [®] The logo is a registered trademark of Colorlight Cloud Tech Ltd.

Without the written permission of the company or the trademark owner, no unit or individual may in any way or for any reason use, reproduce, modify, disseminate, transcribe or infringe all or any part of the above-mentioned trademark, nor may it be bundled with other products. Use sales. As factors such as product batches and production processes may change, in order to provide accurate product information, specification parameters, and product characteristics in order to match the actual product, the text description and picture effects in the document will be adjusted and revised appropriately. If it is necessary to carry out the above modification and adjustment without prior notice, please refer to the actual product.

Welcome to choose to use the products of Colorlight Cloud Tech Ltd. If you have any questions or suggestions in use, please contact us through official channels, we will try our best to support and listen to your valuable suggestions. For more information and updates, please visit the official website www.colorlightinside.com or scan the QR code.



Colorlight Cloud Tech Ltd.

Official Website: www.colorlightinside.com Head Office Address:Room 37F-39F,Building 8, Zone A, Shenzhen International Innovation Valley, Vanke Cloud City, Dashi Yilu, Nanshan District, Shenzhen, China

