



VAPORESSO™
Beyond the ordinary

Target Mini Quick Guide

Thank you for choosing Vaporesso Products!

Target Mini is the ultimate TRUE pocket mod, the best tool to keep your habit low profile, classy, and clean. With 40watts of maximum output and a built in battery of 1400 mAh, the Target mini will be your favorite day to day mod. This mod comes equipped with one of the most highly advanced tanks on the market, the Guardian Tank: fit to measure up to all new legal restrictions and deliver all the taste you want with our reinvented CCELL technology coils inside. It is by far the smallest mod in the market. Target Mini, Small and Smart!

Please read this manual carefully to ensure proper use. For additional information or questions regarding to this product or its use, please visit www.vaporesso.com

Main features

- Mini Design, Easy to Carry
- More output Modes: VM/VT(Ni, SS,Ti)/TCR(M1,M2)
- Advanced Circuit for Reliable and Safe Use
- With Guardian Tank with revolutionary Leak Free Design
- No Overfill Ever, top filling with coil remains inside the tank
- Double Child Locking Mechanism
- 2 in 1 Tank (DTL + MTL), Easy Switch between 2 settings
- CCELL Ceramic Coil Inside

Package Include

- 1 x Target Mini Mod
- 1 x Guardian Tank with CCELL-GD SS 0.5Ω coil preinstalled
- 1 x Extra CCELL-GD MTL 1.4Ω coil
- 1 x Mouthpiece for MTL
- 1 x USB charging cable
- 1 x User Manual

Specification

Guardian Tank

- Diameter:** 22 x 55 mm
- Weight:** 60 g
- Capacity:** 2.0 ml

How to Use

- 1.Switch On/Off:** Connect the Guardian Tank onto the Box. Then press the fire button 5 times in quick succession within 2 seconds to turn the device on. In the same way, the device will be powered off after 5 presses.
- 2.Adjust Wattage:** Press the "+" "-" to adjust the wattage at 0.1 increment long-press will adjust at an accelerated rate.
- 3.Swith Modes:** Press the mode button for 2 seconds to switch between wattage mode and different temperature control modes.
- 4.TCR:** To enter TCR settings, press the mode button 3 times consecutively then use the "+" and "-" buttons to set the desired coefficient of resistance for your wire. hold the mode button 2 seconds to exit this screen.
- 5.Lock the System:** Press the mode button and "+" button simultaneously, the system will be locked with "system lock" on the screen.
- 6.Lock the Resistance :** Press the mode button and "-" button simultaneously, the resistance will be locked
- 7.To rotate the screen display:** Press the "+" and "-" button simultaneously, the display screen will be rotated.
- 8. How to vape:** Hold the fire button and inhale through the mouthpiece. Release the fire button and exhale.
- 9.Switch between DTL/MTL settings:** The tank is pre-installed with DTL setting. To switch between such modes it is necessary to match the coil in use with the mouthpiece type. The 1.0 ohm SS CCELL coil intended use is with the thinner mouthpiece for MTL and the 0.5 ohm coil shall be matched with the wider mouthpiece for DTL.
- 10.Charging:** Simply charge the Target Mini by connecting it to a PC or suitable wall adapter via USB cable included. Once plugged in, the charging indicator will display the progress.

Notes:

- 1.When there is no operation on the device for 20 seconds after it is on, the display will go off automatically. The screen will be on by pressing any button.
- 2.When there is no operation on the device for 3 minutes after it is on, the device will standby automatically. It would be activated by pressing any button.

Function:

Short Circuit Protection: The display will indicate and lock the system accordingly when firing causes a short circuit

No Atomizer Protection: the display will let you know when no atomizer is detected and won't "blank-fire"

Low Voltage Protection: When the battery voltage is too low, it will indicate on the display and will prevent use

Over Vaping Protection: When the fire button is pressed for more than 10 seconds, it will automatically stop

Over Charging Protection: When the battery voltage is higher than 4.15V, the light will go off and stop charging automatically

Low Battery Protection: When the battery is under 10% it shall indicate "low battery"

Caution

- 1.The Target Mini is intended for usage by people over 18, NOT by non-smokers, children, pregnant or breastfeeding women, people with or at risk of heart disease, or people taking medication for depression or asthma. The electronic cigarette is not a smoking cessation device.
- 2.Please keep this unit out of reach of children or pets;
- 3.Please don't drop, throw or abuse your Target Mini, it may cause damage;
- 4.Please keep the battery dry;
- 5.Do not place it in extremely temperatures;
- 6.Do not try to disassemble the battery;
- 7.This device does not mean to be used as a nicotine replacement therapy for smoking cessation.



Target Mini Mod

Diameter: 36.5 x 24.2 x 58.1 mm

Weight: 93 g

Temperature Range: 100°C-315°C/200F-600F

Output Wattage: 5-40w

Suitable atomizer: VW:0.15Ω-5Ω / VT:0.1Ω-1.0Ω

Standby Current: < 30uA

Voltage range: 0-9v

Battery Cell: Lithium 1400mAh Built In

Casting: Zinc Alloy and stainless steel

Thread: 510 thread

Display: 0.49" OLED