



# HP LaserJet Pro MFP M130 series

Keep things simple with a compact HP LaserJet Pro MFP powered by JetIntelligence Toner cartridges.

Print professional documents from a range of mobile devices,<sup>1</sup> plus scan, copy, fax, and help save energy with a wireless MFP designed for efficiency.



HP LaserJet Pro MFP M130a



HP LaserJet Pro MFP M130nw

## Designed for efficiency

- Print, scan, copy, and fax with a compact HP LaserJet MFP that fits into tight workspaces.
- Wait less. Print up to 23 pages per minute,<sup>2</sup> with first pages ready in as fast as 7.0 seconds.<sup>6</sup>
- Help save energy with HP Auto-On/Auto-Off Technology.<sup>7</sup>
- Tackle tasks and scan to email, USB, and network folders from the 2.7-inch (6.9 cm) color touchscreen.<sup>8,11</sup>

## Mobile printing made simple<sup>11</sup>

- Get simple setup, and print and scan from your phone, with the HP Smart app.<sup>3</sup>
- Easily print from a variety of smartphones and tablets.<sup>9</sup>
- Print directly from your mobile device to your Wi-Fi Direct® printer—without accessing the company network.<sup>4</sup>
- HP Voice-activated printing—your HP printer works with Amazon Alexa, Google Assistant, Microsoft Cortana.<sup>5</sup>

## HP quality—print after print

- Produce sharp text, bold blacks, and crisp graphics with precision black toner.
- Don't be fooled by alternatives that mimic Original HP. Innovative anti-fraud technology can help ensure you're getting the quality you paid for.
- Track remaining pages with print gauge technology, and get more pages than ever with page maximizer technology.
- No delays or mess—quickly replace your cartridges, using auto seal removal and easy-open packaging.

## Product walkaround



HP LaserJet Pro MFP M130nw

1. Flatbed scanner handles up to 216 by 297 mm paper
2. 100-sheet output bin
3. 2-line LCD
4. Hi-Speed USB 2.0 port, Fast Ethernet network port, access port for optional lock
5. Top cover access to toner cartridges
6. Wi-Fi Direct® printing<sup>1</sup>
7. Built-in wireless networking (802.11b/g/n)<sup>2</sup>
8. 150-sheet input tray with dust cover

## Series at a glance



Model	HP LaserJet Pro MFP M130a	HP LaserJet Pro MFP M130nw
Product number	G3Q57A	G3Q58A
Control panel	LCD	2-line LCD
Print speed	Up to 22 ppm, A4	
150-sheet input tray with dust cover, 100-sheet output bin	Yes	
USB connectivity	Yes	
Ethernet networking	Not available	Yes
Wi-Fi Direct <sup>1</sup> and wireless networking <sup>2</sup>	Not available	Yes
Mobile printing: Apple AirPrint, <sup>3</sup> HP ePrint, <sup>4</sup> Google Cloud Print™ 2.0, <sup>5</sup> Mopria-certified	Not available	Yes

## HP Services

Downtime can have serious consequences, so HP provides support beyond the standard warranty. You benefit from reduced risk, maximized uptime, predictable service delivery and no unbudgeted repair costs.

Choose from:

**Optimized Care (optimum performance and stability):**

4 hour Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configuration Service

**Standard Care (high level of uptime):**

Next Business Day Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configuration Service

**Basic Care (minimum recommended support):**

Next Business Day Onsite Support

**4 hour Onsite Support:**

Onsite support within four hours after a service call received within the coverage window

**Next Business Day Onsite Support:**

Onsite service the next business day after the service call is received

**Maintenance Kit Replacement Service:**

Onsite replacement of your printer's maintenance kit including parts, materials, and labor

**Installation with Network Configuration Service:**

Assembly, network configuration, and basic administrator familiarization. For more information about HP Care Pack, HP Contractual, or HP Managed Print Services, visit [hp.com/go/printservices](http://hp.com/go/printservices)

## Top features

Help save energy. This efficient multifunction laser printer prints, scans, copies, and faxes while keeping energy costs low, so you save resources.

Mobile printing is easier than ever with HP. Print with minimal steps from a broad range of mobile devices—smartphones, tablets, and notebooks.<sup>1</sup>

Count on consistent results—Original HP Toner cartridges with JetIntelligence are designed to work flawlessly with this HP LaserJet Pro. Anti-fraud authentication helps protect your business from frustrating quality issues and costly reprints.

---

**Product**

**G3Q57A** HP LaserJet Pro MFP M130a  
**G3Q58A** HP LaserJet Pro MFP M130nw

**Supplies**

**CF217A** HP 17A Black Original LaserJet Toner Cartridge (1,600 pages)  
**CF219A** HP 19A Original LaserJet Imaging Drum (12,000 pages)

**HP Care Packs**

**UH757E** HP 3 year Care Pack w/Next Day Exchange for LaserJet Printers  
**UH773E** HP 3 year Care Pack w/Onsite Exchange for LaserJet Printers  
**UH769E** HP 3 year Care Pack w/Pickup and Return Support for LaserJet Printers  
**UH764E** HP 3 year Care Pack w/Return to Depot Support for LaserJet Printers

Protect your investment with HP Care Pack. Let HP certified engineers resolve your technical issues. For more details on HP Care Pack, go to [hp.com/go/cpc](http://hp.com/go/cpc)

**Paper**

Contact HP via phone: Asia: 65 6253 8500

**Solutions**

HP Web Jetadmin: [hp.com/go/wja](http://hp.com/go/wja)  
 HP Universal Print Driver: [hp.com/go/upd](http://hp.com/go/upd)  
 HP Imaging and Printing Security Center: [hp.com/go/ipsc](http://hp.com/go/ipsc)

---



HP Care Pack

## HP LaserJet Pro MFP M130 series

Model	HP LaserJet Pro MFP M130a	HP LaserJet Pro MFP M130nw
Product number	G3Q57A	G3Q58A
Functions	Print, copy, scan	
<b>Print</b>		
Duplex print options	Manual duplex	
Print speed	<b>Black (A4, normal):</b> Up to 22 ppm; <b>Black (letter, normal):</b> Up to 23 ppm	
First page out	<b>Black (A4, ready):</b> As fast as 7.4 sec; <b>Black (A4, sleep):</b> As fast as 8.3 sec	<b>Black (A4, ready):</b> As fast as 7.0 sec; <b>Black (A4, sleep):</b> As fast as 7.5 sec
Print technology	Laser	
Print resolution	<b>Black (best)</b> Up to 600 x 600 dpi, HP FastRes 1200 (1200 dpi quality); <b>Black (normal)</b> Up to 600 x 400 dpi, HP FastRes 600 (600 dpi quality)	
Print resolution technology	HP FastRes 600, HP FastRes 1200	
Print cartridges number	1 Black	
Standard print languages	PCLmS, URF, PWG	
Printer management	HP Printer Assistant (UDC); HP Device Toolbox; HP Utility (Mac)	
<b>Scan</b>		
Scan technology	<b>Type:</b> Flatbed; <b>Technology:</b> CIS	
Scan resolution	<b>Hardware:</b> Up to 600 x 600 dpi (color, flatbed); Up to 1200 x 1200 dpi (mono, flatbed); <b>Optical:</b> Up to 600 dpi (color, flatbed); Up to 1200 dpi (mono, flatbed)	
Digital sending standard features	No	
Color scanning	Yes	
Scan Size	<b>Flatbed:</b> 215.9 x 297 mm	
Scan input modes	Scanning via HP LaserJet Scan (Windows®); HP Director (Macintosh) or TWAIN-compliant or WIA-compliant software	
Scan file format	JPEG, PDF, PNG	
<b>Copy</b>		
Copier smart software features		ID Copy
First copy out	<b>Black (A4):</b> As fast as 10.1 sec; <b>Black (A4, sleep):</b> As fast as 10.9 sec; <b>Black (letter):</b> As fast as 9.6 sec	<b>Black (A4):</b> As fast as 10 sec; <b>Black (A4, sleep):</b> As fast as 10.9 sec; <b>Black (letter):</b> As fast as 9.5 sec; <b>Black (letter, sleep):</b> As fast as 10.1 sec
Copy resolution	<b>Black (text and graphics):</b> 600 x 400 dpi	
Max no of copies	Up to 99 copies	
Copier resize	25 to 400%	
Copier settings	Number of Copies; Lighter/Darker; Optimize; Paper; Multi-Page Copy; Draft Mode	
<b>Fax</b>		
Fax Features	Auto fax reduction supported: No; Auto-redialing: No; Fax delayed sending: No; Distinctive ring detection supported: No; Fax forwarding supported: No; Junk barrier supported: No; PC interface supported: No	
Fax smart software features	No	
<b>Connectivity</b>		
Standard connectivity	Hi-Speed USB 2.0 port (device)	Hi-Speed USB 2.0 port (device); built-in Fast Ethernet 10/100Base-TX network port; wireless
Mobile printing capability	No	Apple AirPrint™; HP ePrint; Google Cloud Print 2.0; Mopria-certified; Wi-Fi Direct; HP Smart App
Network ready	No	Standard (built-in Ethernet, Wi-Fi 802.11b/g/n)
Wireless capability	No	Standard (Wi-Fi 802.11b/g/n)
Network capabilities	No	10/100 Ethernet
Memory	Standard: 128 MB; Maximum: 128 MB	Standard: 256 MB; Maximum: 256 MB
Hard disk	No	
Processor speed	600 MHz	
Duty cycle (monthly) <sup>9</sup>	Up to 10,000 pages; <b>Recommended monthly page volume</b> <sup>10</sup> : 150 to 1500	
<b>Paper handling</b>		
Input	150-sheet input tray	
Output	100-sheet output tray	
Media types	Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, postcards	
Media Sizes Custom	76 x 127 to 216 x 356 mm	
Dimensions (w x d x h)	398 x 288 x 231.1 mm	
Weight	6.8 kg	
What's in the box <sup>1</sup>	HP LaserJet Pro MFP M130a; Introductory HP Black LaserJet Toner Cartridge ~700 pages; HP LaserJet Imaging Drum ~12,000 pages; Power cord; USB cable (AP); Getting started guide; Set up poster; Support flyer; Warranty documents (CN, Indo, AU, Mex, BR, AG); Printer documentation and software on CD-ROM; Errata declaration (some countries)	HP LaserJet Pro MFP M130nw; Introductory HP Black LaserJet Toner Cartridge ~700 pages; HP LaserJet Imaging Drum ~12,000 pages; Power cord; USB cable; Getting started guide; Set up poster; Support flyer; Warranty documents (CN, Indo, AU, Mex, BR, AG); Printer documentation and software on CD-ROM; Errata declaration (some countries)
Software included	For Windows OS: HP Software Installer, HP Software Uninstaller (exclude Win8+), HP PCLmS Printer Driver, HP Device Experience (DXP), HP Web Services Assist (HP Connected), Device Setup & Software, Online user manuals, HP Printer Assistant, HP Scan Driver, HP Scan Application, HP Fax Driver (4:1 bundle only), HP Fax Application (4:1 bundle only), HP Product Improvement Study; For Mac OS: Welcome Screen, (Directs users to HP.com or OS App Source for LaserJet Software)	
Warranty features	one year limited warranty	
<b>Systems</b>		
Compatible operating systems <sup>1a</sup>	Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer; Windows Vista®: (32-bit only), 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8; Windows® XP SP3 or higher (32-bit only); any Intel® Pentium® II, Celeron® or 233 MHz compatible processor; 850 MB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8; Apple® OS X El Capitan (v10.11) OS X Yosemite (v10.10) OS X Mavericks (v10.9), 1 GB HD; Internet required; USB; Linux (For more information, see <a href="http://hplipopensource.com/hplip-web/index.html">http://hplipopensource.com/hplip-web/index.html</a> )	
Minimum system requirements	<b>PC:</b> Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer; Windows Vista®: (32-bit only), 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8; Windows® XP SP3 or higher (32-bit only); any Intel® Pentium® II, Celeron® or 233 MHz compatible processor; 850 MB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8; <b>Mac:</b> Apple® OS X El Capitan (v10.11) OS X Yosemite (v10.10) OS X Mavericks (v10.9); 1 GB HD; Internet required; USB	
Security management		Password-protected network embedded Web server; enable/disable Network ports; SNMPv1 community password change
Control panel	ICON LCD: Dual digit numeric LCD display; Buttons (Up, Down, Cancel, Start Copy, Copy Setup); 3 LED indicator lights (Ready, Attention, Toner); Copy setting icons (Copies, Darker/Lighter, Reduce/Enlarge)	2-line LCD: 2-line LCD text display; Buttons (OK, Back, Forward/Backward, Cancel, Number of Copy, Darker/Lighter, Copy Menu, Start Copy, Main Setup, Wireless); 3 light-emitting diode (LED) indicator lights (Ready, Attention, Wireless).
Display	ICON LCD	
Energy efficiency compliance	ENERGY STAR® qualified	
ENERGY STAR Qualified	Yes	
Power	<b>Power supply type:</b> Internal; <b>Power supply required:</b> 110-volt input voltage: 110 to 127 VAC (+/- 10%), 60 Hz/50 Hz, 4.8 A; 220-volt input voltage: 220 to 240 VAC (+/- 10%), 60 Hz/50 Hz, 2.8 A; <b>Power consumption:</b> 255 watts (active printing), 4.2 watts (ready), 1.0 watts (sleep), 0.7 watts (Auto Off/Wake on USB, enabled at shipment); <b>Typical Electricity Consumption number:</b> 0.627 kWh/Week (Blue Angel); 0.285 kWh/Week (Energy Star 3.0)	
Acoustics	<b>Acoustic power emissions:</b> 6.5 B(A) (printing at 23 ppm) ; <b>Acoustic power emissions (ready):</b> 2.6 B(A) ; <b>Acoustic pressure emissions bystander (active, printing):</b> 51 dB(A) ; <b>Acoustic pressure emissions bystander (ready):</b> 16 dB(A)	
Environmental ranges	<b>Operating temperature range:</b> 15 to 32.5°C ; <b>Recommended operating temperature:</b> 17.5 to 25°C ; <b>Non-operating humidity range:</b> 10 to 90% RH ; <b>Operating humidity range:</b> 10 to 80% RH ; <b>Recommended operating humidity range:</b> 30 to 70% RH	
Safety approvals and requirements	IEC 60950-1:2005 +A1:2009+A2:2013/EN60950-1:2006 +A1:2009 +A1:2010+A1:2011+A2:2013, IEC 60825-1:2007 / EN 60825-1:2007 (Class 1 Laser/LED Product), IEC 62479:2010 / EN 62479:2010, GB4943-2011	
Supported network protocols	No	TCP/IP; IPv4; IPv6; IP Direct Mode; LPD; SLP; Bonjour; WS-Discovery; BOOTP/ DHCP/ AutoIP; WINS; SNMP v 1/2/3; and HTTP/HTTPS

## Footnotes

- <sup>1</sup> App or software and HP ePrint account registration also may be required. Some features require purchase of an optional accessory. Learn more at <http://www.hp.com/go/mobileprinting>
- <sup>2</sup> Printing speed measured using ISO/IEC 24734 and excludes first set of test documents. Exact speed versus predecessor varies depending on the system configuration, software application, driver, and document complexity. Learn more at <http://www.hp.com/go/printerclaims>.
- <sup>3</sup> Requires the HP Smart app download. Features controlled may vary by mobile device operating system. Full list of supported operating systems and details at <http://support.hp.com/us-en/document/c03561640>. For details on local printing requirements see <http://hp.com/go/mobileprinting>.
- <sup>4</sup> Feature is supported on select printers. Mobile device needs to be connected directly to the signal of a Wi-Fi Direct® supported MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. For details, see <http://www.hp.com/go/mobileprinting>. Wi-Fi Direct is a registered trademark of Wi-Fi Alliance®.
- <sup>5</sup> Requires Amazon Alexa, Google Assistant, or Microsoft Cortana and an HP web-connected printer registered with Google Cloud Print or ePrint. For ePrint account registration, see <http://www.hp.com/go/support/eprint>.
- <sup>6</sup> Measured using ISO/IEC 17629. Exact speed varies depending on the system configuration, software application, driver, and document complexity. Learn more at <http://www.hp.com/go/printerclaims>.
- <sup>7</sup> HP Auto-On/Auto-Off Technology capabilities are subject to printer and settings.
- <sup>8</sup> Requires an Internet connection to the printer. Services may require registration. App availability varies by country, language, and agreements. For details, see [hpconnected.com](http://hpconnected.com).
- <sup>9</sup> For details on local printing requirements see <http://hp.com/go/mobileprinting>.
- <sup>10</sup> As compared with cartridge gauges for HP predecessor products.
- <sup>11</sup> Features are available only in selected printers.

## Product walkaround disclaimers

- <sup>1</sup> Wi-Fi Direct® printing is available with the HP LaserJet Pro MFP M130nw model only. Mobile device needs to be connected directly to the signal of a Wi-Fi Direct supported MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. For details, see <http://www.hp.com/go/mobileprinting>. Wi-Fi Direct is a registered trademark of Wi-Fi Alliance®.
- <sup>2</sup> Wireless networking is available with the HP LaserJet Pro MFP M130nw model only. Wireless performance is dependent on physical environment and distance from access point, and may be limited during active VPN connections.
- <sup>3</sup> Mobile device must have iOS v7.0 or higher. Learn more at [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting).
- <sup>4</sup> Printer requires ePrint account registration. App or software may be required. Learn more at [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting).

## Technical specifications disclaimers

- <sup>1</sup> Introductory HP Black LaserJet Toner Cartridge (~700 pages), HP Original LaserJet Imaging Drum (~12,000 pages). Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies>
- <sup>2</sup> Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Power consumption values typically based on measurement of 115 V device.
- <sup>3</sup> Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of device.
- <sup>4</sup> Based on the BA TEC method with the following possible exceptions: 1 minute or less sleep delay setting, Wi-Fi disabled.
- <sup>5</sup> Declared yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies>.
- <sup>6</sup> Declared yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies>.
- <sup>7</sup> HP SureSupply alerts you when your print cartridge is running low and helps you purchase online or locally through HP or a participating retailer. Only available with Original HP supplies; Internet access required. To learn more, visit <http://www.hp.com/go/SureSupply>.
- <sup>8</sup> Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups.
- <sup>9</sup> HP recommends that the number of printed pages per month be within the stated range for optimum device performance, based on factors including supplies replacement intervals and device life over an extended warranty period.
- <sup>10</sup> Measured using ISO/IEC 24734, excludes first set of test documents. For more information see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the system configuration, software application, driver, and document complexity.
- <sup>11</sup> Measured using ISO 24734 Feature Test, A5 Landscape Feed. Speed may vary based on content, PC, media orientation, and media type.
- <sup>12</sup> Measured using ISO/IEC 17629. For more information see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the system configuration, software application, driver, and document complexity.
- <sup>13</sup> First Copy Out and Copy Speed measured using ISO/IEC 29183, excludes first set of test documents. For more information see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the system configuration, software application, driver, and document complexity.
- <sup>14</sup> Based on standard ITU-T test image #1 at standard resolution. More complicated pages or higher resolution will increase the transmission time.
- <sup>15</sup> HP recommends that the number of scanned pages per month be within the stated range for optimum device performance.
- <sup>16</sup> Not supporting Windows® XP (64-bit) and Windows Vista® (64-bit). Not all "Compatible Operating Systems" are supported with INBOX software. Full solution software available only for Windows 7 and newer. Legacy Windows Operation Systems (XP, Vista, and equivalent servers) drivers only. For Windows Server 2003 32-bit and 2008 32-bit and 64-bit, 2008 R2 64-bit, 2012 64-bit, 2012 R2 64-bit only drivers (print/scan/fax) are installed, Windows RT OS for Tablets (32- & 64-bit) uses a simplified HP print driver built into the RT OS. Linux systems use in-OS HPLIP software

To learn more, visit <http://www.hp.com>

