

# Gavita Pro 1000<sup>e</sup> DE US



## General product information

Product name:	Gavita Pro 1000 <sup>e</sup> DE US
Manufacturer:	Gavita International bv
Version:	120 - 240 V US
Part number:	18.60.14.14.20

## Compatible products and accessories

	Product name	Gavita part number
Controllers:	Gavita Master Controller EL1	41.00.12.20
	Gavita Master Controller EL2	41.00.13.20
Reflectors:	Gavita Pro HR 96 DE reflector	31.46.13.00
	Gavita Pro W 150 DE reflector	31.26.13.00
	Gavita Pro M 110 DE SR reflector	30.27.13.00
Lamps:	Gavita Pro Plus 1000W EL DE HPS	26.10.16.12
Power cords:	Power cord US 120 V, 16 ft / 5 meter	44.30.41.11
	Power cord US 240 V, 8 ft / 2,5 meter	44.30.41.10
Interconnect cables:	Interconnect cable RJ14, 2 ft / 0,6 meter	43.50.00.08
	Interconnect cable RJ14, 5 ft / 1,5 meter	43.50.00.04
	Interconnect cable RJ14, 8 ft / 2,4 meter	43.50.00.09
	Interconnect cable RJ14, 10 ft / 3 meter	43.50.00.10
Splitter:	3 way RJ14 cable splitter	43.50.00.01

## Technical specifications

Product name:	Gavita Pro 1000 <sup>e</sup> DE US		
Input voltage +/- 10%:	120 Volt AC	208 Volt AC	240 Volt AC
Frequency:	50 - 60 Hz		
Input current at 100%:	9.8 Amps	5.1 Amps	4.4 Amps
Input current at 115%:	10.2 Amps	5.8 Amps	5.1 Amps
Input power at 100%	1060 Watt	1060 Watt	1060 Watt
Input power at 115%	1210 Watt	1200 Watt	1200 Watt
Inrush current:	< 40 Amps		
Power factor:	0.98 - 0.99		
Product weight:	12.3 lbs (5.6 kg)		
Dimensions (LxWxH):	23" x 9.5" x 11.5" (56,5x24.5x22.5cm)		
Temperature ambient:	32-95 °F		
Relative humidity:	<70%		
Total Harmonic Distortion:	<10%		
Power inlet:	IEC C14		
External dim connector	RJ14 (6p4c)		

## Legislation

This device complies with Part 18 of the FCC Rules.CSA approved.

## Included accessories

User manual, power cord, Interconnect cable RJ14 5 ft and a T-splitter for plug and play installation, Gavita Pro lamp.