## How to program Westek TE06WHB 7-day programmable

Timer has rechargeable battery. Plug timer into outlet for 1 hour to charge battery and LCD will display. Unplug timer to program

Make schedule of programming times before starting. Timer will not perform correctly with conflicting on-off schedules

Up to 8 ON/OFF programs per day >> program 1 program 2 ... through program 8 Choice of individual days, or blocks of days

## Set time of day:

Press TIME button MO – TU – WE – TH – FR – SA – SU will display Press +- button to select current day of week Press Set to confirm

Hour will be flashing on display Press +- button to select current hour Press Set to confirm

Minutes will be flashing on display Press +- button to select current minutes Press Set to confirm

Program 1 ON Hour will be flashing (ready to start programming On time hour for Program 1) Press +- button to select Hour you want program 1 to turn ON Press Set to confirm

Program 1 ON Minutes will be flashing (ready to start programming On time minutes for Program 1) Press +- button to select Hour you want program 1 to turn ON Press Set to confirm

Program 1 ON Day(s) of week will be flashing Press +- button to select Day or block of days you want program 1 to turn ON Press Set to confirm

Repeat same steps to set Program 1 Off time

Program 1 is ready. Continue setting more programs

Press manual button until auto displays

To access Random or Countdown mode, press manual button.

