
Branch Shelving System

Assembly Instructions

These installation instructions list the components and steps to create any Branch configuration. Review this document completely before beginning installation.

Please take time to identify the hardware as well as the individual components of the product. As you unpack and prepare for assembly, place them carefully on the floor and protect them from damage. Please follow the assembly instructions closely. Improper assembly may result in personal or property damage. We've included drywall anchors. Be sure to use anchors appropriate for your wall.

Depending on use, it may be necessary to tighten the screws and hardware periodically to maximize the stability of the shelving system components.



Branch - 3 Shelving Unit w/ Desk (individual configurations may differ)






Branch - SHELVING SYSTEM


To maintain the appearance of your shelving, we recommend cleaning the wood uprights, shelves, desk and support brackets with a damp, soft cloth.

Do not use abrasive cleaning products.






Branch Shelving System Components






Shelf And Desk Pre-Assembly



- A) Assemble shelf/desk unit using provided hardware.
- Attach shelf between the uprights to confirm proper width of Branch assembly.
- C) Assemble branch configuration face down on floor prior to fastening anything to the wall.



Shelf And Desk Pre-Assembly




with threaded binding posts.

and tighten from both sides until snug.
D) If multiple bays require support brackets at same height note that binding posts are designed to adjust to the extra length needed.



Method For Marking Position Of Upright Wall Plates



Gus




Considerations For Multiple Bay Configurations


Floor Level. If you are installing more than two bays of Branch Shelving in a row, then it is important to consider the slope of the floor. Please ensure that your floor is level by using a longer level along the floor at the bottom of the desired wall for the installation.

- If the floor is level and does not slope down left or right then you are free to start your install without regard for the floor. We do however recommend that you leave a few turns of the level feet out, so they can be adjusted up or down slightly if needed.

- If the floor is sloping to the left or right, then it is important to start the install at the highest point of the floor. We suggest to start at the highest point with the level feet of the uprights turned to their lowest point for the initial install. As the floor slopes downward the level feet of the uprights can be unscrewed to allow them to touch the floor.


Using a handyman service. A typical three bay Branch Shelving System can take an experienced handyman approximately 1.5 hours to install. The angles of your floor and wall all come into play when determining the complexity of install time. The more out of alignment these elements are, the more experience is needed to ensure an accurate fit and finish. Although the Branch Shelving System has tolerances to account for floor and wall imperfections, a good handyman is recommended for larger multiple bay configurations.








Component Locations - Branch Collection Configurations



Branch - 2 - Wardrobe Unit



Component Branch Collection Configurations





Branch Desk

INSTALLATION INSTRUCTIONS

KEEP ALL PACKAGING MATERIALS UNTIL YOU HAVE VERIFIED ALL COMPONENTS AND PARTS.

- 1. Attach the steel shelf bracks to either side of the wood desk with the fastening hardware provided.
- 2. Determine the placement for the wood desk. Align steel shelf bracket holes with upright holes. Fasten the sheel desk brackets with hardware provided.

To help maintain the appearance of your desk we recommend cleaning the wood surfaces and steel brackets with a damp, soft cloth. Do not use abrasive cleaning products. Depending on use, it may be necessary to tighten the screws and hardware periodically to maximize the stability of the desk connection to the wood uprights.

