DINION IP thermal 8000

www.boschsecurity.com







- ▶ Long detection range (up to 5850 m)
- Integrated Intelligent Video Analytics
- 640 x 480 resolution version available for even sharper images
- ▶ High access security for data protection

This thermal IP camera provides high-sensitivity thermal images using an un-cooled vanadium oxide microbolometer that delivers outstanding image quality. The camera is designed to combine the benefits of thermal imaging with the market leading Intelligent Video Analytics from Bosch. There is no need for natural or artificial lighting of the area of interest. The camera produces crisp and clear images day and night, even in challenging environments with smoke, dust, haze or fog.

Versions

The camera comes with a choice of narrow field-ofview (NFOV) or wide field-of-view (WFOV) lenses. The QVGA resolution variant is available with a frame rate of 9 or 60 fps; the VGA resolution variant is available with a frame rate of 9 or 30 fps.

The camera is enclosed in a robust outdoor housing making it ideal for a wide range of applications in demanding environments.

System overview

Range Performance

The following tables give the approximate range performance under ideal conditions of the various lenses for standard monitoring.

7.5 mm lens QVGA FoV: 41.8°H x 30°V	Human*	Object*
Detection	140 m (459 ft)	640 m (2100 ft)
Recognition	35 m (115 ft)	160 m (525 ft)
Identification	18 m (59 ft)	80 m (262 ft)
9 mm lens VGA FoV: 70°H x 52°V	Human	Object
Detection	155 m (509 ft)	700 m (2297 ft)
Recognition	40 m (131 ft)	175 m (574 ft)
Identification	20 m (66 ft)	88 m (289 ft)
16.7 mm lens VGA FoV: 37.5°H x 28°V	Human	Object
Detection	315 m (1033 ft)	1450 m (4757 ft)
Recognition	80 m (262 ft)	360 m (1181 ft)
Identification	40 m (131 ft)	180 m (591 ft)

19 mm lens QVGA FoV: 16°H x 12°V	Human	Object
Detection	380 m (1247 ft)	1750 m (5741 ft)
Recognition	95 m (312 ft)	440 m (1444 ft)
Identification	48 m (157 ft)	220 m (722 ft)
35 mm lens VGA FoV: 17.6°H x 13.2°V	Human	Object
Detection	690 m (2264 ft)	3200 m (10499 ft)
Recognition	170 m (558 ft)	800 m (2625 ft)
Identification	85 m (279 ft)	400 m (1312 ft)
65 mm lens VGA FoV: 9.6°H x 7.2°V	Human	Object
Detection	1270 m (4167 ft)	5850 m (19193 ft)
Recognition	320 m (1050 ft)	1460 m (4790 ft)
Identification	160 m (525 ft)	730 m (2395 ft)
*Human: 1.8 x 0.5 m (5.9 x 1.6 ft): Object: 2.3 x 2.3 m (7.5 x 7.5 ft)		

*Human: 1.8 x 0.5 m (5.9 x 1.6 ft); Object: 2.3 x 2.3 m (7.5 x 7.5 ft)

Lens	Focus distance
65 mm*	141 m to ∞
35 mm*	41 m to ∞
19 mm	13.2 m to ∞
16.7 mm	9.0 m to ∞
9 mm	2.4m to ∞
7.5 mm	1.7 m to ∞

*The focus distance of the 35 mm and 65 mm lenses can be adjusted manually in the application, please check the Bosch website to download the guide if required.

Functions

Intelligent Video Analytics

The integrated video analytics is both robust and intelligent. The Intelligence-at-the-Edge concept now delivers even more powerful features:

- Simple calibration
- False alarm reduction
- Extended range identification

The mission critical video analytics reliably detects, tracks, and analyzes objects, and alerts you when predefined alarms are triggered. A smart set of alarm rules, together with object filters and tracking modes, makes complex tasks easy.

The system is also extremely robust and is able to reduce false alarms, for example from foliage or shaking objects, even in harsh weather conditions. Metadata is attached to your video to add sense and structure. This enables you to quickly retrieve the relevant images from hours of stored video. Metadata can also be used to deliver irrefutable forensic evidence or to optimize business processes based on people counting or crowd density information. Calibration is quick and easy – just enter the height of the camera. The internal gyro/accelerometer sensor provides the rest of the information to precisely calibrate the video analytics.

Bitrate optimized profile

The average typical optimized bitrate in kbits/s for various frame rates is shown in the table:

IPS	VGA	QVGA
60	-	360
30	850	196
15	510	125
9	250	91
3	105	52

Multiple streams

The innovative multi-streaming feature delivers various H.264 streams together with an M-JPEG stream. These streams facilitate bandwidth-efficient viewing and recording as well as integration with third-party video management systems.

The camera can run multiple independent streams that allows to set a different resolution and frame rate on the first and second stream. The user can also choose to use a copy of the first stream.

The third stream uses the I-frames of the first stream for recording; the fourth stream shows a JPEG image at a maximum of 10 Mbit/s.

Storage management

Recording management can be controlled by the Bosch Video Recording Manager (Video Recording Manager) or the camera can use iSCSI targets directly without any recording software.

Edge recording

Insert a memory card into the card slot to store up to 2 TB of local alarm recording. Pre-alarm recording in RAM reduces recording bandwidth on the network, and extends the effective life of the memory card.

Hybrid operation

A surge-protected analog video output allows full hybrid operation. This means that high resolution IP video streaming and an analog video output are available simultaneously. The hybrid functionality offers an easy migration path from legacy CCTV to a modern IP-based system.

Data security

Special measures have been put in place to ensure the highest level of security for device access and data transport. The three-level password protection with security recommendations allows users to customize device access. Web browser access can be protected using HTTPS and firmware updates can also be protected with authenticated secure uploads. The on-board Trusted Platform Module (TPM) and Public Key Infrastructure (PKI) support, guarantee superior protection from malicious attacks. The 802.1x network authentication with EAP/TLS, supports TLS 1.2 with updated cipher suites including AES 256 encryption.

The advanced certificate handling offers:

- Self-signed unique certificates automatically created when required
- Client and server certificates for authentication
- Client certificates for proof of authenticity
- Certificates with encrypted private keys

Complete viewing software

There are many ways to access the camera's features: using a web browser, with the Bosch Video Management System, with the free-of-charge Bosch Video Client or Video Security Client, with the video security mobile app, or via third-party software.

System integration


The camera conforms to the ONVIF Profile S specifications. Compliance with these standards guarantees interoperability between network video products regardless of manufacturer. Third-party integrators can easily access the internal feature set of the camera for integration into large projects. Visit the Bosch Integration Partner Program (IPP) website (ipp.boschsecurity.com) for more

information.

Certifications and approvals		
Standards		Туре
Emission		EN 55032: 2012 /AC: 2013 class B FCC: 47 CFR Part 15 B, class B RCM: AS/NZS CISPR 22: 2009 /A1: 2010 VCCI: V2 & V3 /2015.04
Immunity		EN 50130-4: 2011 /A1: 2014 EN 50121-4: 2006 /AC: 2008 EN 55024: 2010 /A1: 2015
Environmental		EN 50130-5:2011 Class IV, Salt mist 28 days passed
Safety		EN 60950-1: 2006 /A11: 2009 /A1: 2010 / A12: 2011 /A2: 2013 EN 60950-22: 2006 /A11: 2008 UL 60950-1, Ed. 2, October 14, 2014 CAN/CSA C22.2 No. 60950-1-07, Ed. 2, October 2014
Marks		cUL, CE, WEEE, RCM, EAC, VCCI, FCC, RoHS
Region	Reg	ulatory compliance/quality marks
Europe	CE	DINION IP thermal 8000
USA	UL	DINION IP thermal 8000

Installation/configuration notes

Dimensions



Technical specifications

16.7 mm

-

37.5° x 28°

Power		
Input voltage	24 VAC (SELV) ±10% 50/60 Hz	
Power consumption	34 W max.	
Thermal module		
Image sensor	Un-cooled vanadium oxi	de microbolometer
Picture elements	320(H) x 240(V) or 640	0(H) x 480(V)
Pixel pitch	17 µm	
Thermal sensitivity	< 50 mK	
Video resolution		
QVGA	320 x 240 at 9 fps or 60 fps	
VGA	640 x 480 at 9 fps or 30 fps	
Video functions – colo	r	
Adjustable picture settings	Contrast	
Thermal color mapping	12 selectable modes	
Lenses FoV (H x V)		
	QVGA	VGA
7.5 mm	41.8° x 30°	-
9 mm	-	70° x 52°

Lenses FoV (H x V)		
19 mm	16° x 12°	-
35 mm	-	17.6° x 13.2°
65 mm	-	9.6° x 7.2°
Video etreomine		
Video streaming		
Video compression	H.264 (MP); M- JPEG	
Streaming	Multiple configurable streams in H.264 and M- JPEG, configurable frame rate and bandwidth. Regions of Interest (ROI)	
Camera processing latency	<55 ms	
GOP structure	IP, IBP, IBBP	
Camera installation		
Analog output	Off, 4:3, 16:9 pillar box,	16:9 crop
Positioning	Coordinates / Mounting height	
Video content analysis		
Analysis type	Intelligent Video Analytics	
Configurations	Silent VCA / Profile1/2 / Scheduled / Event triggered	
Alarm rules (combinable)	Any object Object in field Line crossing Enter / leave field Loitering Follow route Counting Occupancy Condition change Similarity search Flow / counter flow	
Object filters	Duration Size Aspect ratio Speed Direction Object classes (4)	
Tracking modes	Standard (2D) tracking Ship tracking Museum mode	
Calibration	Automatic based on gyrc and camera height) / accelerometer data
Additional functions		
Additional functions Video authentication	Off / Watermark / MD5 /	SHA-1 / SHA-256
	Off / Watermark / MD5 / Name; Logo; Time; Alarn	

Local storageInternal RAM5 spre-alarm recordingMemory card slotSupports up to 32 GB microSDMC / 2 TB microSDXC card. (A memory card of Class 6 or higher is recommended for HD recording)RecordingContinuous recording, ring recording, alarm/ events/schedule recordingInput/outputCVBS (NTSC), 1 Vpp, SMB, 75 Ohm (surge protected)Audio connectors3.5 mm stereo jack (x2)Audio line out12 KOhm typical, 1 Vrms maxAudio line out11 Vrms at 1.5 kOhm typical,Audio nine out15 VDC to +40 VDC (+3.3 VDC with DC-coupled 22 kOhm pull-up) resistor)Alarm input connectorClampAlarm output connectorS0 VAC or +40 VDC Maximum 0.5 A continuous, 10VAAlarm output connectorRJ45Alarm output connectorS1.5 NB KHZ sampling rate AC-1C, 48 kbps at 16 kHZ sampling rate AC-1C, 48 k		
Memory card slotSupports up to 32 GB microSDHC / 2 TB microSDXC card. (A memory card of Class 6 or higher is recommended for HD recording)RecordingContinuous recording, ring recording, alarm/ events/schedule recordingInput/outputInput/outputAnalog video outCVBS (NTSC), 1 Vpp, SMB, 75 Ohm (surge protected)Audio connectors3.5 mm stereo jack (x2)Audio line in12 kOhm typical, 1 Vrms maxAudio line out1 Vrms at 1.5 kOhm typical,Alarm input connectorsClamp (x2 non-isolated closing contact)Alarm input activation voltageSOVAC or +40 VDC (+3.3 VDC with DC-coupled 22 kOhm pull-up resistor)Alarm output connectorSOVAC or +40 VDC Maximum 0.5 A continuous, 10VAAlarm output connectorRS-232/422/485Data portFS-232/422/485StandardSoftware L6.6 kHz sampling rate L6.6 kHz sampling rate AC-1C, 48 kbps at 16 kHz sampling rate AC-1C	Local storage	
microSDXC card. (A memory card of Class 6 or higher is recommended for HD recording)RecordingContinuous recording, ring recording, alarm/ events/schedule recordingInput/outputImput/outputAnalog video outS/S (NTSC), 1 Vpp, SMB, 75 Ohm (surge protected)Audio connectors3.5 mm stereo jack (x2)Audio line out12 KOhm typical, 1 Vrms maxAudio line out12 KOhm typical, 1 Vrms maxAudio line out1 Vrms at 1.5 KOhm typical,Audio line out1 Vrms at 1.5 KOhm typical,Alarm input connectorsClamp (x2 non-isolated closing contact) (*3.3 VDC with DC-coupled 22 kOhm pull-up resistor)Alarm output connectorClampAlarm output connectorS0 VAC or +40 VDC Maximum 0.5 A continuous, 10VAAlarm output voltageS0 VAC or +40 VDC Maximum 0.5 A continuous, 10VAEthernetRJ45Data portFS-232/422/485StandardS0 HB L16.16 kHz sampling rate AC-LC, 80 kbps at 16 kHz sampling rate <b< td=""><td>Internal RAM</td><td>5 s pre-alarm recording</td></b<>	Internal RAM	5 s pre-alarm recording
Imput/outputInput/outputAnalog video outCVBS (NTSC), 1 Vpp, SMB, 75 Ohm (surge protected)Audio connectors3.5 mm stereo jack (x2)Audio line in12 kOhm typical, 1 Vrms maxAudio line out1 Vrms at 1.5 kOhm typical,Alarm input connectorsClamp (x2 non-isolated closing contact) (rasi x1 VDC to +40 VDC (rasi x1 VDC to +40 VDC (rasi x1 VDC with DC-coupled 22 kOhm pull-up resistor)Alarm output connectorClampAlarm output connector30 VAC or +40 VDC Maximum 0.5 A continuous, 10VAAlarm output voltageS0 VAC or +40 VDC Maximum 0.5 A continuous, 10VAEthernetRJ45Data portG.711, 8 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate AAC-LC, 80 k	Memory card slot	microSDXC card. (A memory card of Class 6
Analog video outCVBS (NTSC), 1 Vpp, SMB, 75 Ohm (surge protected)Audio connectors3.5 mm stereo jack (x2)Audio line in12 kOhm typical, 1 Vrms maxAudio line out1 Vrms at 1.5 kOhm typical,Alarm input connectorsClamp (x2 non-isolated closing contact) (rasistor)Alarm input activation voltage+5 VDC to +40 VDC (+3.3 VDC with DC-coupled 22 kOhm pull-up resistor)Alarm output connectorClampAlarm output connector30 VAC or +40 VDC Maximum 0.5 A continuous, 10VAAlarm output voltageS0 VAC or +40 VDC Maximum 0.5 A continuous, 10VAEthernetRJ45Data portRS-232/422/485StandardS0 RSSignal-to-Noise Ratio>50 dBAudio StreamingFull-duplex / half duplexVuit discoveryIP HelperUnit configurationVia web browser or Configuration ManagerFirmware updateRemotely programmableSoftware viewing Web browser; Video Security App; Bosch Video Management System; Bosch Video Client; or third party software	Recording	
Protected)Audio connectors3.5 mm stereo jack (x2)Audio line in12 kOhm typical, 1 Vrms maxAudio line out1 Vrms at 1.5 kOhm typical,Alarm input connectorsClamp (x2 non-isolated closing contact)Alarm input activation voltage+5 VDC to +40 VDC (+3.3 VDC with DC-coupled 22 kOhm pull-up resistor)Alarm output connectorClampAlarm output connector30 VAC or +40 VDC Maximum 0.5 A continuous, 10VAAlarm output voltageRS-232/422/485Alarm output voltageG.711, 8 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate AAC-LC, 80	Input/output	
Audio line in12 kOhm typical, 1 Vrms maxAudio line out1 Vrms at 1.5 kOhm typical,Alarm input connectorsClamp (x2 non-isolated closing contact)Alarm input activation voltageClamp (x2 non-isolated closing contact)Alarm output connectorClampAlarm output connectorClampAlarm output connectorClampAlarm output connector30 VAC or +40 VDC Maximum 0.5 A continuous, 10VAAlarm output voltage30 VAC or +40 VDC Maximum 0.5 A continuous, 10VAEthernetRJ45Data portRS-232/422/485Audio streamingG.711, 8 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rate MAC-LC, 80 kbps at 16 kHz sampling ra	Analog video out	
Audio line out1 Vrms at 1.5 kOhm typical,Audio line out1 Vrms at 1.5 kOhm typical,Alarm input activation voltageClamp (x2 non-isolated closing contact)Alarm input activation voltage+5 VDC to +40 VDC (+3.3 VDC with DC-coupled 22 kOhm pull-up resistor)Alarm output connectorClampAlarm output connector30 VAC or +40 VDC Maximum 0.5 A continuous, 10VAAlarm output voltage30 VAC or +40 VDC Maximum 0.5 A continuous, 10VAEthernetRJ45Data portRS-232/422/485StandardG.711, 8 kHz sampling rate L16, 16 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rate MAC-LC, 80 kbps at 16 kHz sampling rateJunit discoveryIP HelperUnit configurationVia web browser or Configuration ManagerFirmware updateRemotely programmableSoftware viewing Software viewing Software viewing Sosch Video Security Client; Video Security App; Bosch Video Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/	Audio connectors	3.5 mm stereo jack (x2)
Alarm input connectorsClamp (x2 non-isolated closing contact)Alarm input activation voltage+5 VDC to +40 VDC (+3.3 VDC with DC-coupled 22 kOhm pull-up resistor)Alarm output connectorClampAlarm output connectorClampAlarm output voltage30 VAC or +40 VDC Maximum 0.5 A continuous, 10VAEthernetRJ45Data portRS-232/422/485StandardG.711, 8 kHz sampling rate L16, 16 kHz sampling rate AC-LC, 48 kbps at 16 kHz sampling rate AC-LC, 80 kbps at 16 kHz sampling rate AC-LC, 80 kbps at 16 kHz sampling rate MAC-LC, 80 kbps at 16 kHz sampling rate AC-LC, 80 kbps at 16 kHz sampling rate AC-LC, 80 kbps at 16 kHz sampling rate AC-LC, 80 kbps at 16 kHz sampling rate MAC-LC, 80 kbps at 16 kHz sampling rate MAC-LC, 80 kbps at 16 kHz sampling rate AC-LC, 80 kbps at 16 kHz sampling rate MAC-LC, 80 kbps at 16 kHz sampling rate10 unit configurationVia web browser or Configuration ManagerFirmware updateRemotely programmableSoftware viewingWeb browser; Video Security Client; Video Security Client; video Security App; Bosch Video Management System; Bosch Video Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/	Audio line in	12 kOhm typical, 1 Vrms max
connectorsInternational ConnectorsAlarm input activation voltage+5 VDC to +40 VDC (+3.3 VDC with DC-coupled 22 kOhm pull-up resistor)Alarm output connectorClampAlarm output voltage30 VAC or +40 VDC Maximum 0.5 A continuous, 10VAAlarm output voltage30 VAC or +40 VDC Maximum 0.5 A continuous, 10VAEthernetRJ45Data portRS-232/422/485Audio streamingConnectorStandardG.711, 8 kHz sampling rate L16, 16 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rate AC-LC, 80 kbps at 16 kHz sampling rate AC-LC, 80 kbps at 16 kHz sampling rateSignal-to-Noise Ratio>50 dBAudio StreamingFull-duplex / half duplexUnit discoveryIP HelperUnit configurationVia web browser or Configuration ManagerFirmware updateRemotely programmableSoftware viewingWeb browser; Video Security Client; Video Security Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/	Audio line out	1 Vrms at 1.5 kOhm typical,
activation voltage(+3.3 VDC with DC-coupled 22 kOhm pull-up resistor)Alarm output connectorClampAlarm output voltage30 VAC or +40 VDC Maximum 0.5 A continuous, 10VAEthernetRJ45Data portRS-232/422/485Audio streamingContention (Contention)StandardG.711, 8 kHz sampling rate L16, 16 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rateSignal-to-Noise Ratio>50 dBAudio StreamingFull-duplex / half duplexUnit discoveryIP HelperUnit configurationVia web browser or Configuration ManagerFirmware updateRemotely programmableSoftware viewingWeb browser; Video Security Client; Video Security App; Bosch Video Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/	'	Clamp (x2 non-isolated closing contact)
connectorImage: ConnectorAlarm output voltage30 VAC or +40 VDC Maximum 0.5 A continuous, 10VAEthernetRJ45Data portRS-232/422/485Audio streamingG.711, 8 kHz sampling rate L16, 16 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rateSignal-to-Noise Ratio>50 dBAudio StreamingFull-duplex / half duplexUnit discoveryIP HelperUnit configurationVia web browser or Configuration ManagerFirmware updateRemotely programmableSoftware viewingWeb browser; Video Security Client; Video Security App; Bosch Video Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/		(+3.3 VDC with DC-coupled 22 kOhm pull-up
Maximum 0.5 A continuous, 10VAEthernetRJ45Data portRS-232/422/485Audio streamingImage: Content of the stream of the		Clamp
Latest firmware andNoteData portRS-232/422/485Audio streamingStandardG.711, 8 kHz sampling rate L16, 16 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rateSignal-to-Noise Ratio>50 dBAudio StreamingFull-duplex / half duplexSoftwareIP HelperUnit discoveryIP HelperUnit configurationVia web browser or Configuration ManagerFirmware updateRemotely programmableSoftware viewingWeb browser; Video Security Client; video Security App; Bosch Video Management System; Bosch Video Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/	Alarm output voltage	
Audio streamingStandardG.711, 8 kHz sampling rate L16, 16 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rateSignal-to-Noise Ratio>50 dBAudio StreamingFull-duplex / half duplexSoftwareUnit discoveryIP HelperUnit configurationVia web browser or Configuration ManagerFirmware updateRemotely programmableSoftware viewingWeb browser; Video Security Client; Video Security App; Bosch Video Management System; Bosch Video Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/	Ethernet	RJ45
StandardG.711, 8 kHz sampling rate L16, 16 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rateSignal-to-Noise Ratio>50 dBAudio StreamingFull-duplex / half duplexSoftwareUnit discoveryIP HelperUnit configurationVia web browser or Configuration ManagerFirmware updateRemotely programmableSoftware viewingWeb browser; Video Security Client; Video Security App; Bosch Video Management System; Bosch Video Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/	Data port	RS-232/422/485
ControlControlL16, 16 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rateSignal-to-Noise Ratio>50 dBAudio StreamingFull-duplex / half duplexSoftwareIP HelperUnit discoveryIP HelperUnit configurationVia web browser or Configuration ManagerFirmware updateRemotely programmableSoftware viewingWeb browser; Video Security Client; Video Security App; Bosch Video Management System; Bosch Video Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/	Audio streaming	
Audio StreamingFull-duplex / half duplexSoftwareUnit discoveryIP HelperUnit configurationVia web browser or Configuration ManagerFirmware updateRemotely programmableSoftware viewingWeb browser; Video Security Client; Video Security App; Bosch Video Management System; Bosch Video Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/	Standard	L16, 16 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate
Software Unit discovery IP Helper Unit configuration Via web browser or Configuration Manager Firmware update Remotely programmable Software viewing Web browser; Video Security Client; Video Security App; Bosch Video Management System; Bosch Video Client; or third party software Latest firmware and http://downloadstore.boschsecurity.com/	Signal-to-Noise Ratio	>50 dB
Unit discoveryIP HelperUnit configurationVia web browser or Configuration ManagerFirmware updateRemotely programmableSoftware viewingWeb browser; Video Security Client; Video Security App; Bosch Video Management System; Bosch Video Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/	Audio Streaming	Full-duplex / half duplex
Unit configurationVia web browser or Configuration ManagerFirmware updateRemotely programmableSoftware viewingWeb browser; Video Security Client; Video Security App; Bosch Video Management System; 	Software	
Firmware updateRemotely programmableSoftware viewingWeb browser; Video Security Client; Video Security App; Bosch Video Management System; Bosch Video Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/	Unit discovery	IP Helper
Software viewingWeb browser; Video Security Client; Video Security App; Bosch Video Management System; Bosch Video Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/	Unit configuration	Via web browser or Configuration Manager
Video Security Client; Video Security App; Bosch Video Management System; Bosch Video Client; or third party softwareLatest firmware andhttp://downloadstore.boschsecurity.com/	Firmware update	Remotely programmable
	Software viewing	Video Security Client; Video Security App; Bosch Video Management System; Bosch Video Client;
		http://downloadstore.boschsecurity.com/

Network		
Protocols	IPv4, IPv6, UDP, TCP, HTTP, HTTPS, RTP/ RTCP, IGMP V2/V3, ICMP, ICMPv6, RTSP, FTP, Telnet, ARP, DHCP, APIPA (Auto-IP, link local address), NTP (SNTP), SNMP (V1, MIB- II), 802.1x, DNS, DNSv6, DDNS (DynDNS.org, selfHOST.de, no-ip.com), SMTP, iSCSI, UPnP (SSDP), DiffServ (QoS), LLDP, SOAP, Dropbox, CHAP, digest authentication	
Encryption	TLS 1.2, SSL	
Ethernet	10/100 Base-T, auto-sensing, half/full duplex	
Connectivity	Auto-MDIX	
Interoperability	ONVIF Profile S; ONVIF Profile G; GB/T 28181	
Mechanical		
Dimensions (H x W x L)	141 x 164 x 430 mm (5.6 x 6.5 x 16.9 in.) including sunshield	
Weight	<3.5 kg (7.72 lb)	
Construction	Aluminum casing, silicone gaskets	
Color	RAL 9003 White	
Window	Germanium glass (Ø52 x 3 mm)	
Environmental		
Operating temperature	-40°C to +55°C (-40°F to +131°F) for continuous operation;	
Storage temperature	-55°C to +70°C (-67°F to +158°F)	
Operating Humidity	5% to 95% RH non-condensing	
Storage Humidity	up to 98% RH	
Ingress protection	IP66, NEMA-4X	
Enclosure protection	Wind load 150 mph; NEMA TS2 vibration, shock	
Ordering informa	tion	

NHT-8000-F07QS DINION THERMAL, <9Hz, QVGA, 7.5mm Thermal imaging IP camera QVGA 9 fps 7.5 mm lens Order number NHT-8000-F07QS

NHT-8000-F07QF DINION THERMAL, 60Hz, QVGA, 7.5mm Thermal imaging IP camera

QVGA 60 fps 7.5 mm lens Order number **NHT-8000-F07QF**

NHT-8000-F19QS DINION THERMAL, <9Hz, QVGA,19mm

Thermal imaging IP camera QVGA 9 fps 19 mm lens Order number **NHT-8000-F19QS**

NHT-8000-F19QF DINION THERMAL, 60Hz, QVGA,19mm

Thermal imaging IP camera QVGA 60 fps 19 mm lens Order number **NHT-8000-F19QF**

NHT-8001-F09VS DINION THERMAL, <9Hz, VGA,9mm

Thermal imaging IP camera VGA 9 fps 9 mm lens Order number **NHT-8001-F09VS**

NHT-8001-F09VF DINION THERMAL, 30Hz, VGA, 9mm

Thermal imaging IP camera VGA 30 fps 9 mm lens Order number **NHT-8001-F09VF**

NHT-8001-F17VS DINION THERMAL, <9Hz, VGA, 16.7mm

Thermal imaging IP camera VGA 9 fps 16.7 mm lens Order number **NHT-8001-F17VS**

NHT-8001-F17VF DINION THERMAL, 30Hz, VGA, 16.7mm

Thermal imaging IP camera VGA 30 fps 16.7 mm lens Order number **NHT-8001-F17VF**

NHT-8001-F35VS DINION THERMAL, <9Hz, VGA, 35mm

Thermal imaging IP camera VGA 9 fps 35 mm lens Order number **NHT-8001-F35VS**

NHT-8001-F35VF DINION THERMAL, 30Hz, VGA, 35mm

Thermal imaging IP camera VGA 30 fps 35 mm lens Order number **NHT-8001-F35VF**

NHT-8001-F65VS DINION THERMAL, <9Hz, VGA, 65mm Thermal imaging IP camera VGA

9 fps 65 mm lens Order number NHT-8001-F65VS

NHT-8001-F65VF DINION THERMAL, 30Hz, VGA, 65mm Thermal imaging IP camera

VGA 30 fps 65 mm lens Order number **NHT-8001-F65VF**

Accessories

NHA-U-WMT Bracket housing for DINION thermal 8000 Universal Wall Mount Bracket Order number NHA-U-WMT NDA-U-PMAL Pole mount adapter large Universal pole mount adapter, white; large Order number NDA-U-PMAL

NDA-U-CMT Corner mount adapter Universal corner mount, white Order number NDA-U-CMT

Represented by:

Europe, Middle East, Africa: Bosch Security Systems B.V. P.O. Box 80002 5600 JB Eindhoven, The Netherlands Phone: + 31 40 2577 284 emea.securitysystems@bosch.com emea.boschsecurity.com Germany: Bosch Sicherheitssysteme GmbH Robert-Bosch-Ring 5 85630 Grasbrunn Germany www.boschsecurity.com North America: Bosch Security Systems, Inc. 130 Perinton Parkway Fairport, New York, 14450, USA Phone: +1 800 289 0096 Fax: +1 585 223 9180 onlinehelp@us.bosch.com www.boschsecurity.us

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems 11 Bishan Street 21 Singapore 573943 Phone: +65 6571 2808 Fax: +65 6571 2809 apr.security.systems@bosch.com www.boschsecurity.asia

© Bosch Security Systems 2018 | Data subject to change without notice 22959903499 | en, V13, 26. Oct 2018