

Area48 Colour DMX protocol

—— CCT MODE ——

CCT Mode: 8 Bit

- 1: Intensity
- 2: CCT
- 3: + / - Green
—— If Strobe is enabled in menu
- 4: Strobe mode
- 5: Strobe Length

CCT Mode: 16 Bit

- 1: Intensity
- 2: Intensity Fine
- 3: CCT
- 4: CCT Fine
- 5: + / - Green
- 6: + / - Green Fine
—— If Strobe is enabled in menu
- 7: Strobe mode
- 8: Strobe Length

—— CCT+ MODE ——

CCT+ 8 bit

- 1: Intensity
- 2: CCT
- 3: + / - Red
- 4: + / - Green
- 5: + / - Blue
- 6: + / - Warm
- 7: + / - Cold
—— If Strobe is enabled in menu
- 8: Strobe mode
- 9: Strobe Length

CCT+ 16 bit

- 1: Intensity
- 2: Intensity Fine
- 3: CCT
- 4: CCT Fine
- 5: + / - Red
- 6: + / - Red Fine
- 7: + / - Green
- 8: + / - Green Fine
- 9: + / - Blue
- 10: + / - Blue Fine
- 11: + / - Warm
- 12: + / - Warm Fine
- 13: + / - Cold
- 14: + / - Cold Fine
—— If Strobe is enabled in menu
- 15: Strobe mode
- 16: Strobe Length

—— FULL MODE ——

Full mode 8 Bit

- 1: Intensity
- 2: Red
- 3: Green
- 4: Blue
- 5: Warm
- 6: Cold
—— If Strobe is enabled in menu
- 7: Strobe mode
- 8: Strobe Length

Full mode 16 Bit

- 1: Intensity
- 2: Intensity Fine
- 3: Red
- 4: Red Fine
- 5: Green
- 6: Green Fine
- 7: Blue
- 8: Blue Fine
- 9: Warm
- 10: Warm Fine
- 11: Cold
- 12: Cold Fine
—— If Strobe is enabled in menu
- 13: Strobe mode
- 14: Strobe Length