



EB180P

HIGH SPEED 1800W/1200W/800W/575W BALLAST

PRODUCT HIGHLIGHTS

THIS 1800W BALLAST CAN OPERATE UP TO 4 DIFFERENT LAMP POWERS, AND WORKS ON WORLDWIDE MAINS SUPPLY VOLTAGES MAKING IT A VERY FLEXIBLE PIECE OF KIT TO HAVE AVAILABLE. BEARING THE TÜV QUALITY LABEL, IT HAS POWER FACTOR CORRECTION WHICH MINIMISES CURRENT DRAW AND ENABLES AN 1800W LAMP TO BE POWERED FROM A US 20A CIRCUIT.

THE EB180P IS MADE USING THE POWER GEMS UNIQUE POWER MODULE, WHICH CAN EVEN BE INTERCHANGED WITH MODULES FROM OUR 4KW OR 6KW MODELS.

MAIN FEATURES

- POWER FACTOR CORRECTION
- HIGH SPEED OPTION AS STANDARD
- DMX CONTROL
- MODULAR POWER CIRCUIT



SPECIFICATIONS

Max Lamp Power	1800W	DMX Built In	Yes
Output Power Options	1.8kW, 1.2kW, 800W, 575W	Max Ambient Temperature	45° / 113°F
Output Frequency Options	1000Hz, 300Hz, 100Hz, Silent Mode	Width	225mm / 8.9"
Input Voltage Range	95-265V AC	Height	115mm / 4.5"
Current Draw	8.7A @ 230V, 16.7A @ 120V	Length	350mm / 13.8"
		Weight	7.5kg / 16.6lb
		Power Factor	>0.98

CONTACT