



INTERFACE COMPONENTS

- AXDSPL-TY2 interface
- AXDSPL-TY2 interface harness
- AXDSPL-TY2 vehicle T-harness Bass knob

APPLICATIONS

Visit axxessinterfaces.com for current application list

Toyota **DSP Interface With Pre-Wired Harness 2010-Up**

INTERFACE FEATURES

- Includes a DSP (Digital Signal Processor)
- 15 Band graphic EQ
- 4 inputs and 6 individually assignable outputs
- Independent equalization for front, rear, and sub
- Selectable low pass, band pass, and high pass filters
- Selectable crossover slopes: 12db, 24db, 36db, 48db
- Each channel can be delayed independently up to 10ms
- Clipping detection and limiting circuits
- Designed for non-amplified models
- Easy behind the radio installation with pre-wired harness
- Internal header port for adding interface modules
- Bass knob included for level control of subwoofer amp
- Settings adjusted via Bluetooth® in a smart device application (tablet or mobile phone), compatible with both Android and Apple devices
- Read, write, and store configurations for future recall
- Password protect feature available in the mobile app
- Micro-B USB updatable

TABLE OF CONTENTS

Installation Options	2
Installation	2
Connections	3-4
AXDSPL-BT Installation	5
AXDSPL-SP Installation	6
Mobile App	
Specifications	

TOOLS & INSTALLATION ACCESSORIES REQUIRED

- Crimping tool and connectors, or solder gun, solder, and heat shrink
 Tape
 Wire cutter
- Zip ties Multimeter

Google Play Store



Apple App Store



INSTALLATION OPTIONS

Adding a sub to a factory system:

This feature offers the ability to add a subwoofer to a factory system. (refer to page 3)

Adding a full-range amp & sub to a factory system:

This feature offers the ability to add a full-range amp and sub to a factory system. (refer to page 4)

16-pin header port:

Inside the interface is a 16-pin header port for adding optional modules (sold separately). Page 5 and 6 will show the installation and use of these modules.


- AXDSPL-BT Bluetooth streaming interface
- AXDSPL-SP Toslink digital output

Note: The interface provides a 12-volt 1-amp output to turn on aftermarket amp(s). If installing multiple amps, an SPDT automotive relay will be required if the amp turn-on current of all amps combined exceeds 1-amp. Use Metra part number E-123 (sold separately) for best results.


INSTALLATION

- **1.** Remove the factory radio †, then unplug all connectors.
- Install the AXDSPL-TY2 vehicle T-harness to the vehicle and make all necessary connections, but leave the amp turn-on wire disconnected.
- 3. Plug the AXDSPL-TY2 vehicle T-harness to the AXDSPL-TY2 interface.
- 4. Plug the AXDSPL-TY2 interface harness to the AXDSPL-TY2 interface.
- 5. Download and install the **AX-DSP-X app** from the **Google Play Store** or **Apple App Store**.
- 6. Cycle the ignition on.
- Open the app then select the **Bluetooth Connection** tab. Follow the instructions to pair the mobile device to the interface. Refer to page 6 for more information.
- **8.** Scroll to the **Configuration** tab then select **General** for the vehicle type. Press the **Lock Down** ‡ button to save the configuration. Refer to <u>page 7</u> for more information.
- **9.** Connect the amp turn-on wire.
- **10.** Adjust the settings in the app as desired. Press the **Lock Down** ‡ button to save any new configurations.
- Refer to Metra online for dash disassembly. If Metra makes a dash kit for the vehicle, disassembly will be within those instructions.
- ‡ Anytime the interface is locked down the key must be cycled off then back on


ADDING A SUB TO A FACTORY SYSTEM




ADDING A FULL-RANGE AMP & SUB TO A FACTORY SYSTEM



BLUETOOTH STREAMING INTERFACE







- The AXDSPL-BT Bluetooth streaming interface can be used to stream media directly to the interface.
- While streaming media the volume on the phone will be used. As an option, the AXBK-1 (sold separately) can be used to control the volume.

Note: The bass knob included with the **AXDSPL-TY2** can be used if it will not be used to control a subwoofer.

- **1. Important!** Unplug the interface from the vehicle.
- Remove (4) Phillips screws securing the interface, then remove the top cover, exposing the circuit board within.
- **3.** Locate the 16-pin header on the circuit board.
- 4. Important! Referencing how the AXDSPL-BT is laid out in the picture, carefully line up the header pins to the interface. Gently press down to secure.


Note: Both interfaces may be damaged if installed wrong.

5. Reinstall the top cover to complete the installation.


AXBK-1 Installation:

Connect the Brown wire from the interface to the Orange wire from the AXBK-1.Ground the Black wire from the AXBK-1.

TOSLINK DIGITAL OUTPUT








- The **AXDSPL-SP** Toslink digital output can be used for adding a digital output to the interface.
- **1. Important!** Unplug the interface from the vehicle.
- 2. Remove (4) Phillips screws securing the interface, then remove the top cover, exposing the circuit board within.
- **3.** Locate the 16-pin header on the circuit board.
- **4.** Important! Carefully line up the header pins to the **AXDSPL-SP**, with the Toslink port facing outward. Gently press down to secure.

Note: Both interfaces may be damaged if installed wrong.

5. Reinstall the top cover provided with the **AXDSPL-SP** to complete the installation.


MOBILE APP

Setup Instructions



General information tab for installing the interface.

Bluetooth Connection




• **Scan** - Press this button to start the Bluetooth pairing process, then select the interface once it is found. "Connected" will appear in the top left corner of the app once paired.

Note: The ignition must be cycled on during this process.

• **Disconnect** - Disconnects the interface from the app.

Configuration




- **Identify** Click this button to send a test tone to the front left speaker*. * Only installations using the front left output (white RCA jack).
- **Reset to Defaults** Resets the interface to factory settings. During the reset process the amp(s)
- will shut off for 5-10 seconds.
- Vehicle Type Select General for the vehicle type from the drop down box, then click apply.
- Lock Down Click this button to save the selected settings.

Attention! This must be done before closing the app or cycling the key otherwise all new changes will be lost!

- **Save Configuration** Saves the current configuration to the mobile device.
- **Recall Configuration** Recalls a configuration from the mobile device.
- About Displays information about the app, interface, and mobile device.
- **Set Password** Assign a 4-digit password to lock the interface. If no password is desired, use "0000". This will clear out any currently set password. It is not necessary to lock down the interface when setting a password.

Note: A 4-digit only password must be chosen otherwise the interface will show "password not valid for this device".


Outputs



Output Channels

- **Location** Location of speaker.
- Group Used to join channels together for simple equalization. Example, left front woofer/midrange and left front tweeter will be considered simply left front. The letter M indicates the speaker assigned as the master speaker.
- **Invert** Will invert the phase of the speaker.
- Mute Will mute desired channel(s) for tuning individual channels.


Crossover Adjust



- Select the desired crossover filter per channel, low pass, band pass, or high pass.
- Select the desired crossover slope per channel, 12db, 24db, 36db, or 48db.
- Select the desired crossover frequency per channel, 20hz to 20khz.


Note: The front and rear channels default to a 100Hz high pass filter to keep the low frequency signals out. If a subwoofer is not being installed, change the front and rear crossover points down to 20Hz for a full range signal, or to the lowest frequency the speakers will play down to.

Equalizer Adjust




- All channels can be adjusted independently within this tab with 15 bands of available equalization. It is best to tune this by using an RTA (Real Time Analyzer).
- The **Gain** slider on the far left is for the channel selected.

Delay Adjust




Allows a delay of each channel. If a delay is desired, first measure the
distance (in inches) from each speaker to the listening position, then
enter those values to the corresponding speaker. Add (in inches) to
the desired speaker to delay it.

Inputs/Levels



- **Chime Volume** Not applicable in this application.
- **Clipping Level** Use this feature to protect sensitive speakers like tweeters from being driven past their capabilities. If the output signal of the interface clips the audio will be reduced by 20dB. Turning down the stereo will allow the audio to come back at a normal level. The sensitivity of this feature can be adjusted to the listening preference of the user.
- Amp Turn On
- Signal Sense Will turn the amp(s) on when an audio signal is detected, and keep on for 10 seconds after the last signal. This ensures the amp(s) won't shut off between tracks.
- **Always On** Will keep the amp(s) on as long as the ignition is cycled on.
- Turn on Delay Can be used to delay audio output to avoid turn-on pops.
- Subwoofer Input Select Front + Rear

Locking Down Data



Last and the most important.

You must lock down your

configuration and cycle the key!!!





SPECIFICATIONS

Input Impedance 1M Ohm Input Channels 6

Input Options High Level or Low Level Input Type Differential balanced

Input Voltage 0 - 28-volts (peak-to-peak)

(high level range)

Input Voltage 0 - 4.9-volts (peak-to-peak)

(low level range)

Ouput Channels 6

Output Voltage Up to 5-volts RMS

Output Impedance 50 Ohms

Equalizer Type 15 Band Graphic EQ. +/- 10dB

THD <0.03%

Frequency Response 20Hz - 20kHz

Crossover Filter

Crossover Frequency Selectable 20hz to 20khz
Crossover Slope 12db/24db/36db/48db

Crossover Type Linkwitz-Riley
Sampling 48kHz

S/N Ratio 105dB @ 5-volts RMS

Operating Voltage 10-16 volts DC

Standby Current Draw 7mA
Operation Current Draw 150mA

Adjustments/Controls Application via Bluetooth
Remote Output 12 volts DC (signal sense

or with ignition

Low pass, band pass, high pass

Having difficulties? We're here to help.



Contact our Tech Support line at: **386–257–1187**



Or via email at: techsupport@metra-autosound.com

Tech Support Hours (Eastern Standard Time)

Monday - Friday: 9:00 AM - 7:00 PM Saturday: 10:00 AM - 7:00 PM

Sunday: 10:00 AM - 4:00 PM



KNOWLEDGE IS POWER

Enhance your installation and tabrication skills by enrolling in the most recognized and respected mobile electronics school in our industry.

Log onto www.installerinstitute.com or call 800-354-6782 for more information and take steps toward a better tomorrow.



Metra recommends MECP certified technicians