

INSTALLATION INSTRUCTIONS FOR PART 95-3106

APPLICATIONS

SATURN

2003-05 lon / 2000-05 LS 2000-02 SL / 2002-05 Vue


95-3106

KIT FEATURES

- Double DIN Head Unit Provision
- Stacked ISO DIN Head Unit Provision

KIT COMPONENTS

• A) DDIN Brackets • B) DDIN Trim Plate



WIRING CONNECTIONS (Sold Separately)

HARNESS:

- 70-2102 GM 2004-05 HARNESS
- 70-2002 SATURN 2000-05 HARNESS

TOOLS REQUIRED:

Phillips Screwdriver
 Panel Removal Tool
 Socket Set



METRA. THE WORLD'S BEST KITS.™

1-800-221-0932 **www.metraonline.com**



TABLE OF CONTENTS

DDIN / Stacked ISO	DIN H	lea	nd	U	n	it	Pi	0	vi:	sic) ii	S												4
<u>Kit Assembly</u>																								
2002-2003 Saluiii l	vuG		• •	•		•	•	•	•	•	•	•	•	•	•	•		• •	•	•	•	• •	•	
2002-2005 Saturn V	مرالا																							4
2000-2002 Saturn S	SL													,										4
2000-2005 Saturn L	LS																							1
2003-2005 Saturn I	lon																•							1
<u>vasn visassemdiy</u>																								



KNOWLEDGE IS POWER Enhance your installation and fabrication skills by

Enhance your installation and fabrication skills by enrolling in the most recognized and respected mobile electronics school in our industry.

Log onto www.installerinstitute.com or call 800-354-6782 for more information and take steps toward a better tomorrow.




Metra recommends using MECP certified technicians.



2003-2005 SATURN ION


- 1 Disconnect the negative battery terminal to prevent an accidental short circuit.
- 2 Unclip and remove the trim panel surrounding the radio. (Figure A)

Remove (2) 9/32" screws from radio to remove. (Figure A)



<u>2000-2005 SATURN LS</u>


- 1 Disconnect the negative battery terminal to prevent an accidental short circuit.
- 2 Unclip and remove the trim panel surrounding the radio. (Figure B)
- 3 Remove (2) 9/32" screws from radio to remove. (Figure B)








2000-2002 SATURN SL

- 1 Disconnect the negative battery terminal to prevent an accidental short circuit.
- 2 Remove (4) Phillips from panel below steering column and unclip and remove. (Figure A)
- 3 Remove (4) Phillips screws from the steering column trim panel and remove. (Figure B)
- 4 Remove (2) screws from the end cap/vent on the left side of the steering column then unclip and remove. (Figure C)
- 5 Unclip and remove the entire dash panel surrounding the radio, instrument cluster and a/c controls. (Figure D)
- 6 Remove (2) 9/32" screws securing the head unit to remove. (Figure D)












2002-2005 SATURN VUE

- 1 Disconnect the negative battery terminal to prevent an accidental short circuit.
- 2 Unsnap and remove shifter trim panel. (Figure A)
- 3 Remove (4) 9/32" screws from the dash pocket and remove. (Figure A)
- 4 Unsnap and remove panel surrounding radio and a/c controls.(Figure A)
- 5 Remove (2) 9/32" screws from radio to remove. (Figure A)





DASH DISASSEMBLY



DOUBLE DIN / STACKED ISO DIN HEAD UNIT PROVISIONS

- 1 Locate the factory wiring harness in the dash. Metra recommends using the proper mating adapter from Metra or AXXESS. Re-connect the negative battery terminal and test the unit for proper operation.
- 2 Attach the Double DIN brackets to the Double DIN trim plate. (Figure A)
- 3 Slide the bracket/radio housing assembly over the Double DIN head unit and secure using the screws supplied with the radio. (Figure B)
- 4 Reassemble dash in reverse order of disassembly.







NOTES

INST95-3106

METRA. THE WORLD'S BEST KITS.™

