

---

# SWEETVINYL

---



---

## The SugarCube SC-1 Mini

### Vinyl Click and Pop Remover

**The SC-1 Mini incorporates all the technology and features of the revolutionary SC-1 SugarCube in an integrated platform - all at a lower price.**

**The rear panel features gold-plated RCA connectors, a gigabit Ethernet port and four USB-A connections. Inside it has 192K/24 AKM AD/DA converters.**

**The front panel allows full control of the basic functions with push-buttons and the pairing function integrated with the strength knob, while an LCD display provides status information,**

The SC-1 Mini's flawless Click and Pop removal process benefits from the latest algorithm updates with version 2.0 software. The iOS and Android apps and web interface provide remote control of Click and Pop removal and Analog Bypass.

The soundstage is virtually indistinguishable when the unit is engaged or in Analog Bypass.

The SC-1 Mini provides hours of enjoyment from previously unplayable vinyl records in any collection

#### **SC-1 Mini In Brief**

- 2.0 Click and Pop Algorithm
- 192K/24 Bit AKM AD-DA Processing
- Analog Bypass
- Adjustable Removal Strength
- Click & Pop Removal Monitor
- Gold Plated RCA Interconnects
- Front Panel Pairing
- iOS, Android and Web Apps
- LCD Front Panel Display
- USB-A and Ethernet Ports
- Compact Size
- Excellent Build Quality (Black Only)

---

# SWEETVINYL

---



SugarCube SC-1 Mini

---

## SPECIFICATIONS

### Electronics

Line In maximum level = +20 dBu (7.7Vrms or 22Vp-p)  
Line Out level = Line In level  
THD+N = 0.0025% (A-weighted)  
Frequency Response = 20Hz to 60kHz +/- 3dB  
DC in = 5 volts, center-pin positive  
Average Power Dissipation = 9 watts

### Inputs

2x Line In RCA (Left-Right)  
2x Line Out RCA (Left-Right)  
4x USB type 'A' connector  
Ethernet 10/100/1000 UTP

### General

Dimensions: WxHxD: 8" x 8" x 2"  
Weight: 5 pounds (6 lbs. in box)