



Performance Games Inc.®

WWW.PERFORMANCEGAMESINC.COM

Fun starts here

PHONE: 248.705.5395

EMAIL: TODD@PERFORMANCEGAMESINC.COM

4058 Dixie Highway ■ Saginaw, Michigan 48601

Ice Boxx

Assembly Instructions

Congratulations on your purchase of the Ice Boxx home entertainment table. We want to ensure that you are completely satisfied with your purchase. Please feel free to contact us for any assistance in the assembly of your new product or for any other information you may want or need.

Tools Needed for Assembly:

- Wrench (included)
- Phillips-Head Screw Driver
- 2-Foot Level

Contents :

Item	Qty
Ice Boxx Cabinet	1
Legs	4
Accessory Package	1



Be sure to verify that all of the items listed above are included in the box before starting assembly.

Assembly Procedure:

DUE TO THE WEIGHT AND SIZE OF THE TABLE, IT IS RECOMMENDED THAT (2) PEOPLE ASSEMBLE THE TABLE TOGETHER.

Step 1: Contents Removal

- Carefully lift the Ice Boxx cabinet out of the box and lay it on its side (opposite of the rods), placing it on a clean and smooth surface to avoid scratching the finish.
- Remove the legs from the box and locate the accessory package.

Step 2: Leg Assembly

- Attach the legs to the cabinet by inserting the leg bolts into and through the cabinet holes.
- Secure with (1) washer and (1) lock nut on each stud.
- Tighten until nuts are flush with the each leg pad surface.
***Note: Over-tightening can cause damage to the cabinet**
- Repeat this process for each leg.

Step 3: Flip Table Over

- Check that all leg levelers are screwed completely into each leg
- Carefully lift and rotate the table onto its legs.

DO NOT ALLOW WEIGHT OF TABLE TO ROCK ON ANY ONE OR TWO LEGS ALONE*

*We recommend (2) or more people lift the table together.

Step 4: Electronic Scoring Unit Assembly

**If scoring unit is already attached jump to★*

- Attach the scoring unit by bolting it to the black brackets on the side of the dome using the (2) bolts, (2) washers, (2) nuts, and (1) small screw provided.

**The (2) long screws should be disregarded.*

- Run the small screw through the small hole on the inside of the dome and into the scoring unit.
- ★• Push the smaller end of the AC power cord into the rubber tube on the bottom of the table.
- Carefully pull the rubber tube through the top of the cabinet.
- The AC power cord should be through the hole in the top of the cabinet. This will allow you to plug in the scoring unit without the cord hanging down the side of the cabinet.
- Locate the (2) wires coming out of the hole located on the hinge side of the dome. Connect them to the scoring unit.

**The scoring unit can be powered either by plugging the AC power cord into the power strip or by using (4) AA batteries (not included).*

- Test that the sensor wires are correctly attached by shooting a puck into one of the goal openings.
 - If the scored goal credits the wrong team, simply switch the identical wires as they were plugged into the wrong position.

Step 5: Level Table Using Leg Levelers

- Adjust the leg levelers until the puck slides true on the playing surface.
- For more precise leveling, use a level.
- Place the level horizontally on the playing surface pointing towards the goal openings.
- Check that all leg levelers are screwed all the way in as a starting point.
- Evenly and alternately adjust the leg levelers on one end until you are horizontally level.
- Turn the level 90 degrees so it is pointing towards the ball server holes.
- Evenly and alternately adjust the levelers on one side of the table until it is vertically level.

Step 6: Lubricate Rods

- Push the rods away from the cabinet completely.
- Apply 2 or 3 drops of lubricant to each rod while rotating and pulling it toward you to evenly spread the lubricant.
- Repeat as needed.

**Specifications subject to change without notice.*



Fun starts here

Updated: June 16, 2019