

RSR Digital Multimeter- Autoranging w/ Resettable Fuse

PART NUMBER -01DMMS8268



MS8268

DMM WITH INPUT INDICATION

- Testleads socket built with LED indication, **sound/LED warning for wrong input**
- 4000 counts LCD display with backlit
- Data hold, relative measurement
- Auto-ranging, auto power-off
- Safety as per IEC1010-1, CAT.II 1000V & CAT. III 600V

Technical specifications

DCV: 400m/4/40/400/1000V, $\pm 0.7\%$

ACV: 400m/4/40/400/750V, $\pm 0.8\%$

DCA: 400 μ /4m/40m/400m/10A, $\pm 1.2\%$

ACA: 400 μ /4m/40m/400m/10A, $\pm 1.5\%$

OHM: 400/4k/40k/400k/4M/40M Ω , $\pm 1.2\%$

CAP: 4n/40n/400n/4 μ /40 μ /200 μ F, $\pm 3.0\%$

FREQ: 100/1k/10k/200kHz, $\pm 2.0\%$

Duty cycle: 5~95%, $\pm 2.0\%$

Audible continuity & diode test

Transistor h_{FE} : 0~1000

Battery: 1.5Vx3. AAA size