

# **Technical Specifications**

Unless otherwise specified, the technical specifications applied are for SDS-E only, and Probes attenuation set as 10X. Only if the oscilloscope fulfills the following two conditions at first, these specification standards can be reached.

- This instrument should run for at least 30 minutes continuously under the specified operating temperature.
- If change of the operating temperature is up to or exceeds 5 do, a "Self-calibration" procedure (see "*How to Implement Self-calibration*" on P15).

All specification standards can be fulfilled, except one(s) marked with the word "Typical".

| <b>Performance Characteristics</b> |                                    |                      | Instruction         |             |      |
|------------------------------------|------------------------------------|----------------------|---------------------|-------------|------|
|                                    |                                    | SDS5032E(V)          | 3                   | 30MHz       |      |
|                                    |                                    | SDS6062E(V)          | 60MHz               |             |      |
| Ban                                | dwidth                             | SDS7072E(V)          | 7                   | 70MHz       |      |
|                                    |                                    | SDS7102E(V)          | 1                   | 00MHz       |      |
|                                    |                                    | SDS7122E(V)          | 125MHz              |             |      |
| Ch                                 | nannel                             |                      | 2 + 1 (External)    |             |      |
|                                    | Mode                               | Normal,              | Peak detect,        | Averaging   |      |
|                                    |                                    | SDS5032E(V)          | Dual CH             | 125MS/s     |      |
|                                    |                                    | SDS3032E(V)          | Single CH           | 250MS/s     |      |
|                                    |                                    | SDS6063E(V)          | Dual CH             | 250MS/s     |      |
|                                    |                                    | SDS6062E(V)          | Single CH           | 500MS/s     |      |
| Acquisition                        | (real time)                        | CDC7070E(V)          | Dual CH             | 500MS/s     |      |
|                                    |                                    | SDS7072E(V)          | Single CH           | 1GS/s       |      |
|                                    |                                    | SDS7102E(V)          | Dual CH             | 500MS/s     |      |
|                                    |                                    |                      | Single CH           | 1GS/s       |      |
|                                    |                                    | SDS7122E(V)          | Dual CH             | 500MS/s     |      |
|                                    |                                    |                      | Single CH           | 1GS/s       |      |
|                                    | Input coupling                     | DC, A                | C, Ground           |             |      |
|                                    |                                    | SDS5032E(V)          | 1MΩ±2%,<br>10pF±5pF | in parallel | with |
|                                    | Input impedance  Probe attenuation | SDS6062E(V)          |                     |             |      |
|                                    |                                    | SDS7072E(V)          | 1MΩ±2%,             | in parallel | with |
| Input                              |                                    | SDS7102E(V)          | 15pF±3pF            |             |      |
|                                    |                                    | SDS7122E(V)          |                     |             |      |
|                                    |                                    |                      |                     |             |      |
|                                    | factor                             | 1X, 10X, 100X, 1000X |                     | 000X        |      |
|                                    | Max. input voltage                 | 400V (PK-PK) (       | DC + AC PK          | (-PK)       |      |

| Performance        | e Characteristics                   |   | Instruction                       | n                  |                  |
|--------------------|-------------------------------------|---|-----------------------------------|--------------------|------------------|
|                    | Channel –channel                    |   | 50Hz: 100 : 1                     |                    |                  |
|                    | isolation                           |   | 10MHz: 40                         | : 1                |                  |
|                    | Time delay between channel(typical) |   | 150ps                             |                    |                  |
|                    |                                     | 20MHz, full bar   | ndwidth                           |                    |                  |
|                    | Bandwidth limit                     | (Only SDS7102 this function)                              | 2E(V) and S                       | DS7122E            | E(V) have        |
|                    |                                     | SDS5032E(V)   | Dual CH                           | 5S/s~12            | 5MS/s            |
|                    |                                     | 3D33032E(V)   | Single CH                         | I 5S/s~250MS/s     |                  |
|                    |                                     | SDS6062E(V)   | Dual CH                           |                    | 250MS/s          |
|                    |                                     | 55500022(1)   | Single CH                         | 1                  | 500MS/s          |
|                    | Sampling rate range                 | SDS7072E(V)   | Dual CH                           | +                  | 500MS/s          |
|                    | Sumpring rave range                 | 22270722(1)   | Single CH                         | 0.5S/s~            |                  |
|                    |                                     | SDS7102E(V)   | Dual CH                           | +                  | 500MS/s          |
|                    |                                     | 55571022(1)   | Single CH                         | 0.5S/s~            |                  |
|                    |                                     | SDS7122E(V)   | Dual CH                           | 0.5S/s~            | 500MS/s          |
|                    |                                     | 5D57122E(V)   | Single CH                         | $0.5\mathrm{S/s}$  | ·1GS/s           |
|                    | Interpolation                       |   | (sin x)/x                         |                    |                  |
|                    |                                     | SDS5032E(V)   | Dual CH                           | ≤Max               | 1017             |
|                    |                                     |   | Single CH                         | sampling 10 rate   | 10K              |
| Horizontal         | Max Record length                   | SDS6062E(V)<br>SDS7072E(V)                                | Dual CH                           | ≤Max               | 100K<br>(can be  |
| System             |                                     | SDS7102E(V)<br>SDS7122E(V)                                | Single CH                         | - sampling<br>rate | upgraded to 10M) |
|                    |                                     | SDS5032E(V) 4ns/div~100s/div,<br>step by1~2~4             |                                   |                    |                  |
|                    | Scanning speed                      | SDS6062E(V)   |                                   |                    |                  |
|                    | (S/div)                             | SDS7072E(V)   | 2ns/div~100s/div,<br>step by1~2~5 |                    |                  |
|                    | (2, 52, )                           | SDS7102E(V)   |                                   |                    |                  |
|                    |                                     | SDS7122E(V)   |                                   |                    |                  |
|                    | Sampling rate / relay               |   |                                   |                    |                  |
|                    | time accuracy                       | ±100ppm   |                                   |                    |                  |
|                    | Interval(△T) accuracy               | Single:   |                                   |                    |                  |
|                    |                                     | ±(1 interval time+100ppm×reading+0.6ns);                  |                                   |                    |                  |
|                    |                                     |   |                                   |                    |                  |
|                    | (DC~100MHz)                         | Average>16:   |                                   |                    |                  |
|                    | (DC TOOMITE)                        | ±(1 interval time +100ppm×reading+0.4ns)                  |                                   |                    |                  |
| Vertical system    | A/D converter                       | O converter 8 bits resolution (2 Channels simultaneously) |                                   |                    |                  |
| ver iicai systeili | Sensitivity                         | SDS5032E(V)   | 5mV/div~5V                        | V/div              |                  |

| <b>Performance Characteristics</b> |                  |                  | Instruction                                     |  |  |
|------------------------------------|------------------|------------------|---|--|--|
|                                    |                  |                  | SDS6062E(V)                                     |  |  |
|                                    |                  |                  | SDS7072E(V)                                     | 2mV/div~10V/div  |  |
|                                    |                  |                  | SDS7102E(V)                                     | Zili v/div × 10 v/div  |  |
|                                    |                  |                  | SDS7122E(V)                                     |  |  |
|                                    |                  |                  | SDS5032E(V)                                     | $\pm 10 \mathrm{div}$  |  |
|                                    |                  |                  | SDS7102E(V)                                     |  |  |
|                                    | Displace         | ement            | SDS7122E(V)                                     | $\pm 1 \text{V} (2 \text{mV} \sim 100 \text{mV});$   |  |
|                                    |                  |                  | SDS6062E(V)                                     | $\pm 10 \text{V} (200 \text{mV} \sim 1 \text{V});$<br>$\pm 100 \text{V} (2 \text{V} \sim 10 \text{V})$ |  |
|                                    |                  |                  | SDS7072E(V)                                     | ±100 v (2 v × 10 v )   |  |
|                                    |                  |                  | SDS5032E(V)                                     | 30MHz  |  |
|                                    |                  |                  | SDS6062E(V)                                     | 60MHz  |  |
|                                    | Analog ba        | ndwidth          | SDS7072E(V)                                     | 70MHz  |  |
|                                    |                  |                  | SDS7102E(V)                                     | 100MHz   |  |
|                                    |                  |                  | SDS7122E(V)                                     | 125MHz   |  |
|                                    | Single bandwidth |                  |   | Full bandwidth   |  |
|                                    | Low Frequency    |                  | ≥10Hz (at                                       | input, AC coupling, -3dB)  |  |
|                                    |                  |                  | SDS5032E(V)                                     | ≤11ns (at input, Typical)  |  |
|                                    |                  |                  | SDS6062E(V)                                     | ≤5.8ns (at input, Typical)   |  |
|                                    | Rise t           | ime              | SDS7072E(V)                                     | ≤5.0ns (at input, Typical)   |  |
|                                    |                  |                  | SDS7102E(V)                                     | ≤3.5ns (at input, Typical)   |  |
|                                    |                  |                  | SDS7122E(V)                                     | ≤2.8ns (at input, Typical)   |  |
|                                    | DC accuracy      |                  |   | ±3%  |  |
|                                    | DC acc           | uracy            | Aviama da > 16.                                 | 1(20/ md = 1 0 05 div) for A   |  |
|                                    | (avera           | age)             | Average > 10.                                   | $\pm$ (3% rdg + 0.05 div) for $\triangle$  |  |
|                                    | Waveform i       | nverted O        | N/OFF   |  |  |
|                                    | Curs             | sor              | △V an   | nd △T between cursors  |  |
|                                    |                  |                  | PK-PK, Max, Min, Vtop, Vbase, Vamp, Mean        |  |  |
|                                    | A .              | - a <b>4</b> : - | Cycrms, Overshoot, Preshoot, Freq, Period,      |  |  |
|                                    | Auton            |                  | Rise Time, Fall Time, Delay A→B , Delay         |  |  |
|                                    |                  |                  | A→B <b>₹</b> , +D Width, -D Width, +Duty, -Duty |  |  |
| Measurement                        | Waveform Math    |                  | +, -,*,/,FFT                                    |  |  |
|                                    | Waveform         | Waveform storage |   | 15 waveforms   |  |
|                                    |                  | Bandwid<br>th    |   | Full bandwidth   |  |
|                                    | Lissajous        | Phase            |   |  |  |
|                                    | figure           | differenc        |   | ±3 degrees   |  |
|                                    |                  | e                |   |  |  |

| Performance Characteristics |                      | Instruction        |
|-----------------------------|----------------------|--------------------|
| Communication               | USB2.0, USB for file | storage; LAN port; |
| port                        | VGA port or RS-232 ( | Optional);         |

## Trigger:

| Performance Characteristics                 |  | Instruction  |
|---|--|--|
|   | Internal                                 | ±6 div from the screen center                          |
| Trigger level range                         | EXT                                      | ±600mV   |
|   | EXT/5                                    | ±3V  |
| Tricanland                                  | Internal                                 | ±0.3div  |
| Trigger level                               | EXT                                      | $\pm (40mV + 6\% \text{ of Set Value})$                |
| Accuracy (typical)                          | EXT/5                                    | ±(200mV +6% of Set Value)                              |
| Trigger<br>displacement                     | According to Record length and time base |  |
| Trigger Holdoff range                       | 100ns~10s                                |  |
| 50% level setting (typical)                 | Input signal frequency ≥50Hz             |  |
| Edge trigger                                | slope                                    | Rising, Falling  |
| Edge trigger                                | Sensitivity                              | 0.3div   |
| Pulse trigger                               | Trigger condition                        | Positive pulse: >, <, = negative pulse: >, <, =        |
|   | Pulse Width range                        | 30ns∼10s   |
|   | Modulation                               | Support standard NTSC, PAL and SECAM broadcast systems |
| Video Trigger                               | Line number range                        | 1-525 (NTSC) and 1-625 (PAL/SECAM)                     |
| Slope Trigger Condit                        |  | Positive pulse: >, <, = negative pulse: >, <, =        |
|   | Time setting                             | 24ns~10s   |
| Alternate Trigger                           | Trigger on CH1                           | Edge, Pulse, Video, Slope                              |
| (SDS5032E(V) does<br>not support Alternate) | Trigger on CH2                           | Edge, Pulse, Video, Slope                              |



## **General Technical Specifications**

### **Display**

| Display Type       | 8" Colored LCD (Liquid Crystal Display)  |
|--------------------|--|
| Display Resolution | 800 (Horizontal) × 600 (Vertical) Pixels |
| Display Colors     | 65536 colors, TFT screen                 |

#### **Output of the Probe Compensator**

| Output Voltage (Typical) | About 5V, with the Peak-to-Peak voltage $\geq 1M\Omega$ . |
|--------------------------|---|
| Frequency (Typical )     | Square wave of 1KHz                                       |

#### **Power**

| Mains Voltage     | 100∼240 VAC RMS, 50/60Hz, CAT II |
|-------------------|----------------------------------|
| Power Consumption | < 15W                            |
| Fuse              | 2A, T grade, 250V                |

#### **Environment**

| Tomoromotomo      | Working temperature: 0   |  |
|-------------------|--------------------------|--|
| Temperature       | Storage temperature: -20 |  |
| Relative Humidity | ≤ 90%                    |  |
| II ai ah t        | Operating: 3,000 m       |  |
| Height            | Non-operating: 15,000 m  |  |
| Cooling Method    | Natural convection       |  |

#### **Mechanical Specifications**

| Dimension | 348mm× 170mm×78mm (L*H*W) |
|-----------|---------------------------|
| Weight    | About 1.5 kg              |

#### **Interval Period of Adjustment:**

One year is recommended for the calibration interval period.

