

## ELIT3

## SE8000.1D1

3 1 channel SPL amplifier, optimized for 1 Ohm load

3 Class D Full Range / Full Bridge Technology

3 High power amplifier & small form factor

3 Great price vs performance ratio

Wersatile 12db / octave High pass filter & Low pass filter


3 4 Way Protection Circuit


3 Bass Level Remote including Clip Indicator


Product Specifications		
Power (1 ohm):	1x8000W RMS	
Power (2 ohm):	1x5000W RMS	
Power (4 ohm):	1x3000W RMS	
Power MAX:	16000W MAX	
S/N ratio:	100dB	
Freq. response:	15Hz - 10KHz	
HP filter:	15Hz - 1KHz	
LP filter:	60Hz - 10KHz	
Bass boost:	0-12 dB (50Hz)	
Voltage:	10.5V-15.5V DC	

Note! It's strongly recommended to have an additional power source/ battery placed within 2m from the amplifier to get maximum performance.













Minimum 12V+ cable	Recommended REM cable	Minimum GND cable	Recommended fuse rating
2 x 0 AWG / 2 x 50mm²	17-10 AWG / 1-6mm²	2 x 0 AWG / 2 x 50mm²	2x350 A