INSTRUCTION MANUAL

BluJax - ISBT32R Rev B

NOTE: Make sure you are parked in a safe spot before installation and whenever you are pairing your device. NEVER WHILE DRIVING.

1. Charge

- a. Charge your ISBT32R using the USB charging cable included.
- b. When connected to a USB power source, BT icon will glow red while charging. When charging is complete, red LED light will turn off.

2. Initial Pairing

- a. After charging your ISBT32R , unplug it from the USB cable.
- b. Enable your Bluetooth function on your smart device.
- c. Turn on ISBT32R by pushing and holding the Bluetooth button for 3 seconds. BT icon will be blinking red and blue. Power is on, and you are now in pairing mode...
- d. Open the Bluetooth menu on your smartphone, and scan for available Bluetooth accessories.
- e. Choose "ISBT32R" from the list, and select "Connect".
- f. When a successful connection has been established, LED light will change to a solid blue light.

TO PAIR ADDITIONAL DEVICES: 2 phones can be connected at the same time with only one playing music. You can toggle back and forth between both connected phones To do this turn off the Bluetooth on your first device and repeat steps b-f. NOTE: You can store up to 5 devices in the memory, but ISBT32R can only play two devices in tandem at the same time.

3. Let's go! Connect!

- a. Plug ISBT32R into the vehicle's AUX port.
- b. Select the AUX input source on your radio to enjoy your music.
- c. Use your phone to access your music.

4. Day to Day Operation

- Press "PLAY" button to play
- Press "PAUSE" button to pause
- Press "FORWARD" button to skip track
- ▶ Press "BACK" button to go back to beginning of track Double click to go back to previous track

Turning Off Your BluJax

To save battery life while not in use, press the control button for 3 seconds to turn off ISBT32R.

LED Indicator Guide

Paring mode: Flashing red and blue lights Steady blue light Paired: Low Battery: Flashing red light Charging: Steady red light Full battery: No light

Here is what you get





ISBT32R

3.5mm Extension Cable USB Charging Cable











isimple

INSTRUCTION MANUAL

isimple

BluJax - ISBT32R - Page 2

Auto Connect

ISBT32R will autoconnect when turned on after the first pairing but will only grab the last paired unit. It will not go down the list to find the next paired device.

Power Save Mode

If your smartphone is out of range for 5 minutes, ISBT32R will automatically turn off to preserve the battery power. When returning to the vehicle, press the control button once to wake BluJax up.

Battery Low

You can expect about 8 hours of playback from ISBT32R on a single charge. When ISBT32R is low, it will flash red, and say "Battery low, please charge."

For Pairing Multiple Devices (ISBT32R can store up to 5 paired smartphones in its memory)

- a. To pair an additional device, disconnect from the currently paired device by going into your smartphone's Bluetooth settings and clicking "Disconnect."
- b. ISBT32R can connect to 2 phones at the same time.
- c. If you have more than 5 devices, the oldest paired device will be erased when you pair with a new smartphone.
- d. Follow intial pairing instructions.

In Case of Tight Quarters

The 3.5mm jack on ISBT32R has been intentionally designed to be off-center so that it can be rotated to allow it to clear buttons or other obstructions located near your AUX input. If rotating ISBT32R is not allowing full insertion into the AUX input, we have provided a short extension cable which can be used to make the connection. Connect the extension cable between ISBT32R and the AUX input.

WARNING:

This equipment may be reset by unintentional electrostatic discharge during operation. Exposure to direct sunlight or extreme heat may cause damage or malfunction.

FCC Class B Radio Frequency Interference Statement This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

1. Re-orientate or relocate the receiving antenna.

2. Increase the separation between the equipment and receiver.

3. Connect the equipment into an outlet on a circuit different from that of which the receiver is connected.

4. Consult the dealer or an experienced radio / television technical for help.

Notice : The changes or modifications not expressly approved by the party responsible compliance could void the user authority to operate the equipment.

Tech Support: support@isimplesolutions.com 866-788-4237