

This guide is meant to help determine whether or not the EZ Lite Cruiser Charger will work in a specific country. As you may know, the shape of the outlets varies per country. The EZ Lite Cruiser Charger comes with a Plug Type for the 'USA', and if you intend to use it in any other country, you will need an Adapter to Change the Plug Shape.



Also, as you may know, the voltage output of an outlet varies per country. The EZ Lite Cruiser can work with voltages between 100 Volts all the way up to 240 Volts, at 50-60 Hz. If the voltage has the chance of spiking beyond 240 Volts, you must use a Surge Protector in countries where the Voltage is 240 Volts, or a Step Down Transformer to reduce the voltage back to 120 Volts to keep it a safe level for charging.

Continent/Country	Voltage	Frequency	Plug Type	Will Charger Work?	Need Adapter for Plug?	Need Transformer or Surge Protector?
North America						
Canada	120 V	60 HZ	USA	Yes	No	No
United States	120 V	60 HZ	USA	Yes	No	No
Mexico	120 V (127V)	60 HZ	USA	Yes	No	No

Europe						
<i>Note, the European Commission has mandated that all EU countries standardize to 230V -10% +6% (i.e. 207.0 V-243.8 V). Since this fits all of the old voltages listed below you can probably expect the following voltages to still apply.</i>						
Albania	220 V	50 HZ	Europe	Yes	Yes	No
Austria	230 V	50 HZ	Europe	Yes	Yes	No
Belgium	230 V	50 HZ	Europe	Yes	Yes	No
Belarus	220 V	50 HZ	Europe	Yes	Yes	No
Bulgaria	220 V	50 HZ	Europe	Yes	Yes	No
Croatia	220 V	50 HZ	Europe	Yes	Yes	No
Czech Republic	120-220 V	50 HZ	Europe	Yes	Yes	No
Denmark	230 V	50 HZ	Europe, Denmark	Yes	Yes	No
Estonia	220 V	50 HZ	Europe	Yes	Yes	No
Finland	230 V	50 HZ	Europe	Yes	Yes	No
France	230 V	50 HZ	Europe	Yes	Yes	No
Germany	230 V	50 HZ	Europe	Yes	Yes	No
Greece	220 V	50 HZ	Europe	Yes	Yes	No
Hungary	220 V	50 HZ	Europe	Yes	Yes	No
Iceland	220 V	50 HZ	Europe	Yes	Yes	No
Ireland	220 V	50 HZ	Europe, UK	Yes	Yes	No
Italy	230 V	50 HZ	Europe, Italy	Yes	Yes	No
Latvia	220 V	50 HZ	Europe	Yes	Yes	No
Lithuania	220 V	50 HZ	Europe	Yes	Yes	No
Luxembourg	230 V	50 HZ	Europe	Yes	Yes	No
Moldavia	220 V	50 HZ	Europe	Yes	Yes	No
Netherlands	230 V	50 HZ	Europe	Yes	Yes	No
Norway	230 V	50 HZ	Europe	Yes	Yes	No
Poland	220 V	50 HZ	Europe	Yes	Yes	No
Portugal	220 V	50 HZ	Europe	Yes	Yes	No
Romania	220 V	50 HZ	Europe	Yes	Yes	No
Russia	220 V	50 HZ	Europe	Yes	Yes	No
Slovakia	120-220 V	50 HZ	Europe	Yes	Yes	No
Slovenia	220 V	50 HZ	Europe	Yes	Yes	No
Spain	230 V	50 HZ	Europe	Yes	Yes	No
Sweden	230 V	50 HZ	Europe	Yes	Yes	No
Switzerland	230 V	50 HZ	Swiss	Yes	Yes	No
Ukraine	220 V	50 HZ	Europe	Yes	Yes	No
United Kingdom	240 V	50 HZ	UK	Yes	Yes	No, but Surge Protector is recommended
Yugoslavia	220 V	50 HZ	Europe	Yes	Yes	No

South America						
Argentina	230 V	50 HZ	Europe, Australia	Yes	Yes	No
Bolivia	110 V	50 HZ	USA	Yes	No	No
Brazil	110-127-220 V	60 HZ	Europe, USA	Yes	Only if using 'Europe' Type Socket	No

Chile	220 V	50 HZ	Europe, Italy	Yes	Yes	No
Colombia	110-220 V	50 HZ	USA	Yes	No	No
Ecuador	110-220 V	60 HZ	Europe, USA	Yes	Only if using 'Europe' Type Socket	No
French Guiana	220 V	50 HZ	Europe	Yes	Yes	No
Guyana	110-240 V	60 HZ	USA	Yes	No	No, but Surge Protector is recommended
Paraguay	220 V	60 HZ	Europe	Yes	Yes	No
Peru	220 V	60 HZ	Europe, USA	Yes	Only if using 'Europe' Type Socket	No
Surinam	110-127 V	60 HZ	Europe, USA	Yes	Only if using 'Europe' Type Socket	No
Uruguay	220 V	50 HZ	Europe	Yes	Yes	No
Venezuela	120-240 V	60 HZ	USA	Yes	No	No, but Surge Protector is recommended

Central America						
Bahamas	115 V	60 HZ	USA,UK	Yes	Only if using 'UK' Type Socket	No
Barbados	115 V	50 HZ	USA	Yes	No	No
Belize	110-220 V	60 HZ	USA	Yes	No	No
Bermuda	115 V	60 HZ	USA	Yes	No	No
Costa Rica	120 V	60 HZ	USA	Yes	No	No
Cuba	115-120 V	60 HZ	USA	Yes	No	No
Dominican Republic	110-220 V	60 HZ	USA	Yes	No	No
El Salvador	120-240 V	60 HZ	USA	Yes	No	No, but Surge Protector is recommended
Guatemala	115-230 V	60 HZ	USA	Yes	No	No
Haiti	110-220 V	60 HZ	USA	Yes	No	No
Honduras	110-220 V	60 HZ	USA	Yes	No	No
Jamaica	220 V	50 HZ	USA,UK	Yes	Only if using 'UK' Type Socket	No
Netherland Antilles	110-127 V	50 HZ	Europe, USA	Yes	Only if using 'Europe' Type Socket	No
Netherland Antilles -- Dutch (Sint Maartin)	110V	60Hz	USA	Yes	No	No
Netherland Antilles -- French (Saint Martin)	220V	60Hz	French	Yes	Yes	No
Netherland Antilles -- Curacao	110V	50Hz	USA	Yes	No	No
Netherland Antilles -- Curacao	220V	50Hz	Europe	Yes	Yes	No
Nicaragua	120 V	60 HZ	USA	Yes	No	No
Panama	120 V	60 HZ	USA	Yes	No	No
Puerto Rico	120 V	60 HZ	USA	Yes	No	No
Trinidad & Tobago	115-230 V	60 HZ	USA, UK	Yes	Only if using 'UK' Type Socket	No
Virgin Islands	120 V	60 HZ	USA	Yes	No	No

Africa						
Algeria	127-220 V	50 HZ	Europe	Yes	Yes	No
Angola	220 V	50 HZ	Europe	Yes	Yes	No
Benin	220 V	50 HZ	Europe	Yes	Yes	No
Botswana	220 V	50 HZ	UK	Yes	Yes	No
Burkina Faso	220 V	50 HZ	Europe	Yes	Yes	No
Burundi	220 V	50 HZ	Europe	Yes	Yes	No
Cameroon	127-220 V	50 HZ	Europe	Yes	Yes	No
Central Africa Rep.	220 V	50 HZ	Europe	Yes	Yes	No
Chad	220 V	50 HZ	Europe	Yes	Yes	No
Congo	220 V	50 HZ	Europe	Yes	Yes	No
Dahomey	220 V	50 HZ	Europe	Yes	Yes	No
Egypt	220 V	50 HZ	Europe, UK	Yes	Yes	No
Ethiopia	220 V	50 HZ	Europe, Italy	Yes	Yes	No
Gabon	220 V	50 HZ	Europe	Yes	Yes	No
Gambia	230 V	50 HZ	UK	Yes	Yes	No
Ghana	240 V	50 HZ	UK	Yes	Yes	No
Ivory Coast	220 V	50 HZ	Europe	Yes	Yes	No
Kenya	240 V	50 HZ	UK	Yes	Yes	No
Lesotho	230 V	60 HZ	UK	Yes	Yes	No
Liberia	120 V	60 HZ	Europe, USA	Yes	Only if using 'Europe' Type Socket	No
Libya	115-220 V	50 HZ	Europe, USA, UK	Yes	Only if using 'Europe' or 'UK' Type Socket	No

Malawi	230 V	50 HZ	UK	Yes	Yes	No
Mali	220 V	50 HZ	Europe	Yes	Yes	No
Mauritania	220 V	50 HZ	Europe	Yes	Yes	No
Mauritius	230 V	50 HZ	UK	Yes	Yes	No
Morocco	127-220 V	50 HZ	Europe	Yes	Yes	No
Mozambique	220 V	50 HZ	Europe	Yes	Yes	No
Namibia (Nambia)	220 V	50 HZ	South Africa	Yes	Yes	No
Niger	220 V	50 HZ	Europe	Yes	Yes	No
Nigeria	230 V	50 HZ	UK	Yes	Yes	No
Rwanda	220 V	50 HZ	Europe	Yes	Yes	No
Senegal	110 V	50 HZ	Europe	Yes	Yes	No
Sierra Leone	230 V	50 HZ	UK	Yes	Yes	No
Somalia	220 V	50 HZ	Europe	Yes	Yes	No
South Africa	220-240 V	50 HZ	South Africa	Yes	Yes	No
Sudan	240V	50 HZ	UK	Yes	Yes	No
Swaziland	220 V	50 HZ	UK	Yes	Yes	No
Tanzania	230 V	50 HZ	UK	Yes	Yes	No
Togo	127-220 V	50 HZ	Europe	Yes	Yes	No
Tunisia	127-220 V	50 HZ	Europe	Yes	Yes	No
Uganda	240 V	50 HZ	UK	Yes	Yes	No
Zaire	220 V	50 HZ	Europe	Yes	Yes	No
Zambia	220 V	50 HZ	UK	Yes	Yes	No
Zimbabwe	220 V	50 HZ	UK	Yes	Yes	No

Australia, Oceania						
Australia	240 V	50 HZ	Australia	Yes	Yes	No, but Surge Protector is recommended
Fiji Islands	240 V	50 HZ	Australia	Yes	Yes	No, but Surge Protector is recommended
New Zealand	230 V	50 HZ	Australia	Yes	Yes	No
Solomon Island	240 V	50 HZ	Australia	Yes	Yes	No, but Surge Protector is recommended
Tonga	230 V	50 HZ	Australia	Yes	Yes	No

Asia						
Abu Dhabi	230 V	50 HZ	UK	Yes	Yes	No
Afghanistan	220 V	50 HZ	Europe	Yes	Yes	No
Armenia	220 V	50 HZ	Europe	Yes	Yes	No
Azerbaijan	220 V	50 HZ	Europe	Yes	Yes	No
Bahrain	110-230 V	50 HZ, 60 HZ	USA, UK	Yes	Only if using 'UK' Type Socket	No
Bangladesh	230 V	50 HZ	UK	Yes	Yes	No
Brunei	240 V	50 HZ	UK	Yes	Yes	No, but Surge Protector is recommended
Cambodia	220 V	50 HZ	Europe, USA	Yes	Only if using 'Europe' Type Socket	No
China	220 V	50 HZ	USA, Australia	Yes	Only is using 'Australia' Type Socket	No
Cyprus	240 V	50 HZ	UK	Yes	Yes	No, but Surge Protector is recommended
Georgia	220 V	50 HZ	Europe	Yes	Yes	No
Hong Kong	220 V	50 HZ	UK	Yes	Yes	No
India	230-250 V	50 HZ, 60 HZ	UK	Yes*	Yes	Yes, you must use a Step Down Transformer.
Indonesia	127-220 V	50 HZ	Europe	Yes	Yes	No
Iran	220 V	50 HZ	Europe	Yes	Yes	No
Iraq	220 V	50 HZ	Europe, UK	Yes	Yes	No
Israel	230 V	50 HZ	Israel	Yes	Yes	No
Japan	100 V	50 HZ, 60 HZ	USA	Yes	No	No
Jordan	220 V	50 HZ	USA, UK	Yes	Only if using 'UK' Type Socket	No
Kazakhstan	220 V	50 HZ	Europe	Yes	Yes	No
Kirgizstan	220 V	50 HZ	Europe	Yes	Yes	No
Korea (North)	220 V	50 HZ	Europe	Yes	Yes	No
Korea (South)	110-220 V	60 HZ	Europe, USA	Yes	Only if using 'Europe' Type Socket	No
Kuwait	240 V	50 HZ	UK	Yes	Yes	No, but Surge Protector is recommended
Laos	220 V	50 HZ	Europe, USA	Yes	Only if using 'Europe' Type Socket	No

Lebanon	110-220 V	50 HZ	Europe, UK	Yes	Yes	No
Malaysia	240 V	50 HZ	UK	Yes	Yes	No, but Surge Protector is recommended
Myanmar	240 V	50 HZ	UK	Yes	Yes	No, but Surge Protector is recommended
Oman	240 V	50 HZ	USA, UK	Yes	Only if using 'UK' Type Socket	No, but Surge Protector is recommended
Pakistan	230 V	50 HZ	UK	Yes	Yes	No
Philippines	110-220 V	60 HZ	USA	Yes	No	No
Qatar	240 V	50 HZ	UK	Yes	Yes	No, but Surge Protector is recommended
Saudi Arabia	127-220 V	60 HZ	Europe, USA, UK	Yes	Only if using 'Europe' or 'UK' Type Socket	No
Singapore	230 V	50 HZ	UK	Yes	Yes	No
Sri Lanka	230 V	50 HZ	UK	Yes	Yes	No
Syria	220 V	50 HZ	Europe	Yes	Yes	No
Taiwan	110-220 V	60 HZ	USA	Yes	No	No
Tajikistan	220 V	50 HZ	Europe	Yes	Yes	No
Thailand	220 V	50 HZ	USA	Yes	No	No
Turkey	220 V	50 HZ	Europe	Yes	Yes	No
Turkmenistan	220 V	50 HZ	Europe	Yes	Yes	No
United Arab Emirates	220 V	50 HZ	UK	Yes	Yes	No
Uzbekistan	220 V	50 HZ	Europe	Yes	Yes	No
Vietnam	120-220 V	50 HZ	Europe, UK	Yes	Yes	No
Yemen	220 V	50 HZ	UK	Yes	Yes	No